

FERC rendition of the electronically filed tariff records in Docket No. **ER25-02571-000**

Filing Data:

CID	Filing Title	Company Filing Identifier	Type of Filing Code	Associated Filing Identifier
C001552	SR Stockton I LGIA Filing	1028	10	
	Tariff Title	Tariff ID	Payment Confirmation	Suspension Motion
	OATT Associated Service Agreements 2	8		

Tariff Record Data:

Record Content Description	Service Agreement No. 842
Tariff Record Title	SR Stockton I LGIA
Record Version Number	0.0.0
Option Code	A
Record Narrative Name	
Tariff Record ID	3765
Tariff Record Collation Value	283115520
Tariff Record Parent Identifier	0
Proposed Date	2025-06-06
Priority Order	1000000000
Record Change Type	NEW
Record Content Type	1
Associated Filing Identifier	

SERVICE AGREEMENT NO. 842

**STANDARD LARGE GENERATOR
INTERCONNECTION AGREEMENT (LGIA)**

BY AND BETWEEN

SR STOCKTON I, LLC

AND

**SOUTHERN COMPANY SERVICES, INC.,
AS AGENT FOR
ALABAMA POWER COMPANY,
GEORGIA POWER COMPANY, AND
MISSISSIPPI POWER COMPANY**

FOR

SR STOCKTON I (24C-IC-1224)

Effective Date:

6/6/2025

Tariff Record Data:

Record Content Description	Table of Contents
Tariff Record Title	
Record Version Number	0.0.0
Option Code	A
Record Narrative Name	
Tariff Record ID	3818
Tariff Record Collation Value	283123712
Tariff Record Parent Identifier	3765
Proposed Date	2025-06-06
Priority Order	1000000000
Record Change Type	NEW
Record Content Type	1
Associated Filing Identifier	

TABLE OF CONTENTS

	Page
Recitals.....	1
Article 1. Definitions.....	1
Article 2. Effective Date, Term, and Termination.....	11
2.1 Effective Date.....	11
2.2 Term of Agreement.....	11
2.3 Termination Procedures.....	11
2.3.1 Written Notice.....	11
2.3.2 Default.....	11
2.4 Termination Costs.....	11
2.5 Disconnection.....	12
2.6 Survival.....	12
Article 3. Regulatory Filings.....	13
3.1 Filing	13
Article 4. Scope of Service.....	13
4.1 Interconnection Product Options.....	13
4.1.1 Energy Resource Interconnection Service.....	13
4.1.1.1 The Product.....	13
4.1.1.2 Transmission Delivery Service Implications.....	13
4.1.2 Network Resource Interconnection Service.....	14
4.1.2.1 The Product.....	14
4.1.2.2 Transmission Delivery Service Implications.....	14
4.2 Provision of Service.....	16
4.3 Performance Standards.....	16
4.4 No Transmission Delivery Service.....	16
4.5 Interconnection Customer Provided Services.....	16
Article 5. Interconnection Facilities Engineering, Procurement, and Construction....	16
5.1 Options.....	16
5.1.1 Standard Option.....	16
5.1.2 Alternate Option.....	17
5.1.3 Option to Build.....	17
5.1.4 Negotiated Option.....	18
5.2 General Conditions Applicable to Option to Build.....	18
5.3 Liquidated Damages.....	19
5.4 Power System Stabilizers.....	20
5.5 Equipment Procurement.....	20
5.6 Construction Commencement.....	21
5.7 Work Progress.....	21
5.8 Information Exchange.....	21

5.9	Other Interconnection Options.....	22
5.9.1	Limited Operation.....	22
5.9.2	Provisional Interconnection Service.....	22
5.10	Interconnection Customer's Interconnection Facilities ('ICIF').....	23
5.10.1	Interconnection Customer's Interconnection Facility Specifications.....	23
5.10.2	Transmission Provider's Review.....	23
5.10.3	ICIF Construction.....	23
5.11	Transmission Provider's Interconnection Facilities Construction.....	24
5.12	Access Rights.....	24
5.13	Lands of Other Property Owners.....	24
5.14	Permits.....	24
5.15	Early Construction of Base Case Facilities.....	25
5.16	Suspension.....	25
5.17	Taxes	25
5.17.1	Interconnection Customer Payments Not Taxable.....	25
5.17.2	Representations and Covenants.....	26
5.17.3	Indemnification for the Cost Consequences of Current Tax Liability Imposed Upon Transmission Provider.....	26
5.17.4	Tax Gross-Up Amount.....	27
5.17.5	Private Letter Ruling or Change or Clarification of Law.....	28
5.17.6	Subsequent Taxable Events.....	28
5.17.7	Contests.....	28
5.17.8	Refund.....	29
5.17.9	Taxes Other Than Income Taxes.....	30
5.17.10	Transmission Owners Who Are Not Transmission Providers.....	31
5.18	Tax Status.....	31
5.19	Modification.....	31
5.19.1	General.....	31
5.19.2	Standards.....	32
5.19.3	Modification Costs.....	32
Article 6.	Testing and Inspection.....	32
6.1	Pre-Commercial Operation Date Testing and Modifications.....	32
6.2	Post-Commercial Operation Date Testing and Modifications.....	32
6.3	Right to Observe Testing.....	32
6.4	Right to Inspect.....	32
Article 7. Metering	33	
7.1	General.....	33
7.2	Check Meters.....	33
7.3	Standards.....	33
7.4	Testing of Metering Equipment.....	33
7.5	Metering Data.....	34
Article 8. Communications.....	34	
8.1	Interconnection Customer Obligations.....	34
8.2	Remote Terminal Unit.....	34

8.3	No Annexation.....	35
8.4	Provision of Data from a Variable Energy Resource.....	35
Article 9.	Operations.....	35
9.1	General.....	35
9.2	Balancing Authority Area Notification.....	36
9.3	Transmission Provider Obligations.....	35
9.4	Interconnection Customer Obligations.....	36
9.5	Start-Up Synchronization and Commercial Operation.....	36
9.6	Reactive Power and Primary Frequency Response.....	36
9.6.1	Power Factor Design Criteria.....	36
9.6.1.1	Synchronous Generation.....	36
9.6.1.2	Non-Synchronous Generation.....	37
9.6.2	Voltage Schedules.....	37
9.6.2.1	Voltage Regulators.....	37
9.6.3	Payment for Reactive Power.....	38
9.6.4	Primary Frequency Response.....	38
9.6.4.1	Governor or Equivalent Controls.....	39
9.6.4.2	Timely and Sustained Response.....	39
9.6.4.3	Exemptions.....	40
9.6.4.4	Electric Storage Resources.....	40
9.7	Outages and Interruptions.....	41
9.7.1	Outages.....	41
9.7.1.1	Outage Authority and Coordination.....	41
9.7.1.2	Outage Schedules.....	41
9.7.1.3	Outage Restoration.....	42
9.7.2	Interruption of Service.....	42
9.7.3	Ride Through Capability and Performance.....	43
9.7.4	System Protection and Other Control Requirements.....	44
9.7.4.1	System Protection Facilities.....	44
9.7.5	Requirements for Protection.....	45
9.7.6	Power Quality.....	45
9.8	Switching and Tagging Rules.....	45
9.9	Use of Interconnection Facilities by Third Parties.....	45
9.9.1	Purpose of Interconnection Facilities.....	45
9.9.2	Third Party Users.....	46
9.10	Disturbance Analysis Data Exchange.....	46
Article 10.	Maintenance.....	46
10.1	Transmission Provider Obligations.....	46
10.2	Interconnection Customer Obligations.....	46
10.3	Coordination.....	46
10.4	Secondary Systems.....	46
10.5	Operating and Maintenance Expenses.....	47

Article 11. Performance Obligation.....	47
11.1 Interconnection Customer Interconnection Facilities.....	47
11.2 Transmission Provider's Interconnection Facilities.....	47
11.3 Network Upgrades and Distribution Upgrades.....	47
11.4 Transmission Credits.....	47
11.4.1 Repayment of Amounts Advanced for Network Upgrades.....	47
11.4.2 Special Provisions for Affected Systems.....	48
11.5 Provision of Security.....	49
11.6 Interconnection Customer Compensation.....	49
11.6.1 Interconnection Customer Compensation for Actions During Emergency Condition.....	50
Article 12. Invoice.....	50
12.1 General.....	50
12.2 Final Invoice.....	50
12.3 Payment.....	50
12.4 Disputes.....	50
Article 13. Emergencies.....	51
13.1 Definition.....	51
13.2 Obligations.....	51
13.3 Notice	51
13.4 Immediate Action.....	51
13.5 Transmission Provider Authority.....	52
13.5.1 General.....	52
13.5.2 Reduction and Disconnection.....	52
13.6 Interconnection Customer Authority.....	53
13.7 Limited Liability.....	53
Article 14. Regulatory Requirements and Governing Law.....	53
14.1 Regulatory Requirements.....	53
14.2 Governing Law.....	53
Article 15. Notices.....	54
15.1 General.....	54
15.2 Billings and Payments.....	54
15.3 Alternative Forms of Notice.....	54
15.4 Operations and Maintenance Notice.....	54
Article 16. Force Majeure.....	54
16.1 Force Majeure.....	54
Article 17. Default.....	55
17.1 Default.....	55
17.1.1 General.....	55
17.1.2 Right to Terminate.....	55

Article 18.	Indemnity, Consequential Damages and Insurance.....	55
18.1	Indemnity.....	55
	18.1.1 Indemnified Person.....	56
	18.1.2 Indemnifying Party.....	56
	18.1.3 Indemnity Procedures.....	56
18.2	Consequential Damages.....	57
18.3	Insurance.....	57
Article 19.	Assignment.....	59
19.1	Assignment.....	59
Article 20.	Severability.....	60
20.1	Severability.....	60
Article 21.	Comparability.....	60
21.1	Comparability.....	60
Article 22.	Confidentiality.....	60
22.1	Confidentiality.....	60
	22.1.1 Term.....	61
	22.1.2 Scope.....	61
	22.1.3 Release of Confidential Information.....	61
	22.1.4 Rights.....	61
	22.1.5 No Warranties.....	62
	22.1.6 Standard of Care.....	62
	22.1.7 Order of Disclosure.....	62
	22.1.8 Termination of Agreement.....	62
	22.1.9 Remedies.....	63
	22.1.10 Disclosure to FERC, its Staff, or a State.....	63
Article 23.	Environmental Releases.....	64
Article 24.	Information Requirements.....	64
24.1	Information Acquisition.....	64
24.2	Information Submission by Transmission Provider.....	64
24.3	Updated Information Submission by Interconnection Customer.....	65
24.4	Information Supplementation.....	65
Article 25.	Information Access and Audit Rights.....	66
25.1	Information Access.....	66
25.2	Reporting of Non-Force Majeure Events.....	66
25.3	Audit Rights.....	66
25.4	Audit Rights Periods.....	67
	25.4.1 Audit Rights Period for Construction-Related Accounts and Records.....	67
	25.4.2 Audit Rights Period for All Other Accounts and Records.....	67
25.5	Audit Results.....	67

Article 26.	Subcontractors.....	67
26.1	General.....	67
26.2	Responsibility of Principal.....	67
26.3	No Limitation by Insurance.....	67
Article 27.	Disputes.....	68
27.1	Submission.....	68
27.2	External Arbitration Procedures.....	68
27.3	Arbitration Decisions.....	68
27.4	Costs	69
Article 28.	Representations, Warranties, and Covenants.....	69
28.1	General.....	69
28.1.1	Good Standing.....	69
28.1.2	Authority.....	69
28.1.3	No Conflict.....	69
28.1.4	Consent and Approval.....	69
Article 29.	Joint Operating Committee.....	70
29.1	Joint Operating Committee.....	70
Article 30.	Miscellaneous.....	70
30.1	Binding Effect.....	70
30.2	Conflicts.....	71
30.3	Rules of Interpretation.....	71
30.4	Entire Agreement.....	71
30.5	No Third Party Beneficiaries.....	71
30.6	Waiver	71
30.7	Headings.....	72
30.8	Multiple Counterparts.....	72
30.9	Amendment.....	72
30.10	Modification by the Parties.....	72
30.11	Reservation of Rights.....	72
30.12	No Partnership.....	72

Appendix A - Interconnection Facilities, Network Upgrades, and Distribution Upgrades

Appendix B – Milestones

Appendix C – Interconnection Details

Appendix D – Security Arrangements Details

Appendix E – Commercial Operation Date

Appendix F – Addresses for Delivery of Notices and Billings

Appendix G – Interconnection Requirements for a Wind Generating Plant

Tariff Record Data:

Record Content Description	LGIA
Tariff Record Title	
Record Version Number	0.0.0
Option Code	A
Record Narrative Name	
Tariff Record ID	3819
Tariff Record Collation Value	283131904
Tariff Record Parent Identifier	3765
Proposed Date	2025-06-06
Priority Order	1000000000
Record Change Type	NEW
Record Content Type	1
Associated Filing Identifier	

STANDARD LARGE GENERATOR INTERCONNECTION AGREEMENT

THIS STANDARD LARGE GENERATOR INTERCONNECTION AGREEMENT (“Agreement”) is made and entered into as of 6/6/2025, by and between SR Stockton I, LLC, a limited liability company organized and existing under the laws of the State of Delaware (“Interconnection Customer” with a Large Generating Facility), and Southern Company Services, Inc., a corporation organized and existing under the laws of the State of Alabama, as agent for Alabama Power Company, Georgia Power Company, and Mississippi Power Company (collectively referred to as “Transmission Provider”, “Transmission Owner” and/or “Southern Companies”). Interconnection Customer and Transmission Provider each may be referred to as a “Party” or collectively as the “Parties.”

Recitals

WHEREAS, Transmission Provider operates the Transmission System; and

WHEREAS, Interconnection Customer intends to own, lease and/or control and operate the Generating Facility identified as a Large Generating Facility in Appendix C to this Agreement; and,

WHEREAS, Interconnection Customer and Transmission Provider have agreed to enter into this Agreement for the purpose of interconnecting the Large Generating Facility with the Transmission System;

NOW, THEREFORE, in consideration of and subject to the mutual covenants contained herein, it is agreed:

When used in this Standard Large Generator Interconnection Agreement, terms with initial capitalization that are not defined in Article 1 shall have the meanings specified in the Article in which they are used or the Open Access Transmission Tariff (Tariff).

Article 1. Definitions

Adverse System Impact shall mean the negative effects due to technical or operational limits on conductors or equipment being exceeded that may compromise the safety and reliability of the electric system.

Affected System shall mean an electric system other than Transmission Provider’s Transmission System that may be affected by the proposed interconnection.

Affected System Operator shall mean the entity that operates an Affected System.

Affiliate shall mean, with respect to a corporation, partnership or other entity, each such

other corporation, partnership or other entity that directly or indirectly, through one or more intermediaries, controls, is controlled by, or is under common control with, such corporation, partnership or other entity.

Ancillary Services shall mean those services that are necessary to support the transmission of capacity and energy from resources to loads while maintaining reliable operation of Transmission Provider's Transmission System in accordance with Good Utility Practice.

Applicable Laws and Regulations shall mean all duly promulgated applicable federal, state and local laws, regulations, rules, ordinances, codes, decrees, judgments, directives, or judicial or administrative orders, permits and other duly authorized actions of any Governmental Authority.

Applicable Reliability Standards shall mean the requirements and guidelines of the Electric Reliability Organization and the Balancing Authority Area of the Transmission System to which the Generating Facility is directly interconnected.

Balancing Authority shall mean an entity that integrates resource plans ahead of time, maintains demand and resource balance within a Balancing Authority Area, and supports interconnection frequency in real time.

Balancing Authority Area shall mean the collection of generation, transmission, and loads within the metered boundaries of the Balancing Authority. The Balancing Authority maintains load-resource balance within this area.

Base Case shall mean the base case power flow, short circuit, and stability data bases used for the Interconnection Studies by Transmission Provider or Interconnection Customer.

Breach shall mean the failure of a Party to perform or observe any material term or condition of the Standard Large Generator Interconnection Agreement.

Breaching Party shall mean a Party that is in Breach of the Standard Large Generator Interconnection Agreement.

Business Day shall mean Monday through Friday, excluding Federal Holidays.

Calendar Day shall mean any day including Saturday, Sunday or a Federal Holiday.

Cluster shall mean a group of one or more Interconnection Requests that are studied together for the purpose of conducting a Cluster Study.

Cluster Restudy shall mean a restudy of a Cluster Study conducted pursuant to Section 7.5 of the LGIP.

Cluster Study shall mean the evaluation of one or more Interconnection Requests within a Cluster as described in Section 7 of the LGIP.

Clustering shall mean the process whereby one or more Interconnection Requests are studied together, instead of serially, as described in Section 7 of the LGIP.

Commercial Operation shall mean the status of a Generating Facility that has commenced generating electricity for sale, excluding electricity generated during Trial Operation.

Commercial Operation Date of a unit shall mean the date on which the Generating Facility commences Commercial Operation as agreed to by the Parties pursuant to Appendix E to the Standard Large Generator Interconnection Agreement.

Confidential Information shall mean any confidential, proprietary or trade secret information of a plan, specification, pattern, procedure, design, device, list, concept, policy or compilation relating to the present or planned business of a Party, which is designated as confidential by the Party supplying the information, whether conveyed orally, electronically, in writing, through inspection, or otherwise.

Contingent Facilities shall mean those unbuilt Interconnection Facilities and Network Upgrades upon which the Interconnection Request's costs, timing, and study findings are dependent, and if delayed or not built, could cause a need for restudies of the Interconnection Request or a reassessment of the Interconnection Facilities and/or Network Upgrades and/or costs and timing.

Default shall mean the failure of a Breaching Party to cure its Breach in accordance with Article 17 of the Standard Large Generator Interconnection Agreement.

Dispute Resolution shall mean the procedure for resolution of a dispute between the Parties in which they will first attempt to resolve the dispute on an informal basis.

Distribution System shall mean Transmission Provider's facilities and equipment used to transmit electricity to ultimate usage points such as homes and industries directly from nearby generators or from interchanges with higher voltage transmission networks which transport bulk power over longer distances. The voltage levels at which distribution systems operate differ among areas.

Distribution Upgrades shall mean the additions, modifications, and upgrades to Transmission Provider's Distribution System at or beyond the Point of Interconnection to facilitate interconnection of the Generating Facility and render the transmission service necessary to effect Interconnection Customer's wholesale sale of electricity in interstate commerce. Distribution Upgrades do not include Interconnection Facilities.

Effective Date shall mean the date on which the Standard Large Generator Interconnection Agreement becomes effective upon execution by the Parties subject to acceptance by FERC, or if filed unexecuted, upon the date specified by FERC.

Electric Reliability Organization shall mean the North American Electric Reliability Corporation (NERC) or its successor organization.

Emergency Condition shall mean a condition or situation: (1) that in the judgment of the Party making the claim is imminently likely to endanger life or property; or (2) that, in the case of a Transmission Provider, is imminently likely (as determined in a non-discriminatory manner) to cause a material adverse effect on the security of, or damage to Transmission Provider's Transmission System, Transmission Provider's Interconnection Facilities or the electric systems of others to which Transmission Provider's Transmission System is directly connected; or (3) that, in the case of Interconnection Customer, is imminently likely (as determined in a non-discriminatory manner) to cause a material adverse effect on the security of, or damage to, the Generating Facility or Interconnection Customer's Interconnection Facilities. System restoration and black start shall be considered Emergency Conditions; provided, that Interconnection Customer is not obligated by the Standard Large Generator Interconnection Agreement to possess black start capability.

Energy Resource Interconnection Service shall mean an Interconnection Service that allows Interconnection Customer to connect its Generating Facility to Transmission Provider's Transmission System to be eligible to deliver the Generating Facility's electric output using the existing firm or nonfirm capacity of Transmission Provider's Transmission System on an as available basis. Energy Resource Interconnection Service in and of itself does not convey transmission service.

Engineering & Procurement (E&P) Agreement shall mean an agreement that authorizes Transmission Provider to begin engineering and procurement of long lead-time items necessary for the establishment of the interconnection in order to advance the implementation of the Interconnection Request.

Environmental Law shall mean Applicable Laws or Regulations relating to pollution or protection of the environment or natural resources.

Federal Power Act shall mean the Federal Power Act, as amended, 16 U.S.C. §§ 791a et seq.

FERC shall mean the Federal Energy Regulatory Commission (Commission) or its successor.

Force Majeure shall mean any act of God, labor disturbance, act of the public enemy, war, insurrection, riot, fire, storm or flood, explosion, breakage or accident to machinery or equipment, any order, regulation or restriction imposed by governmental, military or lawfully established civilian authorities, or any other cause beyond a Party's control. A Force Majeure event does not include acts of negligence or intentional wrongdoing by the Party claiming Force Majeure.

Generating Facility shall mean Interconnection Customer's device(s) for the production and/or storage for later injection of electricity identified in the Interconnection Request, but shall

not include Interconnection Customer's Interconnection Facilities.

Generating Facility Capacity shall mean the net capacity of the Generating Facility or the aggregate net capacity of the Generating Facility where it includes more than one device for the production and/or storage for later injection of electricity.

Good Utility Practice shall mean any of the practices, methods and acts engaged in or approved by a significant portion of the electric industry during the relevant time period, or any of the practices, methods and acts which, in the exercise of reasonable judgment in light of the facts known at the time the decision was made, could have been expected to accomplish the desired result at a reasonable cost consistent with good business practices, reliability, safety and expedition. Good Utility Practice is not intended to be limited to the optimum practice, method, or act to the exclusion of all others, but rather to be acceptable practices, methods, or acts generally accepted in the region.

Governmental Authority shall mean any federal, state, local or other governmental regulatory or administrative agency, court, commission, department, board, or other governmental subdivision, legislature, rulemaking board, tribunal, or other governmental authority having jurisdiction over the Parties, their respective facilities, or the respective services they provide, and exercising or entitled to exercise any administrative, executive, police, or taxing authority or power; provided, however, that such term does not include Interconnection Customer, Transmission Provider, or any Affiliate thereof.

Hazardous Substances shall mean any chemicals, materials or substances defined as or included in the definition of "hazardous substances," "hazardous wastes," "hazardous materials," "hazardous constituents," "restricted hazardous materials," "extremely hazardous substances," "toxic substances," "radioactive substances," "contaminants," "pollutants," "toxic pollutants" or words of similar meaning and regulatory effect under any applicable Environmental Law, or any other chemical, material or substance, exposure to which is prohibited, limited or regulated by any applicable Environmental Law.

Initial Synchronization Date shall mean the date upon which the Generating Facility is initially synchronized and upon which Trial Operation begins.

In-Service Date shall mean the date upon which Interconnection Customer reasonably expects it will be ready to begin use of Transmission Provider's Interconnection Facilities to obtain back feed power.

Interconnection Customer shall mean any entity, including Transmission Provider, Transmission Owner or any of the Affiliates or subsidiaries of either, that proposes to interconnect its Generating Facility with Transmission Provider's Transmission System.

Interconnection Customer's Interconnection Facilities shall mean all facilities and equipment, as identified in Appendix A of the Standard Large Generator Interconnection Agreement, that are located between the Generating Facility and the Point of Change of Ownership, including any modification, addition, or upgrades to such facilities and equipment necessary to physically and electrically interconnect the Generating Facility to Transmission

Provider's Transmission System. Interconnection Customer's Interconnection Facilities are sole use facilities.

Interconnection Facilities shall mean Transmission Provider's Interconnection Facilities and Interconnection Customer's Interconnection Facilities. Collectively, Interconnection Facilities include all facilities and equipment between the Generating Facility and the Point of Interconnection, including any modification, additions or upgrades that are necessary to physically and electrically interconnect the Generating Facility to Transmission Provider's Transmission System. Interconnection Facilities are sole use facilities and shall not include Distribution Upgrades, Stand Alone Network Upgrades or Network Upgrades.

Interconnection Facilities Study shall mean a study conducted by Transmission Provider or a third party consultant for Interconnection Customer to determine a list of facilities (including Transmission Provider's Interconnection Facilities and Network Upgrades as identified in the Cluster Study), the cost of those facilities, and the time required to interconnect the Generating Facility with Transmission Provider's Transmission System. The scope of the study is defined in Section 8 of the LGIP.

Interconnection Facilities Study Agreement shall mean the form of agreement contained in Appendix 3 of the LGIP for conducting the Interconnection Facilities Study.

Interconnection Request shall mean an Interconnection Customer's request, in the form of Appendix 1 to the LGIP, in accordance with the Tariff, to interconnect a new Generating Facility, or to increase the capacity of, or make a Material Modification to the operating characteristics of, an existing Generating Facility that is interconnected with Transmission Provider's Transmission System.

Interconnection Service shall mean the service provided by Transmission Provider associated with interconnecting Interconnection Customer's Generating Facility to Transmission Provider's Transmission System and enabling it to receive electric energy and capacity from the Generating Facility at the Point of Interconnection, pursuant to the terms of the Standard Large Generator Interconnection Agreement and, if applicable, Transmission Provider's Tariff.

Interconnection Study shall mean any of the following studies: the Cluster Study, the Cluster Restudy, the Surplus Interconnection Service Study, the Interconnection Facilities Study, the Affected System Study, Optional Interconnection Study, and Material Modification assessment, described in the LGIP.

IRS shall mean the Internal Revenue Service.

Joint Operating Committee shall be a group made up of representatives from Interconnection Customers and Transmission Provider to coordinate operating and technical considerations of Interconnection Service.

Large Generating Facility shall mean a Generating Facility having a Generating Facility Capacity of more than 20 MW.

LGIA Deposit shall mean the deposit Interconnection Customer submits when returning the executed LGIA, or within ten (10) Business Days of requesting that the LGIA be filed unexecuted at the Commission, in accordance with Section 11.3 of the LGIP.

Loss shall mean any and all losses relating to injury to or death of any person or damage to property, demand, suits, recoveries, costs and expenses, court costs, attorney fees, and all other obligations by or to third parties, arising out of or resulting from the other Party's performance, or non-performance of its obligations under the Standard Large Generator Interconnection Agreement on behalf of the Indemnifying Party, except in cases of gross negligence or intentional wrongdoing by the Indemnifying Party.

Material Modification shall mean those modifications that have a material impact on the cost or timing of any Interconnection Request with an equal or later Queue Position.

Metering Equipment shall mean all metering equipment installed or to be installed at the Generating Facility pursuant to the Standard Large Generator Interconnection Agreement at the metering points, including but not limited to instrument transformers, MWh-meters, data acquisition equipment, transducers, remote terminal unit, communications equipment, phone lines, and fiber optics.

Network Resource shall mean any designated generating resource owned, purchased, or leased by a Network Customer under the Network Integration Transmission Service Tariff. Network Resources do not include any resource, or any portion thereof, that is committed for sale to third parties or otherwise cannot be called upon to meet the Network Customer's Network Load on a non-interruptible basis.

Network Resource Interconnection Service shall mean an Interconnection Service that allows Interconnection Customer to integrate its Large Generating Facility with Transmission Provider's Transmission System (1) in a manner comparable to that in which Transmission Provider integrates its generating facilities to serve native load customers; or (2) in an RTO or ISO with market based congestion management, in the same manner as Network Resources. Network Resource Interconnection Service in and of itself does not convey transmission service.

Network Upgrades shall mean the additions, modifications, and upgrades to Transmission Provider's Transmission System required at or beyond the point at which the Interconnection Facilities connect to Transmission Provider's Transmission System to accommodate the interconnection of the Large Generating Facility to Transmission Provider's Transmission System.

Notice of Dispute shall mean a written notice of a dispute or claim that arises out of or in connection with the Standard Large Generator Interconnection Agreement or its performance.

Optional Interconnection Study shall mean a sensitivity analysis based on assumptions specified by Interconnection Customer in the Optional Interconnection Study Agreement.

Optional Interconnection Study Agreement shall mean the form of agreement contained in Appendix 4 of the LGIP for conducting the Optional Interconnection Study.

Party or Parties shall mean Transmission Provider, Transmission Owner, Interconnection Customer or any combination of the above.

Point of Change of Ownership shall mean the point, as set forth in Appendix A to the Standard Large Generator Interconnection Agreement, where Interconnection Customer's Interconnection Facilities connect to Transmission Provider's Interconnection Facilities.

Point of Interconnection shall mean the point, as set forth in Appendix A to the Standard Large Generator Interconnection Agreement, where the Interconnection Facilities connect to Transmission Provider's Transmission System.

Proportional Impact Method shall mean a technical analysis conducted by Transmission Provider to determine the degree to which each Generating Facility in the Cluster Study contributes to the need for a specific System Network Upgrade.

Provisional Interconnection Service shall mean Interconnection Service provided by Transmission Provider associated with interconnecting Interconnection Customer's Generating Facility to Transmission Provider's Transmission System and enabling that Transmission System to receive electric energy and capacity from the Generating Facility at the Point of Interconnection, pursuant to the terms of the Provisional Large Generator Interconnection Agreement and, if applicable, the Tariff.

Provisional Large Generator Interconnection Agreement shall mean the interconnection agreement for Provisional Interconnection Service established between Transmission Provider and/or the Transmission Owner and Interconnection Customer. This agreement shall take the form of the Standard Large Generator Interconnection Agreement, modified for provisional purposes.

Queue Position shall mean the order of a valid Interconnection Request, relative to all other pending valid Interconnection Requests, established pursuant to Section 4.1 of the LGIP.

Reasonable Efforts shall mean, with respect to an action required to be attempted or taken by a Party under the Standard Large Generator Interconnection Agreement, efforts that are timely and consistent with Good Utility Practice and are otherwise substantially equivalent to those a Party would use to protect its own interests.

Scoping Meeting shall mean the meeting between representatives of Interconnection Customer(s) and Transmission Provider conducted for the purpose of discussing the proposed Interconnection Request and any alternative interconnection options, exchanging information including any transmission data and earlier study evaluations that would be reasonably expected to impact such interconnection options, refining information and models provided by Interconnection Customer(s), discussing the Cluster Study materials posted to OASIS pursuant to Section 3.5 of the LGIP, and analyzing such information.

Site Control shall mean the exclusive land right to develop, construct, operate, and maintain the Generating Facility over the term of expected operation of the Generating Facility.

Site Control may be demonstrated by documentation establishing: (1) ownership of, a leasehold interest in, or a right to develop a site of sufficient size to construct and operate the Generating Facility; (2) an option to purchase or acquire a leasehold site of sufficient size to construct and operate the Generating Facility; or (3) any other documentation that clearly demonstrates the right of Interconnection Customer to exclusively occupy a site of sufficient size to construct and operate the Generating Facility. Transmission Provider will maintain acreage requirements for each Generating Facility type on its OASIS or public website.

Small Generating Facility shall mean a Generating Facility that has a Generating Facility Capacity of no more than 20 MW.

Stand Alone Network Upgrades shall mean Network Upgrades that are not part of an Affected System that Interconnection Customer may construct without affecting day-to-day operations of the Transmission System during their construction. Both Transmission Provider and Interconnection Customer must agree as to what constitutes Stand Alone Network Upgrades and identify them in Appendix A to the Standard Large Generator Interconnection Agreement. If Transmission Provider and Interconnection Customer disagree about whether a particular Network Upgrade is a Stand Alone Network Upgrade, Transmission Provider must provide Interconnection Customer a written technical explanation outlining why Transmission Provider does not consider the Network Upgrade to be a Stand Alone Network Upgrade within fifteen (15) Business Days of its determination.

Standard Large Generator Interconnection Agreement (LGIA) shall mean the form of interconnection agreement applicable to an Interconnection Request pertaining to a Large Generating Facility that is included in Transmission Provider's Tariff.

Standard Large Generator Interconnection Procedures (LGIP) shall mean the interconnection procedures applicable to an Interconnection Request pertaining to a Large Generating Facility that are included in Transmission Provider's Tariff.

Substation Network Upgrades shall mean Network Upgrades that are required at the substation located at the Point of Interconnection.

Surplus Interconnection Service shall mean any unneeded portion of Interconnection Service established in a Standard Large Generator Interconnection Agreement, such that if Surplus Interconnection Service is utilized the total amount of Interconnection Service at the Point of Interconnection would remain the same.

System Network Upgrades shall mean Network Upgrades that are required beyond the substation located at the Point of Interconnection.

System Protection Facilities shall mean the equipment, including necessary protection signal communications equipment, required to protect (1) Transmission Provider's Transmission System from faults or other electrical disturbances occurring at the Generating Facility and (2) the Generating Facility from faults or other electrical system disturbances occurring on Transmission Provider's Transmission System or on other delivery systems or other generating

systems to which Transmission Provider's Transmission System is directly connected.

Tariff shall mean Transmission Provider's Tariff through which open access transmission service and Interconnection Service are offered, as filed with FERC, and as amended or supplemented from time to time, or any successor tariff.

Transmission Owner shall mean an entity that owns, leases or otherwise possesses an interest in the portion of the Transmission System at the Point of Interconnection and may be a Party to the Standard Large Generator Interconnection Agreement to the extent necessary.

Transmission Provider shall mean the public utility (or its designated agent) that owns, controls, or operates transmission or distribution facilities used for the transmission of electricity in interstate commerce and provides transmission service under the Tariff. The term Transmission Provider should be read to include the Transmission Owner when the Transmission Owner is separate from Transmission Provider.

Transmission Provider's Interconnection Facilities shall mean all facilities and equipment owned, controlled, or operated by Transmission Provider from the Point of Change of Ownership to the Point of Interconnection as identified in Appendix A to the Standard Large Generator Interconnection Agreement, including any modifications, additions or upgrades to such facilities and equipment. Transmission Provider's Interconnection Facilities are sole use facilities and shall not include Distribution Upgrades, Stand Alone Network Upgrades or Network Upgrades.

Transmission System shall mean the facilities owned, controlled or operated by Transmission Provider or Transmission Owner that are used to provide transmission service under the Tariff.

Trial Operation shall mean the period during which Interconnection Customer is engaged in on-site test operations and commissioning of the Generating Facility prior to Commercial Operation.

Variable Energy Resource shall mean a device for the production of electricity that is characterized by an energy source that: (1) is renewable; (2) cannot be stored by the facility owner or operator; and (3) has variability that is beyond the control of the facility owner or operator.

Withdrawal Penalty shall mean the penalty assessed by Transmission Provider to an Interconnection Customer that chooses to withdraw or is deemed withdrawn from Transmission Provider's interconnection queue or whose Generating Facility does not otherwise reach Commercial Operation. The calculation of the Withdrawal Penalty is set forth in Section 3.7.1 of the LGIP.

Article 2. Effective Date, Term, and Termination

2.1 Effective Date. This LGIA shall become effective upon execution by the Parties subject to acceptance by FERC (if applicable), or if filed unexecuted, upon the date specified by FERC. Transmission Provider shall promptly file this LGIA with FERC upon execution in accordance with Article 3.1, if required.

2.2 Term of Agreement. Subject to the provisions of Article 2.3, this LGIA shall remain in effect for a period of twenty-five (25) years from the Effective Date or such other longer period as Interconnection Customer may request and shall be automatically renewed for each successive one-year period thereafter.

2.3 Termination Procedures.

2.3.1 Written Notice. This LGIA may be terminated by Interconnection Customer after giving Transmission Provider ninety (90) Calendar Days advance written notice, or by Transmission Provider notifying FERC after the Generating Facility permanently ceases Commercial Operation.

2.3.2 Default. Either Party may terminate this LGIA in accordance with Article 17.

2.3.3 Notwithstanding Articles 2.3.1 and 2.3.2, no termination shall become effective until the Parties have complied with all Applicable Laws and Regulations applicable to such termination, including the filing with FERC of a notice of termination of this LGIA, which notice has been accepted for filing by FERC.

2.4 Termination Costs. If a Party elects to terminate this Agreement pursuant to Article 2.3 above, each Party shall pay all costs incurred (including any cancellation costs relating to orders or contracts for Interconnection Facilities and equipment) or charges assessed by the other Party, as of the date of the other Party's receipt of such notice of termination, that are the responsibility of the Terminating Party under this LGIA. In the event of termination by a Party, the Parties shall use commercially Reasonable Efforts to mitigate the costs, damages and charges arising as a consequence of termination. Upon termination of this LGIA, unless otherwise ordered or approved by FERC:

2.4.1 With respect to any portion of Transmission Provider's Interconnection Facilities that have not yet been constructed or installed, Transmission Provider shall to the extent possible and with Interconnection Customer's authorization cancel any pending orders of, or return, any materials or equipment for, or contracts for construction of, such facilities; provided that in the event Interconnection Customer elects not to authorize such cancellation, Interconnection Customer shall assume all payment obligations with respect to such materials, equipment, and contracts, and Transmission Provider shall deliver such material and equipment, and, if necessary, assign such contracts, to Interconnection Customer as soon as practicable, at Interconnection Customer's expense. To the extent that Interconnection Customer has already paid Transmission Provider for any or all

such costs of materials or equipment not taken by Interconnection Customer, Transmission Provider shall promptly refund such amounts to Interconnection Customer, less any costs, including penalties incurred by Transmission Provider to cancel any pending orders or return such materials, equipment, or contracts.

If an Interconnection Customer terminates this LGIA, it shall be responsible for all costs incurred in association with that Interconnection Customer's interconnection, including any cancellation costs relating to orders or contracts for Interconnection Facilities and equipment, and other expenses including any Network Upgrades for which Transmission Provider has incurred expenses and has not been reimbursed by Interconnection Customer.

2.4.2 Transmission Provider may, at its option, retain any portion of such materials, equipment, or facilities that Interconnection Customer chooses not to accept delivery of, in which case Transmission Provider shall be responsible for all costs associated with procuring such materials, equipment, or facilities.

2.4.3 With respect to any portion of the Interconnection Facilities, and any other facilities already installed or constructed pursuant to the terms of this LGIA, Interconnection Customer shall be responsible for all costs associated with the removal, relocation or other disposition or retirement of such materials, equipment, or facilities.

2.5 **Disconnection.** Upon termination of this LGIA, the Parties will take all appropriate steps to disconnect the Large Generating Facility from the Transmission System. All costs required to effectuate such disconnection shall be borne by the terminating Party, unless such termination resulted from the non-terminating Party's Default of this LGIA or such non-terminating Party otherwise is responsible for these costs under this LGIA.

2.6 **Survival.** This LGIA shall continue in effect after termination to the extent necessary to provide for final billings and payments and for costs incurred hereunder, including billings and payments pursuant to this LGIA; to permit the determination and enforcement of liability and indemnification obligations arising from acts or events that occurred while this LGIA was in effect; and to permit each Party to have access to the lands of the other Party pursuant to this LGIA or other applicable agreements, to disconnect, remove or salvage its own facilities and equipment.

Article 3. Regulatory Filings

3.1 Filing. Transmission Provider shall file this LGIA (and any amendment thereto) with the appropriate Governmental Authority, if required. Interconnection Customer may request that any information so provided be subject to the confidentiality provisions of Article 22. If Interconnection Customer has executed this LGIA, or any amendment thereto, Interconnection Customer shall reasonably cooperate with Transmission Provider with respect to such filing and to provide any information reasonably requested by Transmission Provider needed to comply with applicable regulatory requirements.

Article 4. Scope of Service

4.1 Interconnection Product Options. Interconnection Customer has selected the following (checked) type of Interconnection Service:

4.1.1 Energy Resource Interconnection Service.

4.1.1.1 The Product. Energy Resource Interconnection Service allows Interconnection Customer to connect the Large Generating Facility to the Transmission System and be eligible to deliver the Large Generating Facility's output using the existing firm or non-firm capacity of the Transmission System on an "as available" basis. To the extent Interconnection Customer wants to receive Energy Resource Interconnection Service, Transmission Provider shall construct facilities identified in Attachment A.

4.1.1.2 Transmission Delivery Service Implications. Under Energy Resource Interconnection Service, Interconnection Customer will be eligible to inject power from the Large Generating Facility into and deliver power across the interconnecting Transmission Provider's Transmission System on an "as available" basis up to the amount of MWs identified in the applicable stability and steady state studies to the extent the upgrades initially required to qualify for Energy Resource Interconnection Service have been constructed. Where eligible to do so (e.g., PJM, ISO-NE, NYISO), Interconnection Customer may place a bid to sell into the market up to the maximum identified Large Generating Facility output, subject to any conditions specified in the interconnection service approval, and the Large Generating Facility will be dispatched to the extent Interconnection Customer's bid clears. In all other instances, no transmission delivery service from the Large Generating Facility is assured, but Interconnection Customer may obtain Point-To-Point Transmission Service, Network Integration Transmission Service, or be used for secondary network transmission service, pursuant to Transmission Provider's Tariff,

up to the maximum output identified in the stability and steady state studies. In those instances, in order for Interconnection Customer to obtain the right to deliver or inject energy beyond the Large Generating Facility Point of Interconnection or to improve its ability to do so, transmission delivery service must be obtained pursuant to the provisions of Transmission Provider's Tariff. Interconnection Customer's ability to inject its Large Generating Facility output beyond the Point of Interconnection, therefore, will depend on the existing capacity of Transmission Provider's Transmission System at such time as a transmission service request is made that would accommodate such delivery. The provision of firm Point-To-Point Transmission Service or Network Integration Transmission Service may require the construction of additional Network Upgrades.

4.1.2 Network Resource Interconnection Service.

- 4.1.2.1** **The Product.** Transmission Provider must conduct the necessary studies pursuant to Attachment J-1 of the Tariff and construct the Network Upgrades needed to integrate the Large Generating Facility (1) in a manner comparable to that in which Transmission Provider integrates its generating facilities to serve native load customers; or (2) in an ISO or RTO with market based congestion management, in the same manner as all Network Resources. To the extent Interconnection Customer wants to receive Network Resource Interconnection Service, Transmission Provider shall construct the facilities identified in Attachment A to this LGIA.
- 4.1.2.2** **Transmission Delivery Service Implications.** Network Resource Interconnection Service allows Interconnection Customer's Large Generating Facility to be designated by any Network Customer under the Tariff on Transmission Provider's Transmission System as a Network Resource, up to the Large Generating Facility's full output, on the same basis as existing Network Resources interconnected to Transmission Provider's Transmission System, and to be studied as a Network Resource on the assumption that such a designation will occur. Although Network Resource Interconnection Service does not convey a reservation of transmission service, any Network Customer under the Tariff can utilize its network service under the Tariff to obtain delivery of energy from the interconnected Interconnection Customer's Large Generating Facility in the same manner as it accesses Network Resources. A Large Generating Facility receiving Network Resource Interconnection Service may also be used to provide Ancillary Services after technical studies and/or periodic analyses are performed with respect to the Large Generating Facility's ability to provide any applicable Ancillary Services, provided that

such studies and analyses have been or would be required in connection with the provision of such Ancillary Services by any existing Network Resource. However, if an Interconnection Customer's Large Generating Facility has not been designated as a Network Resource by any load, it cannot be required to provide Ancillary Services except to the extent such requirements extend to all generating facilities that are similarly situated. The provision of Network Integration Transmission Service or firm Point-To-Point Transmission Service may require additional studies and the construction of additional upgrades. Because such studies and upgrades would be associated with a request for delivery service under the Tariff, cost responsibility for the studies and upgrades would be in accordance with FERC's policy for pricing transmission delivery services.

Network Resource Interconnection Service does not necessarily provide Interconnection Customer with the capability to physically deliver the output of its Large Generating Facility to any particular load on Transmission Provider's Transmission System without incurring congestion costs. In the event of transmission constraints on Transmission Provider's Transmission System, Interconnection Customer's Large Generating Facility shall be subject to the applicable congestion management procedures in Transmission Provider's Transmission System in the same manner as Network Resources.

There is no requirement either at the time of study or interconnection, or at any point in the future, that Interconnection Customer's Large Generating Facility be designated as a Network Resource by a Network Service Customer under the Tariff or that Interconnection Customer identify a specific buyer (or sink). To the extent a Network Customer does designate the Large Generating Facility as a Network Resource, it must do so pursuant to Transmission Provider's Tariff.

Once an Interconnection Customer satisfies the requirements for obtaining Network Resource Interconnection Service, any future transmission service request for delivery from the Large Generating Facility within Transmission Provider's Transmission System of any amount of capacity and/or energy, up to the amount initially studied, will not require that any additional studies be performed or that any further upgrades associated with such Large Generating Facility be undertaken, regardless of whether or not such Large Generating Facility is ever designated by a Network Customer as a Network Resource and regardless of changes in ownership of the Large Generating Facility. However, the reduction or elimination of congestion or redispatch costs may

require additional studies and the construction of additional upgrades.

To the extent Interconnection Customer enters into an arrangement for long term transmission service for deliveries from the Large Generating Facility outside Transmission Provider's Transmission System, such request may require additional studies and upgrades in order for Transmission Provider to grant such request.

- 4.2 Provision of Service.** Transmission Provider shall provide Interconnection Service for the Large Generating Facility at the Point of Interconnection.
- 4.3 Performance Standards.** Each Party shall perform all of its obligations under this LGIA in accordance with Applicable Laws and Regulations, Applicable Reliability Standards, and Good Utility Practice, and to the extent a Party is required or prevented or limited in taking any action by such regulations and standards, such Party shall not be deemed to be in Breach of this LGIA for its compliance therewith. If such Party is a Transmission Provider or Transmission Owner, then that Party shall amend the LGIA and submit the amendment to FERC for approval.
- 4.4 No Transmission Delivery Service.** The execution of this LGIA does not constitute a request for, nor the provision of, any transmission delivery service under Transmission Provider's Tariff, and does not convey any right to deliver electricity to any specific customer or Point of Delivery.
- 4.5 Interconnection Customer Provided Services.** The services provided by Interconnection Customer under this LGIA are set forth in Article 9.6 and Article 13.5.1. Interconnection Customer shall be paid for such services in accordance with Article 11.6.

Article 5. Interconnection Facilities Engineering, Procurement, and Construction

- 5.1 Options.** Unless otherwise mutually agreed to between the Parties, Interconnection Customer shall select the In-Service Date, Initial Synchronization Date, and Commercial Operation Date; and either the Standard Option or Alternate Option set forth below, and such dates and selected option shall be set forth in Appendix B, Milestones. At the same time, Interconnection Customer shall indicate whether it elects to exercise the Option to Build set forth in Article 5.1.3 below. If the dates designated by Interconnection Customer are not acceptable to Transmission Provider, Transmission Provider shall so notify Interconnection Customer within thirty (30) Calendar Days. Upon receipt of the notification that Interconnection Customer's designated dates are not acceptable to Transmission Provider, Interconnection Customer shall notify Transmission Provider within thirty (30) Calendar Days whether it elects to exercise the Option to Build if it has not already elected to exercise the Option to Build.

- 5.1.1 Standard Option.** Transmission Provider shall design, procure, and construct Transmission Provider's Interconnection Facilities and Network Upgrades, using

Reasonable Efforts to complete Transmission Provider's Interconnection Facilities and Network Upgrades by the dates set forth in Appendix B, Milestones. Transmission Provider shall not be required to undertake any action which is inconsistent with its standard safety practices, its material and equipment specifications, its design criteria and construction procedures, its labor agreements, and Applicable Laws and Regulations. In the event Transmission Provider reasonably expects that it will not be able to complete Transmission Provider's Interconnection Facilities and Network Upgrades by the specified dates, Transmission Provider shall promptly provide written notice to Interconnection Customer and shall undertake Reasonable Efforts to meet the earliest dates thereafter.

5.1.2 Alternate Option. If the dates designated by Interconnection Customer are acceptable to Transmission Provider, Transmission Provider shall so notify Interconnection Customer within thirty (30) Calendar Days, and shall assume responsibility for the design, procurement and construction of Transmission Provider's Interconnection Facilities by the designated dates.

If Transmission Provider subsequently fails to complete Transmission Provider's Interconnection Facilities by the In-Service Date, to the extent necessary to provide back feed power; or fails to complete Network Upgrades by the Initial Synchronization Date to the extent necessary to allow for Trial Operation at full power output, unless other arrangements are made by the Parties for such Trial Operation; or fails to complete the Network Upgrades by the Commercial Operation Date, as such dates are reflected in Appendix B, Milestones; Transmission Provider shall pay Interconnection Customer liquidated damages in accordance with Article 5.3, Liquidated Damages, provided, however, the dates designated by Interconnection Customer shall be extended day for day for each day that the applicable RTO or ISO refuses to grant clearances to install equipment.

5.1.3 Option to Build. Individual or multiple Interconnection Customers shall have the option to assume responsibility for the design, procurement and construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades on the dates specified in Article 5.1.2, if the requirements of this Article 5.1.3 are met. When multiple Interconnection Customers exercise this option, multiple Interconnection Customers may agree to exercise this option provided (1) all Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades constructed under this option are only required for Interconnection Customers in a single Cluster and (2) all impacted Interconnection Customers execute and provide to Transmission Provider an agreement regarding responsibilities and payment for the construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades planned to be built under this option. Transmission Provider and the individual Interconnection Customer or each of the multiple Interconnection Customers must agree as to what constitutes Stand Alone Network Upgrades and identify such Stand Alone Network Upgrades in Appendix A. Except for Stand

Alone Network Upgrades, Interconnection Customer shall have no right to construct Network Upgrades under this option.

5.1.4 Negotiated Option. If the dates designated by Interconnection Customer are not acceptable to Transmission Provider, the Parties shall in good faith attempt to negotiate terms and conditions (including revision of the specified dates and liquidated damages, the provision of incentives, or the procurement and construction of all facilities other than Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades if Interconnection Customer elects to exercise the Option to Build under Article 5.1.3). If the Parties are unable to reach agreement on such terms and conditions, then, pursuant to Article 5.1.1 (Standard Option), Transmission Provider shall assume responsibility for the design, procurement and construction of all facilities other than Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades if Interconnection Customer elects to exercise the Option to Build.

5.2 General Conditions Applicable to Option to Build. If Interconnection Customer assumes responsibility for the design, procurement and construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades,

- (1) Interconnection Customer shall engineer, procure equipment, and construct Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades (or portions thereof) using Good Utility Practice and using standards and specifications provided in advance by Transmission Provider;
- (2) Interconnection Customer's engineering, procurement and construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades shall comply with all requirements of law to which Transmission Provider would be subject in the engineering, procurement or construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades;
- (3) Transmission Provider shall review and approve the engineering design, equipment acceptance tests, and the construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades;
- (4) prior to commencement of construction, Interconnection Customer shall provide to Transmission Provider a schedule for construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades, and shall promptly respond to requests for information from Transmission Provider;
- (5) at any time during construction, Transmission Provider shall have the right to gain unrestricted access to Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades and to conduct inspections of the same;
- (6) at any time during construction, should any phase of the engineering, equipment procurement, or construction of Transmission Provider's

Interconnection Facilities and Stand Alone Network Upgrades not meet the standards and specifications provided by Transmission Provider, Interconnection Customer shall be obligated to remedy deficiencies in that portion of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades;

- (7) Interconnection Customer shall indemnify Transmission Provider for claims arising from Interconnection Customer's construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades under the terms and procedures applicable to Article 18.1 Indemnity;
- (8) Interconnection Customer shall transfer control of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades to Transmission Provider;
- (9) Unless Parties otherwise agree, Interconnection Customer shall transfer ownership of Transmission Provider's Interconnection Facilities and Stand-Alone Network Upgrades to Transmission Provider;
- (10) Transmission Provider shall approve and accept for operation and maintenance Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades to the extent engineered, procured, and constructed in accordance with this Article 5.2; and
- (11) Interconnection Customer shall deliver to Transmission Provider "as-built" drawings, information, and any other documents that are reasonably required by Transmission Provider to assure that the Interconnection Facilities and Stand-Alone Network Upgrades are built to the standards and specifications required by Transmission Provider.
- (12) If Interconnection Customer exercises the Option to Build pursuant to Article 5.1.3, Interconnection Customer shall pay Transmission Provider the agreed upon amount of [\$ PLACEHOLDER] for Transmission Provider to execute the responsibilities enumerated to Transmission Provider under Article 5.2. Transmission Provider shall invoice Interconnection Customer for this total amount to be divided on a monthly basis pursuant to Article 12.

5.3 Liquidated Damages. The actual damages to Interconnection Customer, in the event Transmission Provider's Interconnection Facilities or Network Upgrades are not completed by the dates designated by Interconnection Customer and accepted by Transmission Provider pursuant to subparagraphs 5.1.2 or 5.1.4, above, may include Interconnection Customer's fixed operation and maintenance costs and lost opportunity costs. Such actual damages are uncertain and impossible to determine at this time. Because of such uncertainty, any liquidated damages paid by Transmission Provider to Interconnection Customer in the event that Transmission Provider does not complete any portion of Transmission Provider's Interconnection Facilities or Network Upgrades by the applicable dates, shall be an amount equal to $\frac{1}{2}$ of 1 percent per day of the actual cost

of Transmission Provider's Interconnection Facilities and Network Upgrades, in the aggregate, for which Transmission Provider has assumed responsibility to design, procure and construct.

However, in no event shall the total liquidated damages exceed 20 percent of the actual cost of Transmission Provider's Interconnection Facilities and Network Upgrades for which Transmission Provider has assumed responsibility to design, procure, and construct. The foregoing payments will be made by Transmission Provider to Interconnection Customer as just compensation for the damages caused to Interconnection Customer, which actual damages are uncertain and impossible to determine at this time, and as reasonable liquidated damages, but not as a penalty or a method to secure performance of this LGIA. Liquidated damages, when the Parties agree to them, are the exclusive remedy for Transmission Provider's failure to meet its schedule.

No liquidated damages shall be paid to Interconnection Customer if: (1) Interconnection Customer is not ready to commence use of Transmission Provider's Interconnection Facilities or Network Upgrades to take the delivery of power for the Large Generating Facility's Trial Operation or to export power from the Large Generating Facility on the specified dates, unless Interconnection Customer would have been able to commence use of Transmission Provider's Interconnection Facilities or Network Upgrades to take the delivery of power for Large Generating Facility's Trial Operation or to export power from the Large Generating Facility, but for Transmission Provider's delay; (2) Transmission Provider's failure to meet the specified dates is the result of the action or inaction of Interconnection Customer or any other Interconnection Customer who has entered into an LGIA with Transmission Provider or any cause beyond Transmission Provider's reasonable control or reasonable ability to cure; (3) Interconnection Customer has assumed responsibility for the design, procurement and construction of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades; or (4) the Parties have otherwise agreed.

5.4 Power System Stabilizers. Interconnection Customer shall procure, install, maintain and operate Power System Stabilizers in accordance with the guidelines and procedures established by the Electric Reliability Organization. Transmission Provider reserves the right to reasonably establish minimum acceptable settings for any installed Power System Stabilizers, subject to the design and operating limitations of the Large Generating Facility. If the Large Generating Facility's Power System Stabilizers are removed from service or not capable of automatic operation, Interconnection Customer shall immediately notify Transmission Provider's system operator, or its designated representative. The requirements of this paragraph shall not apply to wind generators.

5.5 Equipment Procurement. If responsibility for construction of Transmission Provider's Interconnection Facilities or Network Upgrades is to be borne by Transmission Provider, then Transmission Provider shall commence design of Transmission Provider's Interconnection Facilities or Network Upgrades and procure necessary equipment as soon as practicable after all of the following conditions are satisfied, unless the Parties

otherwise agree in writing:

- 5.5.1** Transmission Provider has completed the Interconnection Facilities Study pursuant to the Interconnection Facilities Study Agreement;
- 5.5.2** Transmission Provider has received written authorization to proceed with design and procurement from Interconnection Customer by the date specified in Appendix B, Milestones; and
- 5.5.3** Interconnection Customer has provided security to Transmission Provider in accordance with Article 11.5 by the dates specified in Appendix B, Milestones.

5.6 **Construction Commencement.** Transmission Provider shall commence construction of Transmission Provider's Interconnection Facilities and Network Upgrades for which it is responsible as soon as practicable after the following additional conditions are satisfied:

- 5.6.1** Approval of the appropriate Governmental Authority has been obtained for any facilities requiring regulatory approval;
- 5.6.2** Necessary real property rights and rights-of-way have been obtained, to the extent required for the construction of a discrete aspect of Transmission Provider's Interconnection Facilities and Network Upgrades;
- 5.6.3** Transmission Provider has received written authorization to proceed with construction from Interconnection Customer by the date specified in Appendix B, Milestones; and
- 5.6.4** Interconnection Customer has provided security to Transmission Provider in accordance with Article 11.5 by the dates specified in Appendix B, Milestones.

5.7 **Work Progress.** The Parties will keep each other advised periodically as to the progress of their respective design, procurement and construction efforts. Either Party may, at any time, request a progress report from the other Party. If, at any time, Interconnection Customer determines that the completion of Transmission Provider's Interconnection Facilities will not be required until after the specified In-Service Date, Interconnection Customer will provide written notice to Transmission Provider of such later date upon which the completion of Transmission Provider's Interconnection Facilities will be required.

5.8 **Information Exchange.** As soon as reasonably practicable after the Effective Date, the Parties shall exchange information regarding the design and compatibility of the Parties' Interconnection Facilities and compatibility of the Interconnection Facilities with Transmission Provider's Transmission System, and shall work diligently and in good faith to make any necessary design changes.

5.9 Other Interconnection Options.

5.9.1 Limited Operation. If any of Transmission Provider's Interconnection Facilities or Network Upgrades are not reasonably expected to be completed prior to the Commercial Operation Date of the Large Generating Facility, Transmission Provider shall, upon the request and at the expense of Interconnection Customer, perform operating studies on a timely basis to determine the extent to which the Large Generating Facility and Interconnection Customer's Interconnection Facilities may operate prior to the completion of Transmission Provider's Interconnection Facilities or Network Upgrades consistent with Applicable Laws and Regulations, Applicable Reliability Standards, Good Utility Practice, and this LGIA. Transmission Provider shall permit Interconnection Customer to operate the Large Generating Facility and Interconnection Customer's Interconnection Facilities in accordance with the results of such studies.

5.9.2 Provisional Interconnection Service. Upon the request of Interconnection Customer, and prior to completion of requisite Interconnection Facilities, Network Upgrades, Distribution Upgrades, or System Protection Facilities Transmission Provider may execute a Provisional Large Generator Interconnection Agreement or Interconnection Customer may request the filing of an unexecuted Provisional Large Generator Interconnection Agreement with Interconnection Customer for limited Interconnection Service at the discretion of Transmission Provider based upon an evaluation that will consider the results of available studies. Transmission Provider shall determine, through available studies or additional studies as necessary, whether stability, short circuit, thermal, and/or voltage issues would arise if Interconnection Customer interconnects without modifications to the Generating Facility or Transmission System. Transmission Provider shall determine whether any Interconnection Facilities, Network Upgrades, Distribution Upgrades, or System Protection Facilities that are necessary to meet the requirements of the Electric Reliability Organization, or any applicable Regional Entity for the interconnection of a new, modified and/or expanded Generating Facility are in place prior to the commencement of Interconnection Service from the Generating Facility. Where available studies indicate that such, Interconnection Facilities, Network Upgrades, Distribution Upgrades, and/or System Protection Facilities that are required for the interconnection of a new, modified and/or expanded Generating Facility are not currently in place, Transmission Provider will perform a study, at Interconnection Customer's expense, to confirm the facilities that are required for Provisional Interconnection Service. The maximum permissible output of the Generating Facility in the Provisional Large Generator Interconnection Agreement shall be studied and updated annually or as otherwise agreed to by the Parties, with such studies and updates to be performed at Interconnection Customer's expense. Interconnection Customer assumes all risk and liabilities with respect to changes between the Provisional Large Generator Interconnection Agreement and the Standard Large Generator Interconnection Agreement, including changes in output limits and Interconnection Facilities, Network Upgrades, Distribution

Upgrades, and/or System Protection Facilities cost responsibilities.

5.10 Interconnection Customer's Interconnection Facilities ('ICIF'). Interconnection Customer shall, at its expense, design, procure, construct, own and install the ICIF, as set forth in Appendix A, Interconnection Facilities, Network Upgrades and Distribution Upgrades.

5.10.1 Interconnection Customer's Interconnection Facility Specifications.

Interconnection Customer shall submit initial specifications for the ICIF, including System Protection Facilities, to Transmission Provider at least one hundred eighty (180) Calendar Days prior to the Initial Synchronization Date; and final specifications for review and comment at least ninety (90) Calendar Days prior to the Initial Synchronization Date. Transmission Provider shall review such specifications to ensure that the ICIF are compatible with the technical specifications, operational control, and safety requirements of Transmission Provider and comment on such specifications within thirty (30) Calendar Days of Interconnection Customer's submission. All specifications provided hereunder shall be deemed confidential.

5.10.2 Transmission Provider's Review. Transmission Provider's review of Interconnection Customer's final specifications shall not be construed as confirming, endorsing, or providing a warranty as to the design, fitness, safety, durability or reliability of the Large Generating Facility, or the ICIF. Interconnection Customer shall make such changes to the ICIF as may reasonably be required by Transmission Provider, in accordance with Good Utility Practice, to ensure that the ICIF are compatible with the technical specifications, operational control, and safety requirements of Transmission Provider.

5.10.3 ICIF Construction. The ICIF shall be designed and constructed in accordance with Good Utility Practice. Within one hundred twenty (120) Calendar Days after the Commercial Operation Date, unless the Parties agree on another mutually acceptable deadline, Interconnection Customer shall deliver to Transmission Provider "as-built" drawings, information and documents for the ICIF, such as: a one-line diagram, a site plan showing the Large Generating Facility and the ICIF, plan and elevation drawings showing the layout of the ICIF, a relay functional diagram, relaying AC and DC schematic wiring diagrams and relay settings for all facilities associated with Interconnection Customer's step-up transformers, the facilities connecting the Large Generating Facility to the step-up transformers and the ICIF, and the impedances (determined by factory tests) for the associated step-up transformers and the Large Generating Facility. Interconnection Customer shall provide Transmission Provider specifications for the excitation system, automatic voltage regulator, Large Generating Facility control and protection settings,

transformer tap settings, and communications, if applicable.

5.11 Transmission Provider's Interconnection Facilities Construction. Transmission Provider's Interconnection Facilities shall be designed and constructed in accordance with Good Utility Practice. Upon request, within one hundred twenty (120) Calendar Days after the Commercial Operation Date, unless the Parties agree on another mutually acceptable deadline, Transmission Provider shall deliver to Interconnection Customer the following "as-built" drawings, information and documents for Transmission Provider's Interconnection Facilities [include appropriate drawings and relay diagrams].

Transmission Provider will obtain control of Transmission Provider's Interconnection Facilities and Stand Alone Network Upgrades upon completion of such facilities.

5.12 Access Rights. Upon reasonable notice and supervision by a Party, and subject to any required or necessary regulatory approvals, a Party ("Granting Party") shall furnish at no cost to the other Party ("Access Party") any rights of use, licenses, rights of way and easements with respect to lands owned or controlled by the Granting Party, its agents (if allowed under the applicable agency agreement), or any Affiliate, that are necessary to enable the Access Party to obtain ingress and egress to construct, operate, maintain, repair, test (or witness testing), inspect, replace or remove facilities and equipment to: (i) interconnect the Large Generating Facility with the Transmission System; (ii) operate and maintain the Large Generating Facility, the Interconnection Facilities and the Transmission System; and (iii) disconnect or remove the Access Party's facilities and equipment upon termination of this LGIA. In exercising such licenses, rights of way and easements, the Access Party shall not unreasonably disrupt or interfere with normal operation of the Granting Party's business and shall adhere to the safety rules and procedures established in advance, as may be changed from time to time, by the Granting Party and provided to the Access Party.

5.13 Lands of Other Property Owners. If any part of Transmission Provider or Transmission Owner's Interconnection Facilities and/or Network Upgrades is to be installed on property owned by persons other than Interconnection Customer or Transmission Provider or Transmission Owner, Transmission Provider or Transmission Owner shall at Interconnection Customer's expense use efforts, similar in nature and extent to those that it typically undertakes on its own behalf or on behalf of its Affiliates, including use of its eminent domain authority, and to the extent consistent with state law, to procure from such persons any rights of use, licenses, rights of way and easements that are necessary to construct, operate, maintain, test, inspect, replace or remove Transmission Provider or Transmission Owner's Interconnection Facilities and/or Network Upgrades upon such property.

5.14 Permits. Transmission Provider or Transmission Owner and Interconnection Customer shall cooperate with each other in good faith in obtaining all permits, licenses, and authorizations that are necessary to accomplish the interconnection in compliance with Applicable Laws and Regulations. With respect to this paragraph, Transmission Provider or Transmission Owner shall provide permitting assistance to Interconnection Customer

comparable to that provided to Transmission Provider's own, or an Affiliate's generation.

5.15 Early Construction of Base Case Facilities. Interconnection Customer may request Transmission Provider to construct, and Transmission Provider shall construct, using Reasonable Efforts to accommodate Interconnection Customer's In-Service Date, all or any portion of any Network Upgrades required for Interconnection Customer to be interconnected to the Transmission System which are included in the Base Case of the Interconnection Facilities Study for Interconnection Customer, and which also are required to be constructed for another Interconnection Customer, but where such construction is not scheduled to be completed in time to achieve Interconnection Customer's In-Service Date.

5.16 Suspension. Interconnection Customer reserves the right, upon written notice to Transmission Provider, to suspend at any time all work by Transmission Provider associated with the construction and installation of Transmission Provider's Interconnection Facilities and/or Network Upgrades required under this LGIA with the condition that Transmission System shall be left in a safe and reliable condition in accordance with Good Utility Practice and Transmission Provider's safety and reliability criteria. In such event, Interconnection Customer shall be responsible for all reasonable and necessary costs which Transmission Provider (i) has incurred pursuant to this LGIA prior to the suspension and (ii) incurs in suspending such work, including any costs incurred to perform such work as may be necessary to ensure the safety of persons and property and the integrity of the Transmission System during such suspension and, if applicable, any costs incurred in connection with the cancellation or suspension of material, equipment and labor contracts which Transmission Provider cannot reasonably avoid; provided, however, that prior to canceling or suspending any such material, equipment or labor contract, Transmission Provider shall obtain Interconnection Customer's authorization to do so.

Transmission Provider shall invoice Interconnection Customer for such costs pursuant to Article 12 and shall use due diligence to minimize its costs. In the event Interconnection Customer suspends work by Transmission Provider required under this LGIA pursuant to this Article 5.16, and has not requested Transmission Provider to recommence the work required under this LGIA on or before the expiration of three (3) years following commencement of such suspension, this LGIA shall be deemed terminated. The three-year period shall begin on the date the suspension is requested, or the date of the written notice to Transmission Provider, if no effective date is specified.

5.17 Taxes.

5.17.1 Interconnection Customer Payments Not Taxable. The Parties intend that all payments or property transfers made by Interconnection Customer to Transmission Provider for the installation of Transmission Provider's Interconnection Facilities and the Network Upgrades shall be non-taxable, either as contributions to capital, or as an advance, in accordance with the Internal Revenue Code and any applicable state income tax laws and shall not be taxable as contributions in aid of construction or otherwise under

the Internal Revenue Code and any applicable state income tax laws.

5.17.2

Representations and Covenants. In accordance with IRS Notice 2001-82 and IRS Notice 88-129, Interconnection Customer represents and covenants that (i) ownership of the electricity generated at the Large Generating Facility will pass to another party prior to the transmission of the electricity on the Transmission System, (ii) for income tax purposes, the amount of any payments and the cost of any property transferred to Transmission Provider for Transmission Provider's Interconnection Facilities will be capitalized by Interconnection Customer as an intangible asset and recovered using the straight-line method over a useful life of twenty (20) years, and (iii) any portion of Transmission Provider's Interconnection Facilities that is a "dual-use intertie," within the meaning of IRS Notice 88-129, is reasonably expected to carry only a de minimis amount of electricity in the direction of the Large Generating Facility. For this purpose, "de minimis amount" means no more than 5 percent of the total power flows in both directions, calculated in accordance with the "5 percent test" set forth in IRS Notice 88-129. This is not intended to be an exclusive list of the relevant conditions that must be met to conform to IRS requirements for non-taxable treatment.

At Transmission Provider's request, Interconnection Customer shall provide Transmission Provider with a report from an independent engineer confirming its representation in clause (iii), above. Transmission Provider represents and covenants that the cost of Transmission Provider's Interconnection Facilities paid for by Interconnection Customer will have no net effect on the base upon which rates are determined.

5.17.3

Indemnification for the Cost Consequences of Current Tax Liability Imposed Upon Transmission Provider. Notwithstanding Article 5.17.1, Interconnection Customer shall protect, indemnify and hold harmless Transmission Provider from the cost consequences of any current tax liability imposed against Transmission Provider as the result of payments or property transfers made by Interconnection Customer to Transmission Provider under this LGIA for Interconnection Facilities, as well as any interest and penalties, other than interest and penalties attributable to any delay caused by Transmission Provider.

Transmission Provider shall not include a gross-up for the cost consequences of any current tax liability in the amounts it charges Interconnection Customer under this LGIA unless (i) Transmission Provider has determined, in good faith, that the payments or property transfers made by Interconnection Customer to Transmission Provider should be reported as income subject to taxation or (ii) any Governmental Authority directs Transmission Provider to report payments or property as income subject to taxation; provided, however, that Transmission Provider may require Interconnection Customer to provide security for

Interconnection Facilities, in a form reasonably acceptable to Transmission Provider (such as a parental guarantee or a letter of credit), in an amount equal to the cost consequences of any current tax liability under this Article 5.17. Interconnection Customer shall reimburse Transmission Provider for such costs on a fully grossed-up basis, in accordance with Article 5.17.4, within thirty (30) Calendar Days of receiving written notification from Transmission Provider of the amount due, including detail about how the amount was calculated.

The indemnification obligation shall terminate at the earlier of (1) the expiration of the ten year testing period and the applicable statute of limitation, as it may be extended by Transmission Provider upon request of the IRS, to keep these years open for audit or adjustment, or (2) the occurrence of a subsequent taxable event and the payment of any related indemnification obligations as contemplated by this Article 5.17.

5.17.4

Tax Gross-Up Amount. Interconnection Customer's liability for the cost consequences of any current tax liability under this Article 5.17 shall be calculated on a fully grossed-up basis. Except as may otherwise be agreed to by the parties, this means that Interconnection Customer will pay Transmission Provider, in addition to the amount paid for the Interconnection Facilities and Network Upgrades, an amount equal to (1) the current taxes imposed on Transmission Provider ("Current Taxes") on the excess of (a) the gross income realized by Transmission Provider as a result of payments or property transfers made by Interconnection Customer to Transmission Provider under this LGIA (without regard to any payments under this Article 5.17) (the "Gross Income Amount") over (b) the present value of future tax deductions for depreciation that will be available as a result of such payments or property transfers (the "Present Value Depreciation Amount"), plus (2) an additional amount sufficient to permit Transmission Provider to receive and retain, after the payment of all Current Taxes, an amount equal to the net amount described in clause (1).

For this purpose, (i) Current Taxes shall be computed based on Transmission Provider's composite federal and state tax rates at the time the payments or property transfers are received and Transmission Provider will be treated as being subject to tax at the highest marginal rates in effect at that time (the "Current Tax Rate"), and (ii) the Present Value Depreciation Amount shall be computed by discounting Transmission Provider's anticipated tax depreciation deductions as a result of such payments or property transfers by Transmission Provider's current weighted average cost of capital. Thus, the formula for calculating Interconnection Customer's liability to Transmission Owner pursuant to this Article 5.17.4 can be expressed as follows: (Current Tax Rate x (Gross Income Amount – Present Value of Tax Depreciation))/(1-Current

Tax Rate). Interconnection Customer's estimated tax liability in the event taxes are imposed shall be stated in Appendix A, Interconnection Facilities, Network Upgrades and Distribution Upgrades.

5.17.5 Private Letter Ruling or Change or Clarification of Law. At Interconnection Customer's request and expense, Transmission Provider shall file with the IRS a request for a private letter ruling as to whether any property transferred or sums paid, or to be paid, by Interconnection Customer to Transmission Provider under this LGIA are subject to federal income taxation. Interconnection Customer will prepare the initial draft of the request for a private letter ruling, and will certify under penalties of perjury that all facts represented in such request are true and accurate to the best of Interconnection Customer's knowledge. Transmission Provider and Interconnection Customer shall cooperate in good faith with respect to the submission of such request.

Transmission Provider shall keep Interconnection Customer fully informed of the status of such request for a private letter ruling and shall execute either a privacy act waiver or a limited power of attorney, in a form acceptable to the IRS, that authorizes Interconnection Customer to participate in all discussions with the IRS regarding such request for a private letter ruling. Transmission Provider shall allow Interconnection Customer to attend all meetings with IRS officials about the request and shall permit Interconnection Customer to prepare the initial drafts of any follow-up letters in connection with the request.

5.17.6 Subsequent Taxable Events. If, within ten (10) years from the date on which the relevant Transmission Provider's Interconnection Facilities are placed in service, (i) Interconnection Customer Breaches the covenants contained in Article 5.17.2, (ii) a "disqualification event" occurs within the meaning of IRS Notice 88-129, or (iii) this LGIA terminates and Transmission Provider retains ownership of the Interconnection Facilities and Network Upgrades, Interconnection Customer shall pay a tax gross-up for the cost consequences of any current tax liability imposed on Transmission Provider, calculated using the methodology described in Article 5.17.4 and in accordance with IRS Notice 90-60.

5.17.7 Contests. In the event any Governmental Authority determines that Transmission Provider's receipt of payments or property constitutes income that is subject to taxation, Transmission Provider shall notify Interconnection Customer, in writing, within thirty (30) Calendar Days of receiving notification of such determination by a Governmental Authority. Upon the timely written request by Interconnection Customer and at Interconnection Customer's sole expense, Transmission Provider may appeal, protest, seek abatement of, or otherwise oppose such determination. Upon Interconnection Customer's written request and sole expense, Transmission Provider may file a claim for refund with respect to

any taxes paid under this Article 5.17, whether or not it has received such a determination. Transmission Provider reserves the right to make all decisions with regard to the prosecution of such appeal, protest, abatement or other contest, including the selection of counsel and compromise or settlement of the claim, but Transmission Provider shall keep Interconnection Customer informed, shall consider in good faith suggestions from Interconnection Customer about the conduct of the contest, and shall reasonably permit Interconnection Customer or an Interconnection Customer representative to attend contest proceedings.

Interconnection Customer shall pay to Transmission Provider on a periodic basis, as invoiced by Transmission Provider, Transmission Provider's documented reasonable costs of prosecuting such appeal, protest, abatement or other contest. At any time during the contest, Transmission Provider may agree to a settlement either with Interconnection Customer's consent or after obtaining written advice from nationally-recognized tax counsel, selected by Transmission Provider, but reasonably acceptable to Interconnection Customer, that the proposed settlement represents a reasonable settlement given the hazards of litigation. Interconnection Customer's obligation shall be based on the amount of the settlement agreed to by Interconnection Customer, or if a higher amount, so much of the settlement that is supported by the written advice from nationally-recognized tax counsel selected under the terms of the preceding sentence. The settlement amount shall be calculated on a fully grossed-up basis to cover any related cost consequences of the current tax liability. Any settlement without Interconnection Customer's consent or such written advice will relieve Interconnection Customer from any obligation to indemnify Transmission Provider for the tax at issue in the contest.

5.17.8

Refund. In the event that (a) a private letter ruling is issued to Transmission Provider which holds that any amount paid or the value of any property transferred by Interconnection Customer to Transmission Provider under the terms of this LGIA is not subject to federal income taxation, (b) any legislative change or administrative announcement, notice, ruling or other determination makes it reasonably clear to Transmission Provider in good faith that any amount paid or the value of any property transferred by Interconnection Customer to Transmission Provider under the terms of this LGIA is not taxable to Transmission Provider, (c) any abatement, appeal, protest, or other contest results in a determination that any payments or transfers made by Interconnection Customer to Transmission Provider are not subject to federal income tax, or (d) if Transmission Provider receives a refund from any taxing authority for any overpayment of tax attributable to any payment or property transfer made by Interconnection Customer to Transmission Provider pursuant to this LGIA, Transmission Provider shall promptly refund to Interconnection Customer the following:

- (i) any payment made by Interconnection Customer under this Article 5.17 for taxes that is attributable to the amount determined to be non-taxable, together with interest thereon,
- (ii) interest on any amounts paid by Interconnection Customer to Transmission Provider for such taxes which Transmission Provider did not submit to the taxing authority, calculated in accordance with the methodology set forth in FERC's regulations at 18 CFR §35.19a(a)(2)(iii) from the date payment was made by Interconnection Customer to the date Transmission Provider refunds such payment to Interconnection Customer, and
- (iii) with respect to any such taxes paid by Transmission Provider, any refund or credit Transmission Provider receives or to which it may be entitled from any Governmental Authority, interest (or that portion thereof attributable to the payment described in clause (i), above) owed to Transmission Provider for such overpayment of taxes (including any reduction in interest otherwise payable by Transmission Provider to any Governmental Authority resulting from an offset or credit); provided, however, that Transmission Provider will remit such amount promptly to Interconnection Customer only after and to the extent that Transmission Provider has received a tax refund, credit or offset from any Governmental Authority for any applicable overpayment of income tax related to Transmission Provider's Interconnection Facilities.

The intent of this provision is to leave the Parties, to the extent practicable, in the event that no taxes are due with respect to any payment for Interconnection Facilities and Network Upgrades hereunder, in the same position they would have been in had no such tax payments been made.

5.17.9

Taxes Other Than Income Taxes. Upon the timely request by Interconnection Customer, and at Interconnection Customer's sole expense, Transmission Provider may appeal, protest, seek abatement of, or otherwise contest any tax (other than federal or state income tax) asserted or assessed against Transmission Provider for which Interconnection Customer may be required to reimburse Transmission Provider under the terms of this LGIA. Interconnection Customer shall pay to Transmission Provider on a periodic basis, as invoiced by Transmission Provider, Transmission Provider's documented reasonable costs of prosecuting such appeal, protest, abatement, or other contest. Interconnection Customer and Transmission Provider shall cooperate in good faith with respect to any such contest. Unless the payment of such taxes is a prerequisite to an appeal or abatement or cannot be deferred, no amount shall be payable by

Interconnection Customer to Transmission Provider for such taxes until they are assessed by a final, non-appealable order by any court or agency of competent jurisdiction. In the event that a tax payment is withheld and ultimately due and payable after appeal, Interconnection Customer will be responsible for all taxes, interest and penalties, other than penalties attributable to any delay caused by Transmission Provider.

5.17.10

Transmission Owners Who Are Not Transmission Providers. If Transmission Provider is not the same entity as the Transmission Owner, then (i) all references in this Article 5.17 to Transmission Provider shall be deemed also to refer to and to include the Transmission Owner, as appropriate, and (ii) this LGIA shall not become effective until such Transmission Owner shall have agreed in writing to assume all of the duties and obligations of Transmission Provider under this Article 5.17 of this LGIA.

5.18

Tax Status. Each Party shall cooperate with the other to maintain the other Party's tax status. Nothing in this LGIA is intended to adversely affect any Transmission Provider's tax exempt status with respect to the issuance of bonds including, but not limited to, Local Furnishing Bonds.

5.19 Modification.

5.19.1

General. Either Party may undertake modifications to its facilities. If a Party plans to undertake a modification that reasonably may be expected to affect the other Party's facilities, that Party shall provide to the other Party sufficient information regarding such modification so that the other Party may evaluate the potential impact of such modification prior to commencement of the work. Such information shall be deemed to be confidential hereunder and shall include information concerning the timing of such modifications and whether such modifications are expected to interrupt the flow of electricity from the Large Generating Facility. The Party desiring to perform such work shall provide the relevant drawings, plans, and specifications to the other Party at least ninety (90) Calendar Days in advance of the commencement of the work or such shorter period upon which the Parties may agree, which agreement shall not unreasonably be withheld, conditioned or delayed.

In the case of Large Generating Facility modifications that do not require Interconnection Customer to submit an Interconnection Request, Transmission Provider shall provide, within thirty (30) Calendar Days (or such other time as the Parties may agree), an estimate of any additional modifications to the Transmission System, Transmission Provider's Interconnection Facilities or Network Upgrades necessitated by such Interconnection Customer modification and a good faith estimate of the costs thereof.

5.19.2 Standards. Any additions, modifications, or replacements made to a Party's facilities shall be designed, constructed and operated in accordance with this LGIA and Good Utility Practice.

5.19.3 Modification Costs. Interconnection Customer shall not be directly assigned for the costs of any additions, modifications, or replacements that Transmission Provider makes to Transmission Provider's Interconnection Facilities or the Transmission System to facilitate the interconnection of a third party to Transmission Provider's Interconnection Facilities or the Transmission System, or to provide transmission service to a third party under Transmission Provider's Tariff. Interconnection Customer shall be responsible for the costs of any additions, modifications, or replacements to Interconnection Customer's Interconnection Facilities that may be necessary to maintain or upgrade such Interconnection Customer's Interconnection Facilities consistent with Applicable Laws and Regulations, Applicable Reliability Standards or Good Utility Practice.

Article 6. Testing and Inspection

6.1 Pre-Commercial Operation Date Testing and Modifications. Prior to the Commercial Operation Date, Transmission Provider shall test Transmission Provider's Interconnection Facilities and Network Upgrades and Interconnection Customer shall test the Large Generating Facility and Interconnection Customer's Interconnection Facilities to ensure their safe and reliable operation. Similar testing may be required after initial operation. Each Party shall make any modifications to its facilities that are found to be necessary as a result of such testing. Interconnection Customer shall bear the cost of all such testing and modifications. Interconnection Customer shall generate test energy at the Large Generating Facility only if it has arranged for the delivery of such test energy.

6.2 Post-Commercial Operation Date Testing and Modifications. Each Party shall at its own expense perform routine inspection and testing of its facilities and equipment in accordance with Good Utility Practice as may be necessary to ensure the continued interconnection of the Large Generating Facility with the Transmission System in a safe and reliable manner. Each Party shall have the right, upon advance written notice, to require reasonable additional testing of the other Party's facilities, at the requesting Party's expense, as may be in accordance with Good Utility Practice.

6.3 Right to Observe Testing. Each Party shall notify the other Party in advance of its performance of tests of its Interconnection Facilities. The other Party has the right, at its own expense, to observe such testing.

6.4 Right to Inspect. Each Party shall have the right, but shall have no obligation to: (i) observe the other Party's tests and/or inspection of any of its System Protection Facilities and other protective equipment, including Power System Stabilizers; (ii) review the settings of the other Party's System Protection Facilities and other protective equipment; and (iii) review the other Party's maintenance records relative to the

Interconnection Facilities, the System Protection Facilities and other protective equipment. A Party may exercise these rights from time to time as it deems necessary upon reasonable notice to the other Party. The exercise or non-exercise by a Party of any such rights shall not be construed as an endorsement or confirmation of any element or condition of the Interconnection Facilities or the System Protection Facilities or other protective equipment or the operation thereof, or as a warranty as to the fitness, safety, desirability, or reliability of same. Any information that a Party obtains through the exercise of any of its rights under this Article 6.4 shall be deemed to be Confidential Information and treated pursuant to Article 22 of this LGIA.

Article 7. Metering

7.1 General. Each Party shall comply with the Electric Reliability Organization requirements. Unless otherwise agreed by the Parties, Transmission Provider shall install Metering Equipment at the Point of Interconnection prior to any operation of the Large Generating Facility and shall own, operate, test and maintain such Metering Equipment. Power flows to and from the Large Generating Facility shall be measured at or, at Transmission Provider's option, compensated to, the Point of Interconnection. Transmission Provider shall provide metering quantities, in analog and/or digital form, to Interconnection Customer upon request. Interconnection Customer shall bear all reasonable documented costs associated with the purchase, installation, operation, testing and maintenance of the Metering Equipment.

7.2 Check Meters. Interconnection Customer, at its option and expense, may install and operate, on its premises and on its side of the Point of Interconnection, one or more check meters to check Transmission Provider's meters. Such check meters shall be for check purposes only and shall not be used for the measurement of power flows for purposes of this LGIA, except as provided in Article 7.4 below. The check meters shall be subject at all reasonable times to inspection and examination by Transmission Provider or its designee. The installation, operation and maintenance thereof shall be performed entirely by Interconnection Customer in accordance with Good Utility Practice.

7.3 Standards. Transmission Provider shall install, calibrate, and test revenue quality Metering Equipment in accordance with applicable ANSI standards.

7.4 Testing of Metering Equipment. Transmission Provider shall inspect and test all Transmission Provider-owned Metering Equipment upon installation and at least once every two (2) years thereafter. If requested to do so by Interconnection Customer, Transmission Provider shall, at Interconnection Customer's expense, inspect or test Metering Equipment more frequently than every two (2) years. Transmission Provider shall give reasonable notice of the time when any inspection or test shall take place, and Interconnection Customer may have representatives present at the test or inspection. If at any time Metering Equipment is found to be inaccurate or defective, it shall be adjusted, repaired or replaced at Interconnection Customer's expense, in order to provide accurate metering, unless the inaccuracy or defect is due to Transmission Provider's failure to

maintain, then Transmission Provider shall pay. If Metering Equipment fails to register, or if the measurement made by Metering Equipment during a test varies by more than two percent from the measurement made by the standard meter used in the test, Transmission Provider shall adjust the measurements by correcting all measurements for the period during which Metering Equipment was in error by using Interconnection Customer's check meters, if installed. If no such check meters are installed or if the period cannot be reasonably ascertained, the adjustment shall be for the period immediately preceding the test of the Metering Equipment equal to one-half the time from the date of the last previous test of the Metering Equipment.

7.5 Metering Data. At Interconnection Customer's expense, the metered data shall be telemetered to one or more locations designated by Transmission Provider and one or more locations designated by Interconnection Customer. Such telemetered data shall be used, under normal operating conditions, as the official measurement of the amount of energy delivered from the Large Generating Facility to the Point of Interconnection.

Article 8. Communications

8.1 Interconnection Customer Obligations. Interconnection Customer shall maintain satisfactory operating communications with Transmission Provider's Transmission System dispatcher or representative designated by Transmission Provider. Interconnection Customer shall provide standard voice line, dedicated voice line and facsimile communications at its Large Generating Facility control room or central dispatch facility through use of either the public telephone system, or a voice communications system that does not rely on the public telephone system. Interconnection Customer shall also provide the dedicated data circuit(s) necessary to provide Interconnection Customer data to Transmission Provider as set forth in Appendix D, Security Arrangements Details. The data circuit(s) shall extend from the Large Generating Facility to the location(s) specified by Transmission Provider. Any required maintenance of such communications equipment shall be performed by Interconnection Customer. Operational communications shall be activated and maintained under, but not be limited to, the following events: system paralleling or separation, scheduled and unscheduled shutdowns, equipment clearances, and hourly and daily load data.

8.2 Remote Terminal Unit. Prior to the Initial Synchronization Date of the Large Generating Facility, a Remote Terminal Unit, or equivalent data collection and transfer equipment acceptable to the Parties, shall be installed by Interconnection Customer, or by Transmission Provider at Interconnection Customer's expense, to gather accumulated and instantaneous data to be telemetered to the location(s) designated by Transmission Provider through use of a dedicated point-to-point data circuit(s) as indicated in Article 8.1. The communication protocol for the data circuit(s) shall be specified by Transmission Provider. Instantaneous bi-directional analog real power and reactive power flow information must be telemetered directly to the location(s) specified by Transmission Provider.

Each Party will promptly advise the other Party if it detects or otherwise learns of any metering, telemetry or communications equipment errors or malfunctions that require the attention and/or correction by the other Party. The Party owning such equipment shall correct such error or malfunction as soon as reasonably feasible.

8.3 No Annexation. Any and all equipment placed on the premises of a Party shall be and remain the property of the Party providing such equipment regardless of the mode and manner of annexation or attachment to real property, unless otherwise mutually agreed by the Parties.

8.4 Provision of Data from a Variable Energy Resource. Interconnection Customer whose Generating Facility contains at least one Variable Energy Resource shall provide meteorological and forced outage data to Transmission Provider to the extent necessary for Transmission Provider's development and deployment of power production forecasts for that class of Variable Energy Resources. Interconnection Customer with a Variable Energy Resource having wind as the energy source, at a minimum, will be required to provide Transmission Provider with site-specific meteorological data including: temperature, wind speed, wind direction, and atmospheric pressure. Interconnection Customer with a Variable Energy Resource having solar as the energy source, at a minimum, will be required to provide Transmission Provider with site-specific meteorological data including: temperature, atmospheric pressure, and irradiance. Transmission Provider and Interconnection Customer whose Generating Facility contains a Variable Energy Resource shall mutually agree to any additional meteorological data that are required for the development and deployment of a power production forecast. Interconnection Customer whose Generating Facility contains a Variable Energy Resource also shall submit data to Transmission Provider regarding all forced outages to the extent necessary for Transmission Provider's development and deployment of power production forecasts for that class of Variable Energy Resources. The exact specifications of the meteorological and forced outage data to be provided by Interconnection Customer to Transmission Provider, including the frequency and timing of data submittals, shall be made taking into account the size and configuration of the Variable Energy Resource, its characteristics, location, and its importance in maintaining generation resource adequacy and transmission system reliability in its area. All requirements for meteorological and forced outage data must be commensurate with the power production forecasting employed by Transmission Provider. Such requirements for meteorological and forced outage data are set forth in Appendix C, Interconnection Details, of this LGIA, as they may change from time to time.

Article 9. Operations

9.1 General. Each Party shall comply with the Electric Reliability Organization requirements. Each Party shall provide to the other Party all information that may reasonably be required by the other Party to comply with Applicable Laws and Regulations and Applicable Reliability Standards.

9.2 Balancing Authority Area Notification. At least three months before Initial Synchronization Date, Interconnection Customer shall notify Transmission Provider in writing of the Balancing Authority Area in which the Large Generating Facility will be located. If Interconnection Customer elects to locate the Large Generating Facility in a Balancing Authority Area other than the Balancing Authority Area in which the Large Generating Facility is physically located, and if permitted to do so by the relevant transmission tariffs, all necessary arrangements, including but not limited to those set forth in Article 7 and Article 8 of this LGIA, and remote Balancing Authority Area generator interchange agreements, if applicable, and the appropriate measures under such agreements, shall be executed and implemented prior to the placement of the Large Generating Facility in the other Balancing Authority Area.

9.3 Transmission Provider Obligations. Transmission Provider shall cause the Transmission System and Transmission Provider's Interconnection Facilities to be operated, maintained and controlled in a safe and reliable manner and in accordance with this LGIA. Transmission Provider may provide operating instructions to Interconnection Customer consistent with this LGIA and Transmission Provider's operating protocols and procedures as they may change from time to time. Transmission Provider will consider changes to its operating protocols and procedures proposed by Interconnection Customer.

9.4 Interconnection Customer Obligations. Interconnection Customer shall at its own expense operate, maintain and control the Large Generating Facility and Interconnection Customer's Interconnection Facilities in a safe and reliable manner and in accordance with this LGIA. Interconnection Customer shall operate the Large Generating Facility and Interconnection Customer's Interconnection Facilities in accordance with all applicable requirements of the Balancing Authority Area of which it is part, as such requirements are set forth in Appendix C, Interconnection Details, of this LGIA. Appendix C, Interconnection Details, will be modified to reflect changes to the requirements as they may change from time to time. Either Party may request that the other Party provide copies of the requirements set forth in Appendix C, Interconnection Details, of this LGIA.

9.5 Start-Up Synchronization and Commercial Operation. Consistent with the Parties' mutually acceptable procedures, Interconnection Customer is responsible for the proper synchronization of the Large Generating Facility to Transmission Provider's Transmission System. The pertinent information is provided in Exhibits 3 and 4 of Appendix C.

9.6 Reactive Power and Primary Frequency Response.

9.6.1 Power Factor Design Criteria.

9.6.1.1 Synchronous Generation. Interconnection Customer shall design the Large Generating Facility to maintain a composite power delivery at continuous rated power output at the Point of Interconnection at a power factor within the minimum range of

0.95 leading to 0.95 lagging, unless Transmission Provider has established different requirements that apply to all synchronous generators in the Balancing Authority Area on a comparable basis.

9.6.1.2 Non-Synchronous Generation. Interconnection Customer shall design the Large Generating Facility to maintain a composite power delivery at continuous rated power output at the high-side of the generator substation at a power factor within the range of 0.95 leading to 0.95 lagging, unless Transmission Provider has established a different power factor range that applies to all non-synchronous generators in the Balancing Authority Area on a comparable basis. This power factor range standard shall be dynamic and can be met using, for example, power electronics designed to supply this level of reactive capability (taking into account any limitations due to voltage level, real power output, etc.) or fixed and switched capacitors, or a combination of the two. This requirement shall only apply to newly interconnecting non-synchronous generators that have not yet executed a Facilities Study Agreement as of the effective date of the Final Rule establishing this requirement (Order No. 827).

9.6.2 Voltage Schedules. Once Interconnection Customer has synchronized the Large Generating Facility with the Transmission System, Transmission Provider shall require Interconnection Customer to operate the Large Generating Facility to produce or absorb reactive power within the design limitations of the Large Generating Facility in following the assigned voltage schedule. This may be a wider range than the minimum requirement set forth in Article 9.6.1 (Power Factor Design Criteria). Transmission Provider's voltage schedules shall treat all sources of reactive power in the Balancing Authority Area in an equitable and not unduly discriminatory manner. Transmission Provider shall exercise Reasonable Efforts to provide Interconnection Customer with such schedules at least one (1) day in advance, and may make changes to such schedules as necessary to maintain the reliability of the Transmission System. Interconnection Customer shall operate the Large Generating Facility to maintain the specified output voltage or power factor at the Point of Interconnection within the design limitations of the Large Generating Facility set forth in Article 9.6.1 (Power Factor Design Criteria). If Interconnection Customer is unable to maintain the specified voltage or power factor, it shall promptly notify the System Operator.

9.6.2.1 Voltage Regulators. Whenever the Large Generating Facility is operated in parallel with the Transmission System and voltage regulators are capable of operation, Interconnection Customer shall operate the Large Generating Facility with its voltage regulators in automatic operation. If the Large Generating Facility's voltage regulators are not capable of such automatic operation, Interconnection Customer shall immediately notify Transmission Provider's system operator, or its designated representative, and

ensure that such Large Generating Facility's reactive power production or absorption (measured in MVARs) are within the design capability of the Large Generating Facility's generating unit(s) and steady state stability limits. Interconnection Customer shall not cause its Large Generating Facility to disconnect automatically or instantaneously from the Transmission System or trip any generating unit comprising the Large Generating Facility for an under or over frequency condition unless the abnormal frequency condition persists for a time period beyond the limits set forth in ANSI/IEEE Standard C37.106, or such other standard as applied to other generators in the Balancing Authority Area on a comparable basis.

9.6.3 Payment for Reactive Power. Transmission Provider is required to pay Interconnection Customer for reactive power that Interconnection Customer provides or absorbs from the Large Generating Facility when Transmission Provider requests Interconnection Customer to operate its Large Generating Facility outside the range specified in Article 9.6.1. Payments shall be pursuant to Article 11.6 or such other agreement to which the Parties have otherwise agreed.

9.6.4 Primary Frequency Response. Interconnection Customer shall ensure the primary frequency response capability of its Large Generating Facility by installing, maintaining, and operating a functioning governor or equivalent controls. The term "functioning governor or equivalent controls" as used herein shall mean the required hardware and/or software that provides frequency responsive real power control with the ability to sense changes in system frequency and autonomously adjust the Large Generating Facility's real power output in accordance with the droop and deadband parameters and in the direction needed to correct frequency deviations. Interconnection Customer is required to install a governor or equivalent controls with the capability of operating: (1) with a maximum 5 percent droop and ± 0.036 Hz deadband; or (2) in accordance with the relevant droop, deadband, and timely and sustained response settings from an approved Electric Reliability Organization reliability standard providing for equivalent or more stringent parameters. The droop characteristic shall be: (1) based on the nameplate capacity of the Large Generating Facility, and shall be linear in the range of frequencies between 59 to 61 Hz that are outside of the deadband parameter; or (2) based an approved Electric Reliability Organization reliability standard providing for an equivalent or more stringent parameter. The deadband parameter shall be: the range of frequencies above and below nominal (60 Hz) in which the governor or equivalent controls is not expected to adjust the Large Generating Facility's real power output in response to frequency deviations. The deadband shall be implemented: (1) without a step to the droop curve, that is, once the frequency deviation exceeds the deadband parameter, the expected change in the Large Generating Facility's real power output in response to frequency deviations shall start from zero and then increase (for under-frequency deviations) or decrease (for over-frequency deviations) linearly in

proportion to the magnitude of the frequency deviation; or (2) in accordance with an approved Electric Reliability Organization reliability standard providing for an equivalent or more stringent parameter. Interconnection Customer shall notify Transmission Provider that the primary frequency response capability of the Large Generating Facility has been tested and confirmed during commissioning. Once Interconnection Customer has synchronized the Large Generating Facility with the Transmission System, Interconnection Customer shall operate the Large Generating Facility consistent with the provisions specified in Articles 9.6.4.1 and 9.6.4.2 of this Agreement. The primary frequency response requirements contained herein shall apply to both synchronous and non-synchronous Large Generating Facilities.

9.6.4.1 Governor or Equivalent Controls. Whenever the Large Generating Facility is operated in parallel with the Transmission System, Interconnection Customer shall operate the Large Generating Facility with its governor or equivalent controls in service and responsive to frequency. Interconnection Customer shall: (1) in coordination with Transmission Provider and/or the relevant balancing authority, set the deadband parameter to: (1) a maximum of ± 0.036 Hz and set the droop parameter to a maximum of 5 percent; or (2) implement the relevant droop and deadband settings from an approved Electric Reliability Organization reliability standard that provides for equivalent or more stringent parameters. Interconnection Customer shall be required to provide the status and settings of the governor or equivalent controls to Transmission Provider and/or the relevant balancing authority upon request. If Interconnection Customer needs to operate the Large Generating Facility with its governor or equivalent controls not in service, Interconnection Customer shall immediately notify Transmission Provider and the relevant balancing authority, and provide both with the following information: (1) the operating status of the governor or equivalent controls (i.e., whether it is currently out of service or when it will be taken out of service); (2) the reasons for removing the governor or equivalent controls from service; and (3) a reasonable estimate of when the governor or equivalent controls will be returned to service. Interconnection Customer shall make Reasonable Efforts to return its governor or equivalent controls into service as soon as practicable. Interconnection Customer shall make Reasonable Efforts to keep outages of the Large Generating Facility's governor or equivalent controls to a minimum whenever the Large Generating Facility is operated in parallel with the Transmission System.

9.6.4.2 Timely and Sustained Response. Interconnection Customer shall ensure that the Large Generating Facility's real power response to

sustained frequency deviations outside of the deadband setting is automatically provided and shall begin immediately after frequency deviates outside of the deadband, and to the extent the Large Generating Facility has operating capability in the direction needed to correct the frequency deviation. Interconnection Customer shall not block or otherwise inhibit the ability of the governor or equivalent controls to respond and shall ensure that the response is not inhibited, except under certain operational constraints including, but not limited to, ambient temperature limitations, physical energy limitations, outages of mechanical equipment, or regulatory requirements. The Large Generating Facility shall sustain the real power response at least until system frequency returns to a value within the deadband setting of the governor or equivalent controls. A Commission-approved reliability standard with equivalent or more stringent requirements shall supersede the above requirements.

9.6.4.3

Exemptions. Large Generating Facilities that are regulated by the United States Nuclear Regulatory Commission shall be exempt from Articles 9.6.4, 9.6.4.1, and 9.6.4.2 of this Agreement. Large Generating Facilities that are behind the meter generation that is sized-to-load (i.e., the thermal load and the generation are near-balanced in real-time operation and the generation is primarily controlled to maintain the unique thermal, chemical, or mechanical output necessary for the operating requirements of its host facility) shall be required to install primary frequency response capability in accordance with the droop and deadband capability requirements specified in Article 9.6.4, but shall be otherwise exempt from the operating requirements in Articles 9.6.4, 9.6.4.1, 9.6.4.2, and 9.6.4.4 of this Agreement.

9.6.4.4

Electric Storage Resources. Interconnection Customer interconnecting a Generating Facility that contains an electric storage resource shall establish an operating range in Appendix C of its LGIA that specifies a minimum state of charge and a maximum state of charge between which the electric storage resource will be required to provide primary frequency response consistent with the conditions set forth in Articles 9.6.4, 9.6.4.1, 9.6.4.2 and 9.6.4.3 of this Agreement. Appendix C shall specify whether the operating range is static or dynamic, and shall consider (1) the expected magnitude of frequency deviations in the interconnection; (2) the expected duration that system frequency will remain outside of the deadband parameter in the interconnection; (3) the expected incidence of frequency deviations outside of the deadband parameter in the interconnection; (4) the physical capabilities of the electric storage

resource; (5) operational limitations of the electric storage resource due to manufacturer specifications; and (6) any other relevant factors agreed to by Transmission Provider and Interconnection Customer, and in consultation with the relevant transmission owner or balancing authority as appropriate. If the operating range is dynamic, then Appendix C must establish how frequently the operating range will be reevaluated and the factors that may be considered during its reevaluation.

Interconnection Customer's electric storage resource is required to provide timely and sustained primary frequency response consistent with Article 9.6.4.2 of this Agreement when it is online and dispatched to inject electricity to the Transmission System and/or receive electricity from the Transmission System. This excludes circumstances when the electric storage resource is not dispatched to inject electricity to the Transmission System and/or dispatched to receive electricity from the Transmission System. If Interconnection Customer's electric storage resource is charging at the time of a frequency deviation outside of its deadband parameter, it is to increase (for over-frequency deviations) or decrease (for under-frequency deviations) the rate at which it is charging in accordance with its droop parameter. Interconnection Customer's electric storage resource is not required to change from charging to discharging, or vice versa, unless the response necessitated by the droop and deadband settings requires it to do so and it is technically capable of making such a transition.

9.7 Outages and Interruptions.

9.7.1 Outages.

9.7.1.1 **Outage Authority and Coordination.** Each Party may in accordance with Good Utility Practice in coordination with the other Party remove from service any of its respective Interconnection Facilities or Network Upgrades that may impact the other Party's facilities as necessary to perform maintenance or testing or to install or replace equipment. Absent an Emergency Condition, the Party scheduling a removal of such facility(ies) from service will use Reasonable Efforts to schedule such removal on a date and time mutually acceptable to the Parties. In all circumstances, any Party planning to remove such facility(ies) from service shall use Reasonable Efforts to minimize the effect on the other Party of such removal.

9.7.1.2 **Outage Schedules.** Transmission Provider shall post scheduled outages of its transmission facilities on the OASIS. Interconnection Customer shall submit its planned maintenance

schedules for the Large Generating Facility to Transmission Provider for a minimum of a rolling twenty-four month period. Interconnection Customer shall update its planned maintenance schedules as necessary. Transmission Provider may request Interconnection Customer to reschedule its maintenance as necessary to maintain the reliability of the Transmission System; provided, however, adequacy of generation supply shall not be a criterion in determining Transmission System reliability. Transmission Provider shall compensate Interconnection Customer for any additional direct costs that Interconnection Customer incurs as a result of having to reschedule maintenance, including any additional overtime, breaking of maintenance contracts or other costs above and beyond the cost Interconnection Customer would have incurred absent Transmission Provider's request to reschedule maintenance. Interconnection Customer will not be eligible to receive compensation, if during the twelve (12) months prior to the date of the scheduled maintenance, Interconnection Customer had modified its schedule of maintenance activities.

9.7.1.3

Outage Restoration. If an outage on a Party's Interconnection Facilities or Network Upgrades adversely affects the other Party's operations or facilities, the Party that owns or controls the facility that is out of service shall use Reasonable Efforts to promptly restore such facility(ies) to a normal operating condition consistent with the nature of the outage. The Party that owns or controls the facility that is out of service shall provide the other Party, to the extent such information is known, information on the nature of the Emergency Condition, an estimated time of restoration, and any corrective actions required. Initial verbal notice shall be followed up as soon as practicable with written notice explaining the nature of the outage.

9.7.2 Interruption of Service. If required by Good Utility Practice to do so, Transmission Provider may require Interconnection Customer to interrupt or reduce deliveries of electricity if such delivery of electricity could adversely affect Transmission Provider's ability to perform such activities as are necessary to safely and reliably operate and maintain the Transmission System. The following provisions shall apply to any interruption or reduction permitted under this Article 9.7.2:

- 9.7.2.1** The interruption or reduction shall continue only for so long as reasonably necessary under Good Utility Practice;
- 9.7.2.2** Any such interruption or reduction shall be made on an equitable, non-discriminatory basis with respect to all generating facilities directly connected to the Transmission System;

9.7.2.3 When the interruption or reduction must be made under circumstances which do not allow for advance notice, Transmission Provider shall notify Interconnection Customer by telephone as soon as practicable of the reasons for the curtailment, interruption, or reduction, and, if known, its expected duration. Telephone notification shall be followed by written notification as soon as practicable;

9.7.2.4 Except during the existence of an Emergency Condition, when the interruption or reduction can be scheduled without advance notice, Transmission Provider shall notify Interconnection Customer in advance regarding the timing of such scheduling and further notify Interconnection Customer of the expected duration. Transmission Provider shall coordinate with Interconnection Customer using Good Utility Practice to schedule the interruption or reduction during periods of least impact to Interconnection Customer and Transmission Provider;

9.7.2.5 The Parties shall cooperate and coordinate with each other to the extent necessary in order to restore the Large Generating Facility, Interconnection Facilities, and the Transmission System to their normal operating state, consistent with system conditions and Good Utility Practice.

9.7.3 Ride Through Capability and Performance. The Transmission System is designed to automatically activate a load-shed program as required by the Electric Reliability Organization in the event of an under-frequency system disturbance. Interconnection Customer shall implement under-frequency and over-frequency relay set points for the Large Generating Facility as required by the Electric Reliability Organization to ensure frequency “ride through” capability of the Transmission System. Large Generating Facility response to frequency deviations of pre-determined magnitudes, both under-frequency and over-frequency deviations, shall be studied and coordinated with Transmission Provider in accordance with Good Utility Practice. Interconnection Customer shall also implement under-voltage and over-voltage relay set points, or equivalent electronic controls, as required by the Electric Reliability Organization to ensure voltage “ride through” capability of the Transmission System. The term “ride through” as used herein shall mean the ability of a Generating Facility to stay connected to and synchronized with the Transmission System during system disturbances within a range of under-frequency, over-frequency, under-voltage, and over-voltage conditions, in accordance with Good Utility Practice and consistent with any standards and guidelines that are applied to other Generating Facilities in the Balancing Authority Area on a comparable basis. For abnormal frequency conditions and voltage conditions within the “no trip zone” defined by Reliability Standard PRC-024-3 or successor mandatory ride through reliability standards, the non-synchronous Large Generating Facility must ensure that,

within any physical limitations of the Large Generating Facility, its control and protection settings are configured or set to (1) continue active power production during disturbance and post disturbance periods at pre-disturbance levels, unless reactive power priority mode is enabled or unless providing primary frequency response or fast frequency response; (2) minimize reductions in active power and remain within dynamic voltage and current limits, if reactive power priority mode is enabled, unless providing primary frequency response or fast frequency response; (3) not artificially limit dynamic reactive power capability during disturbances; and (4) return to pre-disturbance active power levels without artificial ramp rate limits if active power is reduced, unless providing primary frequency response or fast frequency response.

9.7.4 System Protection and Other Control Requirements.

- 9.7.4.1 System Protection Facilities.** Interconnection Customer shall, at its expense, install, operate and maintain System Protection Facilities as a part of the Large Generating Facility or Interconnection Customer's Interconnection Facilities. Transmission Provider shall install at Interconnection Customer's expense any System Protection Facilities that may be required on Transmission Provider's Interconnection Facilities or the Transmission System as a result of the interconnection of the Large Generating Facility and Interconnection Customer's Interconnection Facilities.
- 9.7.4.2** Each Party's protection facilities shall be designed and coordinated with other systems in accordance with Good Utility Practice.
- 9.7.4.3** Each Party shall be responsible for protection of its facilities consistent with Good Utility Practice.
- 9.7.4.4** Each Party's protective relay design shall incorporate the necessary test switches to perform the tests required in Article 6. The required test switches will be placed such that they allow operation of lockout relays while preventing breaker failure schemes from operating and causing unnecessary breaker operations and/or the tripping of Interconnection Customer's units.
- 9.7.4.5** Each Party will test, operate and maintain System Protection Facilities in accordance with Good Utility Practice.
- 9.7.4.6** Prior to the In-Service Date, and again prior to the Commercial Operation Date, each Party or its agent shall perform a complete calibration test and functional trip test of the System Protection Facilities. At intervals suggested by Good Utility Practice and following any apparent malfunction of the System Protection Facilities, each Party shall perform both calibration and functional

trip tests of its System Protection Facilities. These tests do not require the tripping of any in-service generation unit. These tests do, however, require that all protective relays and lockout contacts be activated.

9.7.5 Requirements for Protection. In compliance with Good Utility Practice, Interconnection Customer shall provide, install, own, and maintain relays, circuit breakers and all other devices necessary to remove any fault contribution of the Large Generating Facility to any short circuit occurring on the Transmission System not otherwise isolated by Transmission Provider's equipment, such that the removal of the fault contribution shall be coordinated with the protective requirements of the Transmission System. Such protective equipment shall include, without limitation, a disconnecting device or switch with load-interrupting capability located between the Large Generating Facility and the Transmission System at a site selected upon mutual agreement (not to be unreasonably withheld, conditioned or delayed) of the Parties. Interconnection Customer shall be responsible for protection of the Large Generating Facility and Interconnection Customer's other equipment from such conditions as negative sequence currents, over- or under-frequency, sudden load rejection, over- or under-voltage, and generator loss-of-field. Interconnection Customer shall be solely responsible to disconnect the Large Generating Facility and Interconnection Customer's other equipment if conditions on the Transmission System could adversely affect the Large Generating Facility.

9.7.6 Power Quality. Neither Party's facilities shall cause excessive voltage flicker nor introduce excessive distortion to the sinusoidal voltage or current waves as defined by ANSI Standard C84.1-1989, in accordance with IEEE Standard 519, or any applicable superseding electric industry standard. In the event of a conflict between ANSI Standard C84.1-1989, or any applicable superseding electric industry standard, ANSI Standard C84.1-1989, or the applicable superseding electric industry standard, shall control.

9.8 Switching and Tagging Rules. Each Party shall provide the other Party a copy of its switching and tagging rules that are applicable to the other Party's activities. Such switching and tagging rules shall be developed on a non-discriminatory basis. The Parties shall comply with applicable switching and tagging rules, as amended from time to time, in obtaining clearances for work or for switching operations on equipment.

9.9 Use of Interconnection Facilities by Third Parties.

9.9.1 Purpose of Interconnection Facilities. Except as may be required by Applicable Laws and Regulations, or as otherwise agreed to among the Parties, the Interconnection Facilities shall be constructed for the sole purpose of interconnecting the Large Generating Facility to the Transmission System and shall be used for no other purpose.

9.9.2 Third Party Users. If required by Applicable Laws and Regulations or if the

Parties mutually agree, such agreement not to be unreasonably withheld, to allow one or more third parties to use Transmission Provider's Interconnection Facilities, or any part thereof, Interconnection Customer will be entitled to compensation for the capital expenses it incurred in connection with the Interconnection Facilities based upon the pro rata use of the Interconnection Facilities by Transmission Provider, all third party users, and Interconnection Customer, in accordance with Applicable Laws and Regulations or upon some other mutually-agreed upon methodology. In addition, cost responsibility for ongoing costs, including operation and maintenance costs associated with the Interconnection Facilities, will be allocated between Interconnection Customer and any third party users based upon the pro rata use of the Interconnection Facilities by Transmission Provider, all third party users, and Interconnection Customer, in accordance with Applicable Laws and Regulations or upon some other mutually agreed upon methodology. If the issue of such compensation or allocation cannot be resolved through such negotiations, it shall be submitted to FERC for resolution.

9.10 Disturbance Analysis Data Exchange. The Parties will cooperate with one another in the analysis of disturbances to either the Large Generating Facility or Transmission Provider's Transmission System by gathering and providing access to any information relating to any disturbance, including information from oscillography, protective relay targets, breaker operations and sequence of events records, and any disturbance information required by Good Utility Practice.

Article 10. Maintenance

10.1 Transmission Provider Obligations. Transmission Provider shall maintain the Transmission System and Transmission Provider's Interconnection Facilities in a safe and reliable manner and in accordance with this LGIA.

10.2 Interconnection Customer Obligations. Interconnection Customer shall maintain the Large Generating Facility and Interconnection Customer's Interconnection Facilities in a safe and reliable manner and in accordance with this LGIA.

10.3 Coordination. The Parties shall confer regularly to coordinate the planning, scheduling and performance of preventive and corrective maintenance on the Large Generating Facility and the Interconnection Facilities.

10.4 Secondary Systems. Each Party shall cooperate with the other in the inspection, maintenance, and testing of control or power circuits that operate below 600 volts, AC or DC, including, but not limited to, any hardware, control or protective devices, cables, conductors, electric raceways, secondary equipment panels, transducers, batteries, chargers, and voltage and current transformers that directly affect the operation of a Party's facilities and equipment which may reasonably be expected to impact the other Party. Each Party shall provide advance notice to the other Party before undertaking any

work on such circuits, especially on electrical circuits involving circuit breaker trip and close contacts, current transformers, or potential transformers.

10.5 Operating and Maintenance Expenses. Subject to the provisions herein addressing the use of facilities by others, and except for operations and maintenance expenses associated with modifications made for providing interconnection or transmission service to a third party and such third party pays for such expenses, Interconnection Customer shall be responsible for all reasonable expenses including overheads, associated with: (1) owning, operating, maintaining, repairing, and replacing Interconnection Customer's Interconnection Facilities; and (2) operation, maintenance, repair and replacement of Transmission Provider's Interconnection Facilities.

Article 11. Performance Obligation

11.1 Interconnection Customer Interconnection Facilities. Interconnection Customer shall design, procure, construct, install, own and/or control Interconnection Customer Interconnection Facilities described in Appendix A, Interconnection Facilities, Network Upgrades and Distribution Upgrades, at its sole expense.

11.2 Transmission Provider's Interconnection Facilities. Transmission Provider or Transmission Owner shall design, procure, construct, install, own and/or control Transmission Provider's Interconnection Facilities described in Appendix A, Interconnection Facilities, Network Upgrades and Distribution Upgrades, at the sole expense of Interconnection Customer.

11.3 Network Upgrades and Distribution Upgrades. Transmission Provider or Transmission Owner shall design, procure, construct, install, and own the Network Upgrades and Distribution Upgrades described in Appendix A, Interconnection Facilities, Network Upgrades and Distribution Upgrades. Interconnection Customer shall be responsible for all costs related to Distribution Upgrades. Unless Transmission Provider or Transmission Owner elects to fund the capital for the Network Upgrades, they shall be solely funded by Interconnection Customer.

11.4 Transmission Credits.

11.4.1 Repayment of Amounts Advanced for Network Upgrades. Interconnection Customer shall be entitled to a cash repayment, equal to the total amount paid to Transmission Provider and Affected System Operator, if any, for the Network Upgrades, including any tax gross-up or other tax-related payments associated with Network Upgrades, and not refunded to Interconnection Customer pursuant to Article 5.17.8 or otherwise, to be paid to Interconnection Customer on a dollar-for-dollar basis for the non-usage sensitive portion of transmission charges, as payments are made under Transmission Provider's Tariff and Affected System's Tariff for transmission services with respect to the Large

Generating Facility. Any repayment shall include interest calculated in accordance with the methodology set forth in FERC's regulations at 18 C.F.R. §35.19a(a)(2)(iii) from the date of any payment for Network Upgrades through the date on which Interconnection Customer receives a repayment of such payment pursuant to this subparagraph. Interconnection Customer may assign such repayment rights to any person.

Notwithstanding the foregoing, Interconnection Customer, Transmission Provider, and Affected System Operator may adopt any alternative payment schedule that is mutually agreeable so long as Transmission Provider and Affected System Operator take one of the following actions no later than five years from the Commercial Operation Date: (1) return to Interconnection Customer any amounts advanced for Network Upgrades not previously repaid, or (2) declare in writing that Transmission Provider or Affected System Operator will continue to provide payments to Interconnection Customer on a dollar-for-dollar basis for the non-usage sensitive portion of transmission charges, or develop an alternative schedule that is mutually agreeable and provides for the return of all amounts advanced for Network Upgrades not previously repaid; however, full reimbursement shall not extend beyond twenty (20) years from the Commercial Operation Date.

If the Large Generating Facility fails to achieve commercial operation, but it or another Generating Facility is later constructed and makes use of the Network Upgrades, Transmission Provider and Affected System Operator shall at that time reimburse Interconnection Customer for the amounts advanced for the Network Upgrades. Before any such reimbursement can occur, Interconnection Customer, or the entity that ultimately constructs the Generating Facility, if different, is responsible for identifying the entity to which reimbursement must be made.

11.4.2 Special Provisions for Affected Systems. Unless Transmission Provider provides, under the LGIA, for the repayment of amounts advanced to Affected System Operator for Network Upgrades, Interconnection Customer and Affected System Operator shall enter into an agreement that provides for such repayment. The agreement shall specify the terms governing payments to be made by Interconnection Customer to the Affected System Operator as well as the repayment by the Affected System Operator.

11.4.3 Notwithstanding any other provision of this LGIA, nothing herein shall be construed as relinquishing or foreclosing any rights, including but not limited to firm transmission rights, capacity rights, transmission congestion rights, or transmission credits, that Interconnection Customer, shall be entitled to, now or in the future under any other agreement or

tariff as a result of, or otherwise associated with, the transmission capacity, if any, created by the Network Upgrades, including the right to obtain cash reimbursements or transmission credits for transmission service that is not associated with the Large Generating Facility.

11.5 Provision of Security. At least thirty (30) Calendar Days prior to the commencement of the procurement, installation, or construction of a discrete portion of a Transmission Provider's Interconnection Facilities, Network Upgrades, or Distribution Upgrades, Interconnection Customer shall provide Transmission Provider, at Interconnection Customer's option, a guarantee, a surety bond, letter of credit or other form of security that is reasonably acceptable to Transmission Provider and is consistent with the Uniform Commercial Code of the jurisdiction identified in Article 14.2.1. Such security for payment, as specified in Appendix B of this LGIA, shall be in an amount sufficient to cover the costs for constructing, procuring and installing the applicable portion of Transmission Provider's Interconnection Facilities, Network Upgrades, or Distribution Upgrades and shall be reduced on a dollar-for-dollar basis for payments made to Transmission Provider for these purposes. Transmission Provider must use the LGIA Deposit required in Section 11.3 of the LGIP before requiring Interconnection Customer to submit security in addition to that LGIA Deposit. Transmission Provider must specify, in Appendix B of this LGIA, the dates for which Interconnection Customer must provide additional security for construction of each discrete portion of Transmission Provider's Interconnection Facilities, Network Upgrades, or Distribution Upgrades and Interconnection Customer must provide such additional security.

In addition:

11.5.1 The guarantee must be made by an entity that meets the creditworthiness requirements of Transmission Provider, and contain terms and conditions that guarantee payment of any amount that may be due from Interconnection Customer, up to an agreed-to maximum amount.

11.5.2 The letter of credit must be issued by a financial institution reasonably acceptable to Transmission Provider and must specify a reasonable expiration date.

11.5.3 The surety bond must be issued by an insurer reasonably acceptable to Transmission Provider and must specify a reasonable expiration date.

11.6 Interconnection Customer Compensation. If Transmission Provider requests or directs Interconnection Customer to provide a service pursuant to Articles 9.6.3 (Payment for Reactive Power), or 13.5.1 of this LGIA, Transmission Provider shall compensate Interconnection Customer in accordance with Interconnection Customer's applicable rate schedule then in effect unless the provision of such service(s) is subject to an RTO or ISO FERC-approved rate schedule. Interconnection Customer shall serve Transmission Provider or RTO or ISO with any filing of a proposed rate schedule at the time of such filing with FERC. To the extent that no rate schedule is in effect at the time Interconnection Customer is required to provide or absorb any Reactive Power under this

LGIA, Transmission Provider agrees to compensate Interconnection Customer in such amount as would have been due Interconnection Customer had the rate schedule been in effect at the time service commenced; provided, however, that such rate schedule must be filed at FERC or other appropriate Governmental Authority within sixty (60) Calendar Days of the commencement of service.

11.6.1 Interconnection Customer Compensation for Actions During Emergency Condition. Transmission Provider or RTO or ISO shall compensate Interconnection Customer for its provision of real and reactive power and other Emergency Condition services that Interconnection Customer provides to support the Transmission System during an Emergency Condition in accordance with Article 11.6.

Article 12. Invoice

12.1 General. Unless the Parties otherwise agree to a different period for invoices, each Party shall submit to the other Party, on a monthly basis, invoices of amounts due for the preceding month. Each invoice shall state the month to which the invoice applies and fully describe the services and equipment provided. The Parties may discharge mutual debts and payment obligations due and owing to each other on the same date through netting, in which case all amounts a Party owes to the other Party under this LGIA, including interest payments or credits, shall be netted so that only the net amount remaining due shall be paid by the owing Party.

12.2 Final Invoice. Within six months after completion of the construction of Transmission Provider's Interconnection Facilities and the Network Upgrades, Transmission Provider shall provide an invoice of the final cost of the construction of Transmission Provider's Interconnection Facilities and the Network Upgrades and shall set forth such costs in sufficient detail to enable Interconnection Customer to compare the actual costs with the estimates and to ascertain deviations, if any, from the cost estimates. Transmission Provider shall refund to Interconnection Customer any amount by which the actual payment by Interconnection Customer for estimated costs exceeds the actual costs of construction within thirty (30) Calendar Days of the issuance of such final construction invoice.

12.3 Payment. Invoices shall be rendered to the paying Party at the address specified in Appendix F. The Party receiving the invoice shall pay the invoice within thirty (30) Calendar Days of receipt. All payments shall be made in immediately available funds payable to the other Party, or by wire transfer to a bank named and account designated by the invoicing Party. Payment of invoices by either Party will not constitute a waiver of any rights or claims either Party may have under this LGIA.

12.4 Disputes. In the event of a billing dispute between Transmission Provider and Interconnection Customer, Transmission Provider shall continue to provide Interconnection Service under this LGIA as long as Interconnection Customer: (i) continues to make all payments not in dispute; and (ii) pays to Transmission Provider or

into an independent escrow account the portion of the invoice in dispute, pending resolution of such dispute. If Interconnection Customer fails to meet these two requirements for continuation of service, then Transmission Provider may provide notice to Interconnection Customer of a Default pursuant to Article 17. Within thirty (30) Calendar Days after the resolution of the dispute, the Party that owes money to the other Party shall pay the amount due with interest calculated in accord with the methodology set forth in FERC's regulations at 18 CFR § 35.19a(a)(2)(iii).

Article 13. Emergencies

13.1 Definition. “Emergency Condition” shall mean a condition or situation: (i) that in the judgment of the Party making the claim is imminently likely to endanger life or property; or (ii) that, in the case of Transmission Provider, is imminently likely (as determined in a non-discriminatory manner) to cause a material adverse effect on the security of, or damage to the Transmission System, Transmission Provider’s Interconnection Facilities or the Transmission Systems of others to which the Transmission System is directly connected; or (iii) that, in the case of Interconnection Customer, is imminently likely (as determined in a non-discriminatory manner) to cause a material adverse effect on the security of, or damage to, the Large Generating Facility or Interconnection Customer’s Interconnection Facilities. System restoration and black start shall be considered Emergency Conditions; provided, that Interconnection Customer is not obligated by this LGIA to possess black start capability.

13.2 Obligations. Each Party shall comply with the Emergency Condition procedures of the applicable ISO/RTO, the Electric Reliability Organization, Applicable Laws and Regulations, and any emergency procedures agreed to by the Joint Operating Committee.

13.3 Notice. Transmission Provider shall notify Interconnection Customer promptly when it becomes aware of an Emergency Condition that affects Transmission Provider’s Interconnection Facilities or the Transmission System that may reasonably be expected to affect Interconnection Customer’s operation of the Large Generating Facility or Interconnection Customer’s Interconnection Facilities. Interconnection Customer shall notify Transmission Provider promptly when it becomes aware of an Emergency Condition that affects the Large Generating Facility or Interconnection Customer’s Interconnection Facilities that may reasonably be expected to affect the Transmission System or Transmission Provider’s Interconnection Facilities. To the extent information is known, the notification shall describe the Emergency Condition, the extent of the damage or deficiency, the expected effect on the operation of Interconnection Customer’s or Transmission Provider’s facilities and operations, its anticipated duration and the corrective action taken and/or to be taken. The initial notice shall be followed as soon as practicable with written notice.

13.4 Immediate Action. Unless, in Interconnection Customer’s reasonable judgment, immediate action is required, Interconnection Customer shall obtain the consent of Transmission Provider, such consent to not be unreasonably withheld, prior to performing any manual switching operations at the Large Generating Facility or Interconnection

Customer's Interconnection Facilities in response to an Emergency Condition either declared by Transmission Provider or otherwise regarding the Transmission System.

13.5 Transmission Provider Authority.

13.5.1

General. Transmission Provider may take whatever actions or inactions with regard to the Transmission System or Transmission Provider's Interconnection Facilities it deems necessary during an Emergency Condition in order to (i) preserve public health and safety, (ii) preserve the reliability of the Transmission System or Transmission Provider's Interconnection Facilities, (iii) limit or prevent damage, and (iv) expedite restoration of service.

Transmission Provider shall use Reasonable Efforts to minimize the effect of such actions or inactions on the Large Generating Facility or Interconnection Customer's Interconnection Facilities. Transmission Provider may, on the basis of technical considerations, require the Large Generating Facility to mitigate an Emergency Condition by taking actions necessary and limited in scope to remedy the Emergency Condition, including, but not limited to, directing Interconnection Customer to shutdown, start-up, increase or decrease the real or reactive power output of the Large Generating Facility; implementing a reduction or disconnection pursuant to Article 13.5.2; directing Interconnection Customer to assist with blackstart (if available) or restoration efforts; or altering the outage schedules of the Large Generating Facility and Interconnection Customer's Interconnection Facilities. Interconnection Customer shall comply with all of Transmission Provider's operating instructions concerning Large Generating Facility real power and reactive power output within the manufacturer's design limitations of the Large Generating Facility's equipment that is in service and physically available for operation at the time, in compliance with Applicable Laws and Regulations.

13.5.2

Reduction and Disconnection. Transmission Provider may reduce Interconnection Service or disconnect the Large Generating Facility or Interconnection Customer's Interconnection Facilities, when such, reduction or disconnection is necessary under Good Utility Practice due to Emergency Conditions. These rights are separate and distinct from any right of curtailment of Transmission Provider pursuant to Transmission Provider's Tariff. When Transmission Provider can schedule the reduction or disconnection in advance, Transmission Provider shall notify Interconnection Customer of the reasons, timing and expected duration of the reduction or disconnection. Transmission Provider shall coordinate with Interconnection Customer using Good Utility Practice to schedule the reduction or disconnection during periods of least impact to Interconnection Customer and Transmission Provider. Any reduction or disconnection shall continue only for so long as reasonably necessary

under Good Utility Practice. The Parties shall cooperate with each other to restore the Large Generating Facility, the Interconnection Facilities, and the Transmission System to their normal operating state as soon as practicable consistent with Good Utility Practice.

13.6 Interconnection Customer Authority. Consistent with Good Utility Practice and the LGIA and the LGIP, Interconnection Customer may take actions or inactions with regard to the Large Generating Facility or Interconnection Customer's Interconnection Facilities during an Emergency Condition in order to (i) preserve public health and safety, (ii) preserve the reliability of the Large Generating Facility or Interconnection Customer's Interconnection Facilities, (iii) limit or prevent damage, and (iv) expedite restoration of service. Interconnection Customer shall use Reasonable Efforts to minimize the effect of such actions or inactions on the Transmission System and Transmission Provider's Interconnection Facilities. Transmission Provider shall use Reasonable Efforts to assist Interconnection Customer in such actions.

13.7 Limited Liability. Except as otherwise provided in Article 11.6.1 of this LGIA, neither Party shall be liable to the other for any action it takes in responding to an Emergency Condition so long as such action is made in good faith and is consistent with Good Utility Practice.

Article 14. Regulatory Requirements and Governing Law

14.1 Regulatory Requirements. Each Party's obligations under this LGIA shall be subject to its receipt of any required approval or certificate from one or more Governmental Authorities in the form and substance satisfactory to the applying Party, or the Party making any required filings with, or providing notice to, such Governmental Authorities, and the expiration of any time period associated therewith. Each Party shall in good faith seek and use its Reasonable Efforts to obtain such other approvals. Nothing in this LGIA shall require Interconnection Customer to take any action that could result in its inability to obtain, or its loss of, status or exemption under the Federal Power Act, the Public Utility Holding Company Act of 1935, as amended, or the Public Utility Regulatory Policies Act of 1978.

14.2 Governing Law.

14.2.1 The validity, interpretation and performance of this LGIA and each of its provisions shall be governed by the laws of the state where the Point of Interconnection is located, without regard to its conflicts of law principles.

14.2.2 This LGIA is subject to all Applicable Laws and Regulations.

14.2.3 Each Party expressly reserves the right to seek changes in, appeal, or otherwise contest any laws, orders, rules, or regulations of a Governmental Authority.

Article 15. Notices.

15.1 General. Unless otherwise provided in this LGIA, any notice, demand or request required or permitted to be given by either Party to the other and any instrument required or permitted to be tendered or delivered by either Party in writing to the other shall be effective when delivered and may be so given, tendered or delivered, by recognized national courier, or by depositing the same with the United States Postal Service with postage prepaid, for delivery by certified or registered mail, addressed to the Party, or personally delivered to the Party, at the address set out in Appendix F, Addresses for Delivery of Notices and Billings.

Either Party may change the notice information in this LGIA by giving five (5) Business Days written notice prior to the effective date of the change.

15.2 Billings and Payments. Billings and payments shall be sent to the addresses set out in Appendix F.

15.3 Alternative Forms of Notice. Any notice or request required or permitted to be given by a Party to the other and not required by this Agreement to be given in writing may be so given by telephone, facsimile or email to the telephone numbers and email addresses set out in Appendix F.

15.4 Operations and Maintenance Notice. Each Party shall notify the other Party in writing of the identity of the person(s) that it designates as the point(s) of contact with respect to the implementation of Articles 9 and 10.

Article 16. Force Majeure

16.1 Force Majeure.

16.1.1 Economic hardship is not considered a Force Majeure event.

16.1.2 Neither Party shall be considered to be in Default with respect to any obligation hereunder, (including obligations under Article 4), other than the obligation to pay money when due, if prevented from fulfilling such obligation by Force Majeure. A Party unable to fulfill any obligation hereunder (other than an obligation to pay money when due) by reason of Force Majeure shall give notice and the full particulars of such Force Majeure to the other Party in writing or by telephone as soon as reasonably possible after the occurrence of the cause relied upon. Telephone notices given pursuant to this article shall be confirmed in writing as soon as reasonably possible and shall specifically state full particulars of the Force Majeure, the time and date when the Force

Majeure occurred and when the Force Majeure is reasonably expected to cease. The Party affected shall exercise due diligence to remove such disability with reasonable dispatch, but shall not be required to accede or agree to any provision not satisfactory to it in order to settle and terminate a strike or other labor disturbance.

Article 17. Default

17.1 Default

17.1.1 General. No Default shall exist where such failure to discharge an obligation (other than the payment of money) is the result of Force Majeure as defined in this LGIA or the result of an act or omission of the other Party. Upon a Breach, the non-breaching Party shall give written notice of such Breach to the breaching Party. Except as provided in Article 17.1.2, the breaching Party shall have thirty (30) Calendar Days from receipt of the Default notice within which to cure such Breach; provided however, if such Breach is not capable of cure within thirty (30) Calendar Days, the breaching Party shall commence such cure within thirty (30) Calendar Days after notice and continuously and diligently complete such cure within ninety (90) Calendar Days from receipt of the Default notice; and, if cured within such time, the Breach specified in such notice shall cease to exist.

17.1.2 Right to Terminate. If a Breach is not cured as provided in this article, or if a Breach is not capable of being cured within the period provided for herein, the non-breaching Party shall have the right to declare a Default and terminate this LGIA by written notice at any time until cure occurs, and be relieved of any further obligation hereunder and, whether or not that Party terminates this LGIA, to recover from the breaching Party all amounts due hereunder, plus all other damages and remedies to which it is entitled at law or in equity. The provisions of this article will survive termination of this LGIA.

Article 18. Indemnity, Consequential Damages and Insurance

18.1 Indemnity. The Parties shall at all times indemnify, defend, and hold the other Party harmless from, any and all damages, losses, claims, including claims and actions relating to injury to or death of any person or damage to property, demand, suits, recoveries, costs and expenses, court costs, attorney fees, and all other obligations by or to third parties, arising out of or resulting from the other Party's action or inactions of its obligations under this LGIA on behalf of the Indemnifying Party, except in cases of gross negligence or intentional wrongdoing by the indemnified Party.

18.1.1 **Indemnified Person.** If an Indemnified Person is entitled to indemnification under this Article 18 as a result of a claim by a third party, and the Indemnifying Party fails, after notice and reasonable opportunity to proceed under Article 18.1, to assume the defense of such claim, such Indemnified Person may at the expense of the Indemnifying Party contest, settle or consent to the entry of any judgment with respect to, or pay in full, such claim.

18.1.2 **Indemnifying Party.** If an Indemnifying Party is obligated to indemnify and hold any Indemnified Person harmless under this Article 18, the amount owing to the Indemnified Person shall be the amount of such Indemnified Person's actual Loss, net of any insurance or other recovery.

18.1.3 **Indemnity Procedures.** Promptly after receipt by an Indemnified Person of any claim or notice of the commencement of any action or administrative or legal proceeding or investigation as to which the indemnity provided for in Article 18.1 may apply, the Indemnified Person shall notify the Indemnifying Party of such fact. Any failure of or delay in such notification shall not affect a Party's indemnification obligation unless such failure or delay is materially prejudicial to the Indemnifying Party.

The Indemnifying Party shall have the right to assume the defense thereof with counsel designated by such Indemnifying Party and reasonably satisfactory to the Indemnified Person. If the defendants in any such action include one or more Indemnified Persons and the Indemnifying Party and if the Indemnified Person reasonably concludes that there may be legal defenses available to it and/or other Indemnified Persons which are different from or additional to those available to the Indemnifying Party, the Indemnified Person shall have the right to select separate counsel to assert such legal defenses and to otherwise participate in the defense of such action on its own behalf. In such instances, the Indemnifying Party shall only be required to pay the fees and expenses of one additional attorney to represent an Indemnified Person or Indemnified Persons having such differing or additional legal defenses.

The Indemnified Person shall be entitled, at its expense, to participate in any such action, suit or proceeding, the defense of which has been assumed by the Indemnifying Party. Notwithstanding the foregoing, the Indemnifying Party (i) shall not be entitled to assume and control the defense of any such action, suit or proceedings if and to the extent that, in the opinion of the Indemnified Person and its counsel, such action, suit or proceeding involves the potential imposition of criminal liability on the Indemnified Person, or there exists a conflict or adversity of interest between the Indemnified Person and the Indemnifying Party, in such event the Indemnifying Party shall pay the reasonable expenses of the Indemnified Person, and (ii) shall not settle or consent to the entry of any

judgment in any action, suit or proceeding without the consent of the Indemnified Person, which shall not be reasonably withheld, conditioned or delayed.

18.2 Consequential Damages. Other than the Liquidated Damages heretofore described, in no event shall either Party be liable under any provision of this LGIA for any losses, damages, costs or expenses for any special, indirect, incidental, consequential, or punitive damages, including but not limited to loss of profit or revenue, loss of the use of equipment, cost of capital, cost of temporary equipment or services, whether based in whole or in part in contract, in tort, including negligence, strict liability, or any other theory of liability; provided, however, that damages for which a Party may be liable to the other Party under another agreement will not be considered to be special, indirect, incidental, or consequential damages hereunder.

18.3 Insurance. Each party shall, at its own expense, maintain in force throughout the period of this LGIA, and until released by the other Party, the following minimum insurance coverages, with insurers authorized to do business in the state where the Point of Interconnection is located:

18.3.1 Employers' Liability in the amount of One Million Dollars (\$1,000,000) and Workers' Compensation Insurance providing statutory benefits in accordance with the laws and regulations of the state in which the Point of Interconnection is located. Employers' Liability limits shall be One Million Dollars (\$1,000,000) each accident; One Million Dollars (\$1,000,000) disease – each employee; One Million Dollars (\$1,000,000) disease – policy limit.

18.3.2 Commercial General Liability Insurance including premises and operations, bodily injury, property damage, contractual liability coverage (including coverage for the contractual indemnification to the extent covered by insurance) products and completed operations coverage, coverage for explosion, collapse and underground hazards, and punitive damages to the extent normally available and a cross liability endorsement/separation of insureds clause, with limits of One Million Dollars (\$1,000,000) per occurrence/One Million Dollars (\$1,000,000) aggregate combined single limit for personal injury, bodily injury, including death and property damage.

18.3.3 Commercial Automobile Liability Insurance for coverage of owned (if any) and non-owned and hired vehicles, trailers or semi-trailers designed for travel on public roads, with a combined single limit of One Million Dollars (\$1,000,000) each accident for bodily injury, including death, and property damage.

18.3.4 Excess/Umbrella Liability Insurance over and above the Employers' Liability Commercial General Liability and Commercial Automobile

Liability Insurance coverage, with a combined single limit of Twenty Million Dollars (\$20,000,000) per occurrence/Twenty Million Dollars (\$20,000,000) aggregate.

18.3.5 The Commercial General Liability Insurance, Commercial Automobile Insurance and Excess/Umbrella Liability Insurance policies shall provide the other Party, its parent, associated and Affiliate companies and their respective directors, officers, agents, servants and employees (“Other Party Group”) with additional insured status. All policies shall contain provisions and each Party agrees that the insurers waive all rights of subrogation in accordance with the provisions of this LGIA against the Other Party Group and a Party shall provide thirty (30) Calendar Days advance written notice to the Other Party Group prior to the date of cancellation except for ten (10) Calendar Days’ notice of nonpayment of premium.

18.3.6 The Commercial General Liability Insurance and Commercial Automobile Liability Insurance policies shall contain provisions that specify that the policies are primary and shall apply to such extent without consideration for other policies separately carried and shall state that each insured is provided coverage as though a separate policy had been issued to each, except the insurer’s liability shall not be increased beyond the amount for which the insurer would have been liable had only one insured been covered. The Excess/Umbrella Liability insurance policy shall be noncontributory. Each Party shall be responsible for its respective deductibles or retentions.

18.3.7 The Commercial General Liability Insurance, Commercial Automobile Liability Insurance and Excess/Umbrella Liability Insurance policies, if written on a Claims First Made Basis, shall be maintained in full force and effect for two (2) years after termination of this LGIA, which coverage may be in the form of tail coverage or extended reporting period coverage if agreed by the Parties.

18.3.8 Contractors Pollution Liability and/or Premises Pollution Liability and/or Sudden & Accidental Pollution in a liability policy: pollution coverage on an occurrence or claims-made basis with limits not less than One Million Dollars (\$1,000,000) per occurrence/claim/event and One Million Dollars (\$1,000,000) in annual aggregate. Coverage shall apply to pollution conditions arising out of the scope of work as described under the contract and shall include coverage for bodily injury, property damage, clean-up costs, and defense costs.

18.3.9 The requirements contained herein as to the types and limits of all insurance to be maintained by the Parties are not intended to and shall not in any manner, limit or qualify the liabilities and obligations assumed by

the Parties under this LGIA.

18.3.10 Within ten (10) Business Days following execution of this LGIA, and as soon as practicable after the end of each fiscal year or at the renewal of the insurance policy and in any event within ninety (90) Calendar Days thereafter, each Party shall provide certification of all insurance required in this LGIA, executed by each insurer or by an authorized representative of each insurer.

18.3.11 Notwithstanding the foregoing, each Party may self-insure, or utilize self-insured retentions, primary or excess policies to meet the minimum insurance requirements of Articles 18.3.1 through 18.3.8 to the extent it maintains a self-insurance program; provided that, such Party's senior secured debt is rated at investment grade or better by Standard & Poor's and that its self-insurance program meets the minimum insurance requirements of Articles 18.3.1 through 18.3.8. For any period of time that a Party's senior secured debt is unrated by Standard & Poor's or is rated at less than investment grade by Standard & Poor's, such Party shall comply with the insurance requirements applicable to it under Articles 18.3.1 through 18.3.9. In the event that a Party is permitted to self-insure pursuant to this article, it shall notify the other Party that it meets the requirements to self-insure and that its self-insurance program meets the minimum insurance requirements in a manner consistent with that specified in Article 18.3.9.

18.3.12 The Parties agree to report to each other in writing as soon as practical all accidents or occurrences resulting in injuries to any person, including death, and any property damage arising out of this LGIA to the extent such damage exceeds one hundred thousand dollars (\$100,000).

Article 19. Assignment

19.1 Assignment. This LGIA may be assigned by either Party only with the written consent of the other; provided that either Party may assign this LGIA without the consent of the other Party to any Affiliate of the assigning Party with an equal or greater credit rating and with the legal authority and operational ability to satisfy the obligations of the assigning Party under this LGIA; and provided further that Interconnection Customer shall have the right to assign this LGIA, without the consent of Transmission Provider, for collateral security purposes to aid in providing financing for the Large Generating Facility, provided that Interconnection Customer will promptly notify Transmission Provider of any such assignment. Any financing arrangement entered into by Interconnection Customer pursuant to this article will provide that prior to or upon the exercise of the secured party's, trustee's or mortgagee's assignment rights pursuant to said arrangement, the secured creditor, the trustee or mortgagee will notify Transmission Provider of the date and particulars of any such exercise of assignment right(s), including providing Transmission Provider with proof that it meets the requirements of Articles

11.5 and 18.3. Any attempted assignment that violates this article is void and ineffective. Any assignment under this LGIA shall not relieve a Party of its obligations, nor shall a Party's obligations be enlarged, in whole or in part, by reason thereof. Where required, consent to assignment will not be unreasonably withheld, conditioned or delayed.

Article 20. Severability

20.1 Severability. If any provision in this LGIA is finally determined to be invalid, void or unenforceable by any court or other Governmental Authority having jurisdiction, such determination shall not invalidate, void or make unenforceable any other provision, agreement or covenant of this LGIA; provided that if Interconnection Customer (or any third party, but only if such third party is not acting at the direction of Transmission Provider) seeks and obtains such a final determination with respect to any provision of the Alternate Option (Article 5.1.2), or the Negotiated Option (Article 5.1.4), then none of these provisions shall thereafter have any force or effect and the Parties' rights and obligations shall be governed solely by the Standard Option (Article 5.1.1).

Article 21. Comparability

21.1 Comparability. The Parties will comply with all applicable comparability and code of conduct laws, rules and regulations, as amended from time to time.

Article 22. Confidentiality

22.1 Confidentiality. Confidential Information shall include, without limitation, all information relating to a Party's technology, research and development, business affairs, and pricing, and any information supplied by either of the Parties to the other prior to the execution of this LGIA.

Information is Confidential Information only if it is clearly designated or marked in writing as confidential on the face of the document, or, if the information is conveyed orally or by inspection, if the Party providing the information orally informs the Party receiving the information that the information is confidential.

If requested by either Party, the other Party shall provide in writing, the basis for asserting that the information referred to in this Article 22 warrants confidential treatment, and the requesting Party may disclose such writing to the appropriate Governmental Authority. Each Party shall be responsible for the costs associated with affording confidential treatment to its information.

22.1.1 Term. During the term of this LGIA, and for a period of three (3) years after the expiration or termination of this LGIA, except as otherwise provided in this Article 22, each Party shall hold in confidence and shall

not disclose to any person Confidential Information.

22.1.2 **Scope.** Confidential Information shall not include information that the receiving Party can demonstrate: (1) is generally available to the public other than as a result of a disclosure by the receiving Party; (2) was in the lawful possession of the receiving Party on a non-confidential basis before receiving it from the disclosing Party; (3) was supplied to the receiving Party without restriction by a third party, who, to the knowledge of the receiving Party after due inquiry, was under no obligation to the disclosing Party to keep such information confidential; (4) was independently developed by the receiving Party without reference to Confidential Information of the disclosing Party; (5) is, or becomes, publicly known, through no wrongful act or omission of the receiving Party or Breach of this LGIA; or (6) is required, in accordance with Article 22.1.7 of the LGIA, Order of Disclosure, to be disclosed by any Governmental Authority or is otherwise required to be disclosed by law or subpoena, or is necessary in any legal proceeding establishing rights and obligations under this LGIA. Information designated as Confidential Information will no longer be deemed confidential if the Party that designated the information as confidential notifies the other Party that it no longer is confidential.

22.1.3 **Release of Confidential Information.** Neither Party shall release or disclose Confidential Information to any other person, except to its Affiliates (limited by the Standards of Conduct requirements), subcontractors, employees, consultants, or to parties who may be or considering providing financing to or equity participation with Interconnection Customer, or to potential purchasers or assignees of Interconnection Customer, on a need-to-know basis in connection with this LGIA, unless such person has first been advised of the confidentiality provisions of this Article 22 and has agreed to comply with such provisions. Notwithstanding the foregoing, a Party providing Confidential Information to any person shall remain primarily responsible for any release of Confidential Information in contravention of this Article 22.

22.1.4 **Rights.** Each Party retains all rights, title, and interest in the Confidential Information that each Party discloses to the other Party. The disclosure by each Party to the other Party of Confidential Information shall not be deemed a waiver by either Party or any other person or entity of the right to protect the Confidential Information from public disclosure.

22.1.5 **No Warranties.** By providing Confidential Information, neither Party makes any warranties or representations as to its accuracy or completeness. In addition, by supplying Confidential Information, neither Party obligates itself to provide any particular information or Confidential Information to the other Party nor to enter into any further agreements or

proceed with any other relationship or joint venture.

22.1.6 **Standard of Care.** Each Party shall use at least the same standard of care to protect Confidential Information it receives as it uses to protect its own Confidential Information from unauthorized disclosure, publication or dissemination. Each Party may use Confidential Information solely to fulfill its obligations to the other Party under this LGIA or its regulatory requirements.

22.1.7 **Order of Disclosure.** If a court or a Government Authority or entity with the right, power, and apparent authority to do so requests or requires either Party, by subpoena, oral deposition, interrogatories, requests for production of documents, administrative order, or otherwise, to disclose Confidential Information, that Party shall provide the other Party with prompt notice of such request(s) or requirement(s) so that the other Party may seek an appropriate protective order or waive compliance with the terms of this LGIA. Notwithstanding the absence of a protective order or waiver, the Party may disclose such Confidential Information which, in the opinion of its counsel, the Party is legally compelled to disclose. Each Party will use Reasonable Efforts to obtain reliable assurance that confidential treatment will be accorded any Confidential Information so furnished.

22.1.8 **Termination of Agreement.** Upon termination of this LGIA for any reason, each Party shall, within ten (10) Calendar Days of receipt of a written request from the other Party, use Reasonable Efforts to destroy, erase, or delete (with such destruction, erasure, and deletion certified in writing to the other Party) or return to the other Party, without retaining copies thereof, any and all written or electronic Confidential Information received from the other Party. Notwithstanding the foregoing, the receiving Party and its Affiliates may retain (i) such Confidential Information as is required to the extent necessary to comply with applicable law or regulation or their respective bona fide internal document retention procedures, and (ii) such Confidential Information as is maintained in archived electronic format for data restoration or business continuity purposes as long as such archived copies are not made generally available to receiving Party's personnel; provided, however, in either case, the receiving Party and any Affiliates retaining such Confidential Information in accordance with this Section 22.1.8 shall continue to be bound by the confidentiality obligations in this Agreement until such Confidential Information is returned or destroyed.

22.1.9 **Remedies.** The Parties agree that monetary damages would be inadequate to compensate a Party for the other Party's Breach of its obligations under this Article 22. Each Party accordingly agrees that the other Party shall be entitled to equitable relief, by way of injunction or otherwise, if the first Party Breaches or threatens to Breach its obligations under this Article 22,

which equitable relief shall be granted without bond or proof of damages, and the receiving Party shall not plead in defense that there would be an adequate remedy at law. Such remedy shall not be deemed an exclusive remedy for the Breach of this Article 22, but shall be in addition to all other remedies available at law or in equity. The Parties further acknowledge and agree that the covenants contained herein are necessary for the protection of legitimate business interests and are reasonable in scope. No Party, however, shall be liable for indirect, incidental, or consequential or punitive damages of any nature or kind resulting from or arising in connection with this Article 22.

22.1.10

Disclosure to FERC, its Staff, or a State. Notwithstanding anything in this Article 22 to the contrary, and pursuant to 18 CFR section 1b.20, if FERC or its staff, during the course of an investigation or otherwise, requests information from one of the Parties that is otherwise required to be maintained in confidence pursuant to this LGIA, the Party shall provide the requested information to FERC or its staff, within the time provided for in the request for information. In providing the information to FERC or its staff, the Party must, consistent with 18 CFR section 388.112, request that the information be treated as confidential and non-public by FERC and its staff and that the information be withheld from public disclosure. Parties are prohibited from notifying the other Party to this LGIA prior to the release of the Confidential Information to FERC or its staff. The Party shall notify the other Party to the LGIA when it is notified by FERC or its staff that a request to release Confidential Information has been received by FERC, at which time either of the Parties may respond before such information would be made public, pursuant to 18 CFR section 388.112. Requests from a state regulatory body conducting a confidential investigation shall be treated in a similar manner if consistent with the applicable state rules and regulations.

22.1.11

Subject to the exception in Article 22.1.10, any information that a Party claims is competitively sensitive, commercial or financial information under this LGIA (“Confidential Information”) shall not be disclosed by the other Party to any person not employed or retained by the other Party, except to the extent disclosure is (i) required by law; (ii) reasonably deemed by the disclosing Party to be required to be disclosed in connection with a dispute between or among the Parties, or the defense of litigation or dispute; (iii) otherwise permitted by consent of the other Party, such consent not to be unreasonably withheld; or (iv) necessary to fulfill its obligations under this LGIA or as a transmission service provider or a Balancing Authority Area operator including disclosing the Confidential Information to an RTO or ISO or to a regional or national reliability organization. The Party asserting confidentiality shall notify the other Party in writing of the information it claims is confidential. Prior to any disclosures of the other Party’s Confidential Information under this subparagraph, or if any third

party or Governmental Authority makes any request or demand for any of the information described in this subparagraph, the disclosing Party agrees to promptly notify the other Party in writing and agrees to assert confidentiality and cooperate with the other Party in seeking to protect the Confidential Information from public disclosure by confidentiality agreement, protective order or other reasonable measures.

Article 23. Environmental Releases

23.1 Each Party shall notify the other Party, first orally and then in writing, of the release of any Hazardous Substances, any asbestos or lead abatement activities, or any type of remediation activities related to the Large Generating Facility or the Interconnection Facilities, each of which may reasonably be expected to affect the other Party. The notifying Party shall: (i) provide the notice as soon as practicable, provided such Party makes a good faith effort to provide the notice no later than twenty-four hours after such Party becomes aware of the occurrence; and (ii) promptly furnish to the other Party copies of any publicly available reports filed with any Governmental Authorities addressing such events.

Article 24. Information Requirements

24.1 Information Acquisition. Transmission Provider and Interconnection Customer shall submit specific information regarding the electrical characteristics of their respective facilities to each other as described below and in accordance with Applicable Reliability Standards.

24.2 Information Submission by Transmission Provider. The initial information submission by Transmission Provider shall occur no later than one hundred eighty (180) Calendar Days prior to Trial Operation and shall include Transmission System information necessary to allow Interconnection Customer to select equipment and meet any system protection and stability requirements, unless otherwise agreed to by the Parties. On a monthly basis Transmission Provider shall provide Interconnection Customer a status report on the construction and installation of Transmission Provider's Interconnection Facilities and Network Upgrades, including, but not limited to, the following information: (1) progress to date; (2) a description of the activities since the last report (3) a description of the action items for the next period; and (4) the delivery status of equipment ordered.

24.3 Updated Information Submission by Interconnection Customer. The updated information submission by Interconnection Customer, including manufacturer information, shall occur no later than one hundred eighty (180) Calendar Days prior to the Trial Operation. Interconnection Customer shall submit a completed copy of the Large Generating Facility data requirements contained in Appendix 1 to the LGIP. It shall also include any additional information provided to Transmission Provider for the

Cluster Study and Facilities Study. Information in this submission shall be the most current Large Generating Facility design or expected performance data. Information submitted for stability models shall be compatible with Transmission Provider standard models. If there is no compatible model, Interconnection Customer will work with a consultant mutually agreed to by the Parties to develop and supply a standard model and associated information.

If Interconnection Customer's data is materially different from what was originally provided to Transmission Provider pursuant to the Interconnection Study Agreement between Transmission Provider and Interconnection Customer, then Transmission Provider will conduct appropriate studies to determine the impact on Transmission Provider Transmission System based on the actual data submitted pursuant to this Article 24.3. Interconnection Customer shall not begin Trial Operation until such studies are completed.

24.4 Information Supplementation. Prior to the Operation Date, the Parties shall supplement their information submissions described above in this Article 24 with any and all "as-built" Large Generating Facility information or "as-tested" performance information that differs from the initial submissions or, alternatively, written confirmation that no such differences exist. Interconnection Customer shall conduct tests on the Large Generating Facility as required by Good Utility Practice such as an open circuit "step voltage" test on the Large Generating Facility to verify proper operation of the Large Generating Facility's automatic voltage regulator.

Unless otherwise agreed, the test conditions shall include: (1) Large Generating Facility at synchronous speed; (2) automatic voltage regulator on and in voltage control mode; and (3) a five percent change in Large Generating Facility terminal voltage initiated by a change in the voltage regulators reference voltage. Interconnection Customer shall provide validated test recordings showing the responses of Large Generating Facility terminal and field voltages. In the event that direct recordings of these voltages is impractical, recordings of other voltages or currents that mirror the response of the Large Generating Facility's terminal or field voltage are acceptable if information necessary to translate these alternate quantities to actual Large Generating Facility terminal or field voltages is provided. Large Generating Facility testing shall be conducted and results provided to Transmission Provider for each individual generating unit in a station.

Subsequent to the Operation Date, Interconnection Customer shall provide Transmission Provider any information changes due to equipment replacement, repair, or adjustment. Transmission Provider shall provide Interconnection Customer any information changes due to equipment replacement, repair or adjustment in the directly connected substation or any adjacent Transmission Provider-owned substation that may affect Interconnection Customer's Interconnection Facilities equipment ratings, protection or operating requirements. The Parties shall provide such information no later than thirty (30) Calendar Days after the date of the equipment replacement, repair or adjustment.

Article 25. Information Access and Audit Rights

25.1 Information Access. Each Party (the “disclosing Party”) shall make available to the other Party information that is in the possession of the disclosing Party and is necessary in order for the other Party to: (i) verify the costs incurred by the disclosing Party for which the other Party is responsible under this LGIA; and (ii) carry out its obligations and responsibilities under this LGIA. The Parties shall not use such information for purposes other than those set forth in this Article 25.1 and to enforce their rights under this LGIA.

25.2 Reporting of Non-Force Majeure Events. Each Party (the “notifying Party”) shall notify the other Party when the notifying Party becomes aware of its inability to comply with the provisions of this LGIA for a reason other than a Force Majeure event. The Parties agree to cooperate with each other and provide necessary information regarding such inability to comply, including the date, duration, reason for the inability to comply, and corrective actions taken or planned to be taken with respect to such inability to comply. Notwithstanding the foregoing, notification, cooperation or information provided under this article shall not entitle the Party receiving such notification to allege a cause for anticipatory breach of this LGIA.

25.3 Audit Rights. Subject to the requirements of confidentiality under Article 22 of this LGIA, each Party shall have the right, during normal business hours, and upon prior reasonable notice to the other Party, to audit at its own expense the other Party’s accounts and records pertaining to either Party’s performance or either Party’s satisfaction of obligations under this LGIA. Such audit rights shall include audits of the other Party’s costs, calculation of invoiced amounts, Transmission Provider’s efforts to allocate responsibility for the provision of reactive support to the Transmission System, Transmission Provider’s efforts to allocate responsibility for interruption or reduction of generation on the Transmission System, and each Party’s actions in an Emergency Condition. Any audit authorized by this article shall be performed at the offices where such accounts and records are maintained and shall be limited to those portions of such accounts and records that relate to each Party’s performance and satisfaction of obligations under this LGIA. Each Party shall keep such accounts and records for a period equivalent to the audit rights periods described in Article 25.4.

25.4 Audit Rights Periods.

25.4.1 Audit Rights Period for Construction-Related Accounts and Records. Accounts and records related to the design, engineering, procurement, and construction of Transmission Provider's Interconnection Facilities and Network Upgrades shall be subject to audit for a period of twenty-four months following Transmission Provider's issuance of a final invoice in accordance with Article 12.2.

25.4.2 Audit Rights Period for All Other Accounts and Records. Accounts and records related to either Party's performance or satisfaction of all obligations under this LGIA other than those described in Article 25.4.1 shall be subject to audit as follows: (i) for an audit relating to cost obligations, the applicable audit rights period shall be twenty-four months after the auditing Party's receipt of an invoice giving rise to such cost obligations; and (ii) for an audit relating to all other obligations, the applicable audit rights period shall be twenty-four months after the event for which the audit is sought.

25.5 Audit Results. If an audit by a Party determines that an overpayment or an underpayment has occurred, a notice of such overpayment or underpayment shall be given to the other Party together with those records from the audit which support such determination.

Article 26. Subcontractors

26.1 General. Nothing in this LGIA shall prevent a Party from utilizing the services of any subcontractor as it deems appropriate to perform its obligations under this LGIA; provided, however, that each Party shall require its subcontractors to comply with all applicable terms and conditions of this LGIA in providing such services and each Party shall remain primarily liable to the other Party for the performance of such subcontractor.

26.2 Responsibility of Principal. The creation of any subcontract relationship shall not relieve the hiring Party of any of its obligations under this LGIA. The hiring Party shall be fully responsible to the other Party for the acts or omissions of any subcontractor the hiring Party hires as if no subcontract had been made; provided, however, that in no event shall Transmission Provider be liable for the actions or inactions of Interconnection Customer or its subcontractors with respect to obligations of Interconnection Customer under Article 5 of this LGIA. Any applicable obligation imposed by this LGIA upon the hiring Party shall be equally binding upon, and shall be construed as having application to, any subcontractor of such Party.

26.3 No Limitation by Insurance. The obligations under this Article 26 will not be limited in any way by any limitation of subcontractor's insurance.

Article 27. Disputes

27.1 Submission. In the event either Party has a dispute, or asserts a claim, that arises out of or in connection with this LGIA or its performance, such Party (the “disputing Party”) shall provide the other Party with written notice of the dispute or claim (“Notice of Dispute”). Such dispute or claim shall be referred to a designated senior representative of each Party for resolution on an informal basis as promptly as practicable after receipt of the Notice of Dispute by the other Party. In the event the designated representatives are unable to resolve the claim or dispute through unassisted or assisted negotiations within thirty (30) Calendar Days of the other Party’s receipt of the Notice of Dispute, such claim or dispute may, upon mutual agreement of the Parties, be submitted to arbitration and resolved in accordance with the arbitration procedures set forth below. In the event the Parties do not agree to submit such claim or dispute to arbitration, each Party may exercise whatever rights and remedies it may have in equity or at law consistent with the terms of this LGIA.

27.2 External Arbitration Procedures. Any arbitration initiated under this LGIA shall be conducted before a single neutral arbitrator appointed by the Parties. If the Parties fail to agree upon a single arbitrator within ten (10) Calendar Days of the submission of the dispute to arbitration, each Party shall choose one arbitrator who shall sit on a three-member arbitration panel. The two arbitrators so chosen shall within twenty (20) Calendar Days select a third arbitrator to chair the arbitration panel. In either case, the arbitrators shall be knowledgeable in electric utility matters, including electric transmission and bulk power issues, and shall not have any current or past substantial business or financial relationships with any party to the arbitration (except prior arbitration). The arbitrator(s) shall provide each of the Parties an opportunity to be heard and, except as otherwise provided herein, shall conduct the arbitration in accordance with the Commercial Arbitration Rules of the American Arbitration Association (“Arbitration Rules”) and any applicable FERC regulations or RTO rules; provided, however, in the event of a conflict between the Arbitration Rules and the terms of this Article 27, the terms of this Article 27 shall prevail.

27.3 Arbitration Decisions. Unless otherwise agreed by the Parties, the arbitrator(s) shall render a decision within ninety (90) Calendar Days of appointment and shall notify the Parties in writing of such decision and the reasons therefor. The arbitrator(s) shall be authorized only to interpret and apply the provisions of this LGIA and shall have no power to modify or change any provision of this Agreement in any manner. The decision of the arbitrator(s) shall be final and binding upon the Parties, and judgment on the award may be entered in any court having jurisdiction. The decision of the arbitrator(s) may be appealed solely on the grounds that the conduct of the arbitrator(s), or the decision itself, violated the standards set forth in the Federal Arbitration Act or the Administrative Dispute Resolution Act. The final decision of the arbitrator must also be filed with FERC if it affects jurisdictional rates, terms and conditions of service, Interconnection Facilities, or Network Upgrades.

27.4 Costs. Each Party shall be responsible for its own costs incurred during the arbitration

process and for the following costs, if applicable: (1) the cost of the arbitrator chosen by the Party to sit on the three member panel and one half of the cost of the third arbitrator chosen; or (2) one half the cost of the single arbitrator jointly chosen by the Parties.

Article 28. Representations, Warranties, and Covenants

28.1 General. Each Party makes the following representations, warranties and covenants:

28.1.1 **Good Standing.** Such Party is duly organized, validly existing and in good standing under the laws of the state in which it is organized, formed, or incorporated, as applicable; that it is qualified to do business in the state or states in which the Large Generating Facility, Interconnection Facilities and Network Upgrades owned by such Party, as applicable, are located; and that it has the corporate power and authority to own its properties, to carry on its business as now being conducted and to enter into this LGIA and carry out the transactions contemplated hereby and perform and carry out all covenants and obligations on its part to be performed under and pursuant to this LGIA.

28.1.2 **Authority.** Such Party has the right, power and authority to enter into this LGIA, to become a Party hereto and to perform its obligations hereunder. This LGIA is a legal, valid and binding obligation of such Party, enforceable against such Party in accordance with its terms, except as the enforceability thereof may be limited by applicable bankruptcy, insolvency, reorganization or other similar laws affecting creditors' rights generally and by general equitable principles (regardless of whether enforceability is sought in a proceeding in equity or at law).

28.1.3 **No Conflict.** The execution, delivery and performance of this LGIA does not violate or conflict with the organizational or formation documents, or bylaws or operating agreement, of such Party, or any judgment, license, permit, order, material agreement or instrument applicable to or binding upon such Party or any of its assets.

28.1.4 **Consent and Approval.** Such Party has sought or obtained, or, in accordance with this LGIA will seek or obtain, each consent, approval, authorization, order, or acceptance by any Governmental Authority in connection with the execution, delivery and performance of this LGIA, and it will provide to any Governmental Authority notice of any actions under this LGIA that are required by Applicable Laws and Regulations.

Article 29. Joint Operating Committee

29.1 Joint Operating Committee. Except in the case of ISOs and RTOs, Transmission Provider shall constitute a Joint Operating Committee to coordinate operating and technical considerations of Interconnection Service. At least six (6) months prior to the expected Initial Synchronization Date, Interconnection Customer and Transmission Provider shall each appoint one representative and one alternate to the Joint Operating Committee. Each Interconnection Customer shall notify Transmission Provider of its appointment in writing. Such appointments may be changed at any time by similar notice. The Joint Operating Committee shall meet as necessary, but not less than once each calendar year, to carry out the duties set forth herein. The Joint Operating Committee shall hold a meeting at the request of either Party, at a time and place agreed upon by the representatives. The Joint Operating Committee shall perform all of its duties consistent with the provisions of this LGIA. Each Party shall cooperate in providing to the Joint Operating Committee all information required in the performance of the Joint Operating Committee's duties. All decisions and agreements, if any, made by the Joint Operating Committee, shall be evidenced in writing. The duties of the Joint Operating Committee shall include the following:

- 29.1.1** Establish data requirements and operating record requirements.
- 29.1.2** Review the requirements, standards, and procedures for data acquisition equipment, protective equipment, and any other equipment or software.
- 29.1.3** Annually review the one (1) year forecast of maintenance and planned outage schedules of Transmission Provider's and Interconnection Customer's facilities at the Point of Interconnection.
- 29.1.4** Coordinate the scheduling of maintenance and planned outages on the Interconnection Facilities, the Large Generating Facility and other facilities that impact the normal operation of the interconnection of the Large Generating Facility to the Transmission System.
- 29.1.5** Ensure that information is being provided by each Party regarding equipment availability.
- 29.1.6** Perform such other duties as may be conferred upon it by mutual agreement of the Parties.

Article 30. Miscellaneous

- 30.1 Binding Effect.** This LGIA and the rights and obligations hereof, shall be binding upon and shall inure to the benefit of the successors and assigns of the Parties hereto.
- 30.2 Conflicts.** In the event of a conflict between the body of this LGIA and any attachment,

appendices or exhibits hereto, the terms and provisions of the body of this LGIA shall prevail and be deemed the final intent of the Parties.

30.3 Rules of Interpretation. This LGIA, unless a clear contrary intention appears, shall be construed and interpreted as follows: (1) the singular number includes the plural number and vice versa; (2) reference to any person includes such person's successors and assigns but, in the case of a Party, only if such successors and assigns are permitted by this LGIA, and reference to a person in a particular capacity excludes such person in any other capacity or individually; (3) reference to any agreement (including this LGIA), document, instrument or tariff means such agreement, document, instrument, or tariff as amended or modified and in effect from time to time in accordance with the terms thereof and, if applicable, the terms hereof; (4) reference to any Applicable Laws and Regulations means such Applicable Laws and Regulations as amended, modified, codified, or reenacted, in whole or in part, and in effect from time to time, including, if applicable, rules and regulations promulgated thereunder; (5) unless expressly stated otherwise, reference to any Article, Section or Appendix means such Article of this LGIA or such Appendix to this LGIA, or such Section to the LGIP or such Appendix to the LGIP, as the case may be; (6) "hereunder", "hereof", "herein", "hereto" and words of similar import shall be deemed references to this LGIA as a whole and not to any particular Article or other provision hereof or thereof; (7) "including" (and with correlative meaning "include") means including without limiting the generality of any description preceding such term; and (8) relative to the determination of any period of time, "from" means "from and including", "to" means "to but excluding" and "through" means "through and including".

30.4 Entire Agreement. This LGIA, including all Appendices and Schedules attached hereto, constitutes the entire agreement between the Parties with reference to the subject matter hereof, and supersedes all prior and contemporaneous understandings or agreements, oral or written, between the Parties with respect to the subject matter of this LGIA. There are no other agreements, representations, warranties, or covenants which constitute any part of the consideration for, or any condition to, either Party's compliance with its obligations under this LGIA.

30.5 No Third Party Beneficiaries. This LGIA is not intended to and does not create rights, remedies, or benefits of any character whatsoever in favor of any persons, corporations, associations, or entities other than the Parties, and the obligations herein assumed are solely for the use and benefit of the Parties, their successors in interest and, where permitted, their assigns.

30.6 Waiver. The failure of a Party to this LGIA to insist, on any occasion, upon strict performance of any provision of this LGIA will not be considered a waiver of any obligation, right, or duty of, or imposed upon, such Party.

Any waiver at any time by either Party of its rights with respect to this LGIA shall not be deemed a continuing waiver or a waiver with respect to any other failure to comply with any other obligation, right, duty of this LGIA. Termination or Default of this LGIA for

any reason by Interconnection Customer shall not constitute a waiver of Interconnection Customer's legal rights to obtain an interconnection from Transmission Provider. Any waiver of this LGIA shall, if requested, be provided in writing.

- 30.7 Headings.** The descriptive headings of the various Articles of this LGIA have been inserted for convenience of reference only and are of no significance in the interpretation or construction of this LGIA.
- 30.8 Multiple Counterparts.** This LGIA may be executed in two or more counterparts, each of which is deemed an original but all constitute one and the same instrument.
- 30.9 Amendment.** The Parties may by mutual agreement amend this LGIA by a written instrument duly executed by the Parties.
- 30.10 Modification by the Parties.** The Parties may by mutual agreement amend the Appendices to this LGIA by a written instrument duly executed by the Parties. Such amendment shall become effective and a part of this LGIA upon satisfaction of all Applicable Laws and Regulations.
- 30.11 Reservation of Rights.** Transmission Provider shall have the right to make a unilateral filing with FERC to modify this LGIA with respect to any rates, terms and conditions, charges, classifications of service, rule or regulation under section 205 or any other applicable provision of the Federal Power Act and FERC's rules and regulations thereunder, and Interconnection Customer shall have the right to make a unilateral filing with FERC to modify this LGIA pursuant to section 206 or any other applicable provision of the Federal Power Act and FERC's rules and regulations thereunder; provided that each Party shall have the right to protest any such filing by the other Party and to participate fully in any proceeding before FERC in which such modifications may be considered. Nothing in this LGIA shall limit the rights of the Parties or of FERC under sections 205 or 206 of the Federal Power Act and FERC's rules and regulations thereunder, except to the extent that the Parties otherwise mutually agree as provided herein.
- 30.12 No Partnership.** This LGIA shall not be interpreted or construed to create an association, joint venture, agency relationship, or partnership between the Parties or to impose any partnership obligation or partnership liability upon either Party. Neither Party shall have any right, power, or authority to enter into any agreement or undertaking for, or act on behalf of, or to act as or be an agent or representative of, or to otherwise bind, the other Party.

IN WITNESS WHEREOF, the Parties have executed this LGIA in duplicate originals, each of which shall constitute and be an original effective Agreement between the Parties.

**Southern Company Services, Inc.,
as agent for**

**Alabama Power Company,
Georgia Power Company, and
Mississippi Power Company**

By: _____

Title: VP, Transmission Operations and Policy

Date: 6/6/2025

SR Stockton I, LLC

By: _____

Title: CEO

Date: 6/6/2025

Tariff Record Data:

Record Content Description	Appendix A
Tariff Record Title	Interconnection Facilities, Network & Distribution Upgrades
Record Version Number	0.0.0
Option Code	A
Record Narrative Name	
Tariff Record ID	3820
Tariff Record Collation Value	283131936
Tariff Record Parent Identifier	3819
Proposed Date	2025-06-06
Priority Order	1000000000
Record Change Type	NEW
Record Content Type	2
Associated Filing Identifier	

Appendix A to LGIA

Interconnection Facilities, Network Upgrades, and Distribution Upgrades

Interconnection Customer's Generating Facility located in Baldwin County, Alabama consists of a solar photovoltaic (PV), inverter-based array which is co-located with the 24C-IC-1225 Generating Facility. The interconnection service for the 24C-IC-1224 Generating Facility is 80 MW at the Point of Interconnection and a total capacity of 101.2 MVA. The interconnection service for the 24C-IC-1225 Generating Facility is 180 MW at the Point of Interconnection and a total capacity of 220 MVA. The combined interconnection service for the 24C-IC-1224 and 24C-IC-1225 Generating Facilities is 260 MW at the Point of Interconnection and a total capacity of 321.2 MVA.

Scope of Service

In accordance with the provisions of Article 4.1, Interconnection Customer has selected Energy Resource Interconnection Service (ERIS). The Parties acknowledge that for ERIS to be provided, all of the facilities set forth below must be constructed and placed into operation prior to the initial synchronization of the Generating Facility to the Transmission System.

Multiple Interconnection Agreements Not Permitted

This Agreement governs the interconnection of Interconnection Customer's Generating Facility to Transmission Provider's electric system. Neither Interconnection Customer nor any of its Affiliates may execute another interconnection agreement for this project while this Agreement is in effect. In the event that Interconnection Customer or any of its Affiliates executes another interconnection agreement for this project, this Agreement shall be deemed terminated. For clarity, Article 17 (Default) shall not be applicable, and, therefore, Transmission Provider may promptly file a notice of termination with FERC.

Standard Option for Interconnection Facilities Engineering, Procurement, and Construction

Transmission Provider shall use the Standard Option under Article 5.1.1 (Standard Option) to design, procure and construct Transmission Provider's Interconnection Facilities and Network Upgrades. Transmission Provider is not responsible for construction, performance of work, or for making any arrangements with any third parties, related to any facilities that are Interconnection Customer's responsibility (e.g., Interconnection Customer's Interconnection Facilities and facilities owned by third parties such as Affected Systems (Table 4)); provided, however, that Transmission Provider shall coordinate with Affected System Operator(s) as required by FERC policy. Interconnection Customer shall be responsible for the construction and performance of work on such facilities referenced in the foregoing sentence, including (but not limited to) entering into applicable terms and conditions between Interconnection Customer and Affected System Operator related to payments to Affected System Operator for any such facilities and for the repayment of amounts advanced by Interconnection Customer to Affected System Operator.

Impacts of Changes to Transitional Cluster Study Assumptions

Changes to the assumptions upon which the 24C-IC-1224 Transitional Cluster Study was performed can occur following the 24C-IC-1224 final Transitional Cluster Study Report that can impact the scope of work, cost estimates, security requirements, and/or the milestone schedule provided in this Agreement.

If there is an extended period of time prior to the design, procurement, or construction of the 24C-IC-1224 project, Transmission Provider will review any material changes to the 24C-IC-1224 Transitional Cluster Study assumptions and determine if a re-study and/or an amendment of this Agreement is necessary. If it is determined that a re-study is needed, Transmission Provider shall provide notice to Interconnection Customer and a re-study will be conducted to identify any impacts to the 24C-IC-1224 interconnection. If it is determined that an amendment to this Agreement is necessary, the Parties will negotiate in good faith to amend this Agreement.

1. Interconnection Facilities:

(a) Interconnection Customer's Interconnection Facilities:

Interconnection Customer's Interconnection Facilities will consist of:

- two (2) main transformers,
- one (1) 230 kV generator tie line from the Generating Facility to the new 24C-IC-1224/1225 230 kV Interconnecting Substation, including associated structures, buswork, switches, etc.,
- two (2) 230 kV interrupting devices, associated disconnect switches, and relaying equipment for the Generating Facility, and
- at least two (2) fiber optic circuits (one for relay coordination and one for data exchange) from the Generating Facility to the new 24C-IC-1224/1225 230 kV Interconnecting Substation.

(b) Transmission Provider's Interconnection Facilities:

Table 1(b)		
Description of Project	Facility Owner	Estimated Cost
New 24C-IC-1224/1225 230 kV Interconnecting Substation <ul style="list-style-type: none">Terminate the customer-installed fiber optic cable from the proposed Generating Facility for relaying, remote tripping, and data communications.Install CTs/PTs and metering for two-way power flow.Install two (2) advanced power quality meter, PQ sensors, and associated equipment.Install a disconnect switch for the generator line coming into the substation.Install step distance protection scheme including relays and other associated equipment for the new 24C-IC-1224/1225 Generating Facility.	APC	\$375,000*
Total Cost for Transmission Provider's Interconnection Facilities for 24C-IC-1224		\$375,000

* This is Interconnection Customer's allocated portion of the Network Upgrade. This amount is subject to change, e.g., shared-queued requests are withdrawn, delayed, or terminated.

(c) System Protection Facilities:

Table 1(c)		
Description of Project	Facility Owner	Estimated Cost
<p>New 24C-IC-1224/1225 230 kV Interconnecting Substation</p> <ul style="list-style-type: none"> DCUB pilot line protection scheme for the North Baldwin SS 230kV Line <ul style="list-style-type: none"> Install relay package. Install line trap, tuners, and carrier set. DCUB pilot line protection scheme for the Barry SP 230 kV Line <ul style="list-style-type: none"> Install relay package. Install line trap, tuners, and carrier set. Anti-Islanding Protection <ul style="list-style-type: none"> Install one (1) relay for anti-islanding protection. Install two (2) single-channel, power-line carrier FSK receivers and one (1) single-channel FSK power-line carrier transmitter and associated equipment. Install two (2) additional power quality meters. 	APC	\$785,000*
<p>Barry SP 230 kV Substation (Stability Requirements)</p> <ul style="list-style-type: none"> Modify existing settings as needed for coordination. <ul style="list-style-type: none"> Set total Breaker Failure Clearing Time to meet stability requirements. Set total Zone 2 clearing time to meet stability requirements. Set total Zone 3 clearing time to meet stability requirements. 	APC	\$9,231*
<p>North Baldwin SS 230 kV Substation</p> <ul style="list-style-type: none"> Modify existing settings as needed for coordination. Anti-Islanding Protection <ul style="list-style-type: none"> Install one (1) single-channel, power-line carrier FSK receiver and one (1) single-channel FSK power-line carrier transmitter and associated equipment. 	APC	\$100,000*
Total Cost for System Protection Facilities for 24C-IC-1224		\$894,231

* This is Interconnection Customer's allocated portion of the Network Upgrade. This amount is subject to change, e.g., shared-queued requests are withdrawn, delayed, or terminated.

(d) Other Directly Assignable Costs:

Table 1(d)		
Description of Project	Facility Owner	Estimated Cost
Barry - Conecuh (FP&L) 230 kV Line <ul style="list-style-type: none"> Loop line into new 24C-IC-1224/1225 230 kV Interconnecting Substation. Survey. 	APC	\$815,000*
Transmission Outages <ul style="list-style-type: none"> Estimated costs of expenses associated with transmission outages necessary for the interconnection of the proposed Generating Facility. Four (4) weeks are estimated to be needed for these outages. 	APC	\$25,000*
Implementation Activities <ul style="list-style-type: none"> Implementation activities related to model validation/verification, stability analysis, voltage schedule analysis, power quality/RVC analysis, reactive power analysis, and sync and CO activities and approvals. 		\$100,000
Total Other Directly Assignable Costs for 24C-IC-1224		\$940,000

* This is Interconnection Customer's allocated portion of the Network Upgrade. This amount is subject to change, e.g., shared-queued requests are withdrawn, delayed, or terminated.

2. Network Upgrades:

(a) Stand Alone Network Upgrades:

Table 2(a)		
Description of Project	Facility Owner	Estimated Cost
New IC-1224/1225 230 kV Interconnecting Substation* <ul style="list-style-type: none"> New 230 kV ring bus substation consisting of three (3) 230 kV, three-cycle gang operated breakers. Install Disturbance Monitoring Equipment. Install AGC equipment. Install a badge reader for access to the switch house. Land acquisition and transfer costs. 	APC	\$2,705,000**
Total Cost for Stand Alone Network Upgrades for 24C-IC-1224		\$2,705,000

* Interconnection Customer to provide an acceptable site to Alabama Power Company (APC) for the new 24C-IC-1224/1225 230 kV Interconnecting Substation with all ingress/egress rights. Substation location, excavation, grading, erosion control, and access to be provided by Interconnection Customer in accordance with APC guidelines. Interconnection Customer shall purchase the substation property for the new 24C-IC-1224/1225 230 kV Interconnecting Substation and transfer ownership or deed the property over to APC.

** This is Interconnection Customer's allocated portion of the Network Upgrade. This amount is subject to change, e.g., shared-queued requests are withdrawn, delayed, or terminated.

(b) Substation Network Upgrades:

No Substation Network Upgrades identified.

(c) System Network Upgrades:

Contingent Facilities*	Table 2(c)**	
Description of Project	Facility Owner	Estimated Cost
Ellicott TS 230 kV Breaker Replacement • Replace eleven (11) 230 kV breakers.	APC	\$8,000,000
Total Cost for Contingent Facilities System Network Upgrades for 24C-IC-1224		\$8,000,000

* Interconnection Customer may become responsible for projects set forth in this Table, see *Impacts of Changes to Transitional Cluster Study Assumptions* section above.

** Projects listed in Table 2(c) are the projects identified in Table f.5.a in the 24C-IC-1224 Transitional Cluster Study Report.

3. Distribution Upgrades:

No Distribution Upgrades identified.

4. Affected System Upgrades:

The 24C-IC-1224 Transitional Cluster Study identified potential Affected Systems and Affected System upgrades. The potential Affected System upgrades are set forth in Table 4. Interconnection Customer is responsible for contracting (in accordance with Article 11.4.2 of this Agreement) and cooperating (in accordance with Section 3.6 of the LGIP) with such operators to determine the impact, if any, of the 24C-IC-1224 interconnection projects on the Affected Systems.

Prior to initial synchronization of the Generating Facility, each Affected System Operator must confirm to Transmission Provider that any impacts upon the relevant Affected System have been satisfactorily addressed. If Transmission Provider does not receive written confirmation from all Affected System Operators listed in Table 4 below prior to the Initial Synchronization Date set forth in the Milestone Table in Appendix B, the Initial Synchronization Date and subsequent milestones may be impacted.

Table 4	
Description of Project	Affected System Operator
Conecuh (FP&L) 230 kV Substation <ul style="list-style-type: none">• Potential additional requirements to be identified by FP&L.	Florida Power & Light (FP&L)
Dogwood TS (FP&L) 230 kV Substation <ul style="list-style-type: none">• Potential additional requirements to be identified by FP&L.• Anti-Islanding Protection<ul style="list-style-type: none">○ Install one (1) single-channel FSK power-line carrier transmitter and associated equipment.	Florida Power & Light (FP&L)
PowerSouth <ul style="list-style-type: none">• Potential upgrades to be determined by PS.	PowerSouth (PS)
Cooperative Energy <ul style="list-style-type: none">• Potential upgrades to be determined by CE.	Cooperative Energy (CE)
Tennessee Valley Authority <ul style="list-style-type: none">• Potential upgrades to be determined by TVA.	Tennessee Valley Authority (TVA)

5. Point of Interconnection:

The Point of Interconnection will be where the generator tie line terminates on the bus of the new 24C-IC-1224/1225 230 kV Interconnecting Substation (as shown in Exhibit 2 of Appendix C).

6. Point of Change of Ownership:

The Point of Change of Ownership is where Interconnection Customer's generator tie line terminates on APC's dead-end structure at the new 24C-IC-1224/1225 230 kV Interconnecting Substation.

7. Tax Liability:

Interconnection Customer's estimated tax liability under Article 5.17 of this Agreement as of the date of this Agreement is zero dollars (\$0).

Because Transmission Provider has not determined that the payments or property transfers to be made by Interconnection Customer to Transmission Provider should be reported as income subject to taxation, and since no Governmental Authority has directed Transmission Provider to report payments or property as income subject to taxation, zero tax will be initially collected for amounts paid by Interconnection Customer for Transmission Provider's Interconnection Facilities and for Network Upgrades; provided, however, Interconnection Customer shall provide security for potential tax liability for Transmission Provider's Interconnection Facilities in the amount and by the date set forth in the Milestone Table in Appendix B. If necessary, the amount of security shall be calculated and adjusted annually by Transmission Provider to reflect Transmission

Provider's exposure to the cost consequences of any current tax liability as of January 1 of each year and the annual security reassessment results shall be delivered to Interconnection Customer.

If the annual security reassessment results in a deficiency in the tax security amount, Interconnection Customer shall increase its amount of tax security within thirty (30) Calendar Days of receipt of a deficiency notice. If the annual security reassessment results in a reduction of the tax security amount, Interconnection Customer may choose to reduce its tax security amount or maintain the tax security in the current amount for the following year. If Interconnection Customer chooses to reduce its tax security amount, Interconnection Customer must first provide security in the new amount to Transmission Provider. Subsequent to receipt and acceptance of such new tax security, Transmission Provider shall return existing tax security within thirty (30) Calendar Days.

8. Transmission Line Outage Costs:

Interconnection Customer shall be responsible for, and shall reimburse Transmission Provider for, all costs and expenses incurred by or on behalf of Transmission Provider caused by or reasonably related to scheduled transmission line outages or other transmission facility outages associated with interconnection of the Generating Facility to Transmission Provider's Transmission System occurring prior to Commercial Operation. The categories of transmission line outages and an estimate of such transmission line outage costs are set forth below. The estimated length of the outage is four (4) weeks.

(a) Estimated Cost of Scheduled Transmission Line Outages: **\$25,000**

(b) Transmission Line Outage Cost Categories:

(i) Re-dispatch Costs. During some transmission outages, Transmission Provider must re-dispatch certain generation resources in order to meet load requirements. Transmission outages may result in the re-dispatch of generation in order to either (i) provide voltage support due to the loss of the Transmission System in the local area, or (ii) the inability to dispatch certain generation due to limited power flow capability caused by the transmission line outage. Such re-dispatch may increase the costs of operating the Transmission System. Interconnection Customer shall be liable for its share of such cost increases ("Re-Dispatch Costs").

For purposes of this provision, the term Re-Dispatch Costs shall mean the actual costs, determined on the basis of an hourly chronological generation production cost model ("Production Cost Analysis"), for additional power supplies to compensate for the additional voltage support and will be determined on as near to a real-time basis as possible and billed to Interconnection Customer. The Production Cost Analysis will analyze the difference in total production costs between a case that includes the generation required for local voltage support as a result of the outages and one without such generation for such voltage support. In performing this

analysis, the Production Cost Analysis may consider, among other factors, system load, fuel price, emissions allowance prices, generating unit characteristics, purchase power agreements, hydro energy schedules, nuclear operation, wholesale bilateral contracts, generating unit availability for the periods in question, and available economy purchases and sales.

- (ii) Purchase or Provision of Additional Electricity. When transmission lines or other Transmission System facilities are taken out of service, additional line loading may occur on other transmission lines. Consequently, additional transmission line losses may occur, and Transmission Provider must purchase or produce additional electricity to compensate for these power losses. To the extent these expenditures are attributable to transmission outages specifically caused by the interconnection of the Generating Facility to Transmission Provider's Transmission System, Transmission Provider will seek reimbursement from Interconnection Customer for such costs. The determination of the actual costs of additional power supplies to compensate for line losses incurred will be performed on as near to a real-time basis as possible and billed to Interconnection Customer.

Tariff Record Data:

Record Content Description	Appendix B
Tariff Record Title	Milestones
Record Version Number	0.0.0
Option Code	A
Record Narrative Name	
Tariff Record ID	3821
Tariff Record Collation Value	283131968
Tariff Record Parent Identifier	3819
Proposed Date	2025-06-06
Priority Order	1000000000
Record Change Type	NEW
Record Content Type	2
Associated Filing Identifier	

Appendix B to LGIA

Milestones

The below milestones have been mutually agreed to by the Parties:

MILESTONE TABLE			
MILESTONE	DATE	COST	RESPONSIBLE PARTY
LGIA Deposit	Due at execution of LGIA	N/A	Interconnection Customer
Non-Confidential Modeling Data Submitted/Confirmed	30 Calendar Days after execution	N/A	Interconnection Customer
Draft securities for potential tax liability and Initial Security for Project	30 Calendar Days after execution	N/A	Interconnection Customer
Provide written authorization to proceed	60 Calendar Days after execution	N/A	Interconnection Customer
Security for potential tax liability for Transmission Provider's Interconnection Facilities (Appendix A, Section 7)	60 Calendar Days after execution	\$54,150	Interconnection Customer
Initial Security for Project	60 Calendar Days after execution	N/A	Interconnection Customer
Pre-Construction Costs Due	60 Calendar Days after execution	\$2,948,541	Interconnection Customer
As-Planned PSCAD/PSSE Model Submittal	150 Calendar Days after execution	N/A	Interconnection Customer
Land Transfer Deadline	January 30, 2027	N/A	Interconnection Customer
1st Payment for Construction Costs Due	July 30, 2027	\$982,845	Interconnection Customer
2nd Payment for Construction Costs Due	January 30, 2028	\$982,845	Interconnection Customer
Continuing Security Deadline	June 30, 2028	TBD	Interconnection Customer
In-Service Date	July 30, 2028	N/A	Transmission Provider
Initial Synchronization Date	August 15, 2028	N/A	Interconnection Customer
Pre-COD Operational Validation Begins	September 15, 2028	N/A	Transmission Provider
Commercial Operation Date	November 30, 2028	N/A	Interconnection Customer

Transmission Provider's Interconnection Facilities cost, Network Upgrade costs, and/or milestone dates (including the payment milestones) may be subject to change if Interconnection Customer does not meet the deadlines set forth above in the Milestone Table.

1. Generating Facility Modeling Data:

Interconnection Customer shall provide Transmission Provider updated Generating Facility non-confidential modeling data (1) after execution of this Agreement, (2) prior to initial synchronization, and (3) prior to Commercial Operation.

Transmission Provider is required under the Federal Power Act to comply with mandatory reliability standards developed by NERC and approved by FERC. Among other things, these mandatory reliability standards require that Transmission Provider use modeling data for the Generating Facility in planning and reliability studies and to share such information with other NERC Reliability Entities. Thus, in order to permit Transmission Provider to comply with these mandatory obligations while protecting Interconnection Customer's confidential information, Interconnection Customer shall provide Generating Facility modeling data that is acceptable to Transmission Provider that may be utilized on a non-confidential basis.

The first set of non-confidential modeling data shall be provided by Interconnection Customer to Transmission Provider within thirty (30) Calendar Days after the execution of this Agreement. Interconnection Customer may fulfill this requirement by one of the following:

- (a) Confirm in writing that the Generating Facility modeling data provided by Interconnection Customer for the Interconnection Studies may be utilized on a non-confidential basis for the above stated purposes, or
- (b) Provide Generating Facility modeling data acceptable to Transmission Provider that may be utilized on a non-confidential basis for the above stated purposes.

When Interconnection Customer provides an updated set of non-confidential Generating Facility modeling data, the data shall fully comply with all of Transmission Provider's requirements, which may be found in the Generator Interconnection folder on Transmission Provider's OASIS website at <https://www.oasis.oati.com/SOCO>. Transmission Provider shall review the updated non-confidential modeling data and notify Interconnection Customer of any deficiencies. Interconnection Customer shall have thirty (30) Calendar Days to remedy any deficiencies with the modeling data. Importantly, missing a milestone date does not mean a simple "day for day" change (e.g., miss a milestone date by one (1) day does not necessarily mean the remaining milestone dates will simply move by one (1) day). Instead, there are a number of factors that may impact a revised schedule (e.g., outage scheduling, resource commitments, weather, Force Majeure events). Therefore, in the event a milestone date is missed, Transmission Provider will re-evaluate and reset the remaining dates set forth in the Milestone Table.

All changes to the Generating Facility modeling data will be evaluated for Material Modification. Any change considered to be a Material Modification will not be allowed under this Agreement.

At any time Interconnection Customer submits significant changes to Generating Facility equipment and/or design (as determined by Transmission Provider), such changes may

require Transmission Provider to conduct a re-study. Interconnection Customer shall be responsible for the costs to conduct any such re-study. The results of such re-study could require Parties to amend this Agreement to reflect updated projects, costs, and/or milestone schedule in order to continue work under this Agreement.

2. Deposit and Initial Security:

Deposit

At the time of execution of this Agreement, Interconnection Customer shall provide to Transmission Provider the LGIA Deposit in the amount set forth in the Milestone Table in this Appendix B.

Suspension

In the event Interconnection Customer suspends the work associated with the construction and installation of Transmission Provider's Interconnection Facilities and/or Network Upgrades under Article 5.16 of this Agreement, Interconnection Customer will provide Transmission Provider written notice of its intent to suspend work, including an estimate of the duration of suspension.

Suspension of the work under this Agreement may not exceed three (3) years. The three-year period shall begin on the date the suspension is requested, or the date of the written notice to Transmission Provider, if no effective date is specified. In order to resume work following suspension under this Agreement, in accordance with Transmission Provider's requirements, Interconnection Customer must request recommencement of work, make all outstanding payments, provide updated non-confidential Generating Facility modeling data, and provide acceptable security and/or payment as originally required in the Milestone Table above.

In order to proceed with this Agreement following a suspension, a re-study may be required to maintain the reliability of the electric system. The re-study may result in a new milestone schedule, and the required scope of interconnection upgrades and estimated costs may change. Interconnection Customer shall be responsible for the costs to conduct any such re-study, as required under this Agreement. Upon completion of the re-study, the Parties will amend this Agreement as appropriate. Such amendment must be executed prior to Southern Companies beginning construction of any Transmission Provider's Interconnection Facilities and/or Network Upgrades.

Initial Security

Interconnection Customer shall provide Transmission Provider the initial security in the amount(s), and no later than, the date(s) set forth in the Milestone Table. As Interconnection Customer makes payments, Interconnection Customer may reduce the amount of security for design, procurement, and construction of Transmission Provider's Interconnection Facilities (including transmission line outage costs) and Network Upgrades on a dollar-for-dollar basis as payments are made hereunder by providing new security equal to the new amount. Subsequent to receipt and acceptance of such new

security, Transmission Provider shall return the existing security within thirty (30) Calendar Days.

3. Design, Procurement, and Construction Commencement:

In order to commence design and procurement of Transmission Provider's Interconnection Facilities and Network Upgrades as set forth in Appendix A, Interconnection Customer shall, by the dates set forth in the Milestone Table, (i) provide to Transmission Provider a written authorization to proceed, (ii) pay pre-construction costs, and (iii) provide initial security and potential tax liability security for the project.

In order to commence construction of Transmission Provider's Interconnection Facilities and Network Upgrades as set forth in Appendix A, Interconnection Customer shall, by the dates set forth in the Milestone Table, (i) make the payment(s) and (ii) transfer land as required.

4. Continuing Security:

Continuing security for Interconnection Customer's obligations under this Agreement for, among other things, operation, maintenance, repair, and replacement of Transmission Provider's Interconnection Facilities and the Monthly Administration Charge, must be provided by Interconnection Customer by the date set forth in the Milestone Table. Attachment Q (Creditworthiness Procedures) of Transmission Provider's Tariff shall apply to these continuing security obligations.

5. Schedules:

- (a) Milestone dates set forth in the Milestone Table have been developed based upon a number of expected events and factors. Any changes to the dates set forth in the Milestone Table are subject to applicable requirements (e.g., extensions of the Commercial Operation Date by three (3) years or more are subject to Material Modification assessments) and some changes may not be permissible. It is possible that other events (e.g., outage scheduling, resource commitments, weather, Force Majeure events) may impact the ability of the Parties to meet the estimated In-Service Date, Initial Synchronization Date, and/or Commercial Operation Date. For example, outages at multiple locations may be needed in order to achieve in-service. If an event occurs that prevents Parties from meeting any such dates and extensions of those dates are permissible (e.g., extensions of the Commercial Operation Date of less than three (3) years), Parties will work diligently to agree to new dates.
- (b) In order to permit the project to achieve Commercial Operation by the date set forth in the Milestone Table, Interconnection Customer must meet the milestone dates set forth therein. Importantly, missing a milestone date does not mean a simple "day for day" change (e.g., miss a milestone date by one (1) day does not necessarily mean the remaining milestone dates will simply move by one (1) day). Instead, there are a number of factors that may impact a revised schedule (e.g., outage scheduling, resource commitments, weather, Force Majeure events).

Therefore, in the event a milestone date is missed, Transmission Provider will reevaluate the dates and, if a change to a date is permissible (e.g., after performance of a Material Modification assessment), reset the remaining dates set forth in the Milestone Table.

- (c) With regard to scheduling the outage(s) necessary to interconnect the Generating Facility to the Transmission System and to construct the Network Upgrades, Interconnection Customer shall coordinate with Transmission Provider in order to minimize the effect of the outage(s) on the electric system. In addition, delays to the interconnection of the Generating Facility or to the construction of Network Upgrades may occur if:
 - (i) Interconnection Customer fails to coordinate the scheduling of the outage(s) with Transmission Provider or fails to complete the construction of Interconnection Customer's Interconnection Facilities prior to the outage(s); or
 - (ii) Affected System Operator(s) fails to complete construction of Affected System Upgrades prior to the outage(s).

6. Site Control:

Check box if applicable []

Interconnection Customer with qualifying regulatory limitations must demonstrate 100% Site Control by {Transmission Provider to insert date one hundred eighty (180) Calendar Days from the effective date of this LGIA} or this Agreement may be terminated per Article 17 (Default) of this Agreement and Interconnection Customer may be subject to Withdrawal Penalties per Section 3.7.1.1 of Transmission Provider's LGIP (Calculation of the Withdrawal Penalty).

Tariff Record Data:

Record Content Description	Appendix C
Tariff Record Title	Interconnection Details
Record Version Number	0.0.0
Option Code	A
Record Narrative Name	
Tariff Record ID	3822
Tariff Record Collation Value	283132000
Tariff Record Parent Identifier	3819
Proposed Date	2025-06-06
Priority Order	1000000000
Record Change Type	NEW
Record Content Type	2
Associated Filing Identifier	

Appendix C to LGIA

Interconnection Details

The following requirements apply to Interconnection Customer's Generating Facility when operated in parallel with Transmission Provider's electric system, in accordance with Article 9.4.

1. Operating Limits:

In order to minimize objectionable and adverse operating conditions on the electric service provided to other customers by Transmission Provider, the Generating Facility shall meet the following operating criteria:

(a) Inverter Requirements.

Inverters shall comply at all times with Southern Companies' Transmission Interconnection Requirements for Inverter-Based Generation or any successor document(s) (unless Transmission Provider provides a written exemption for any specific requirement), which may be found in the Generator Interconnection folder on Transmission Provider's OASIS website at: <https://www.oasis.oati.com/SOCO>. Design and technical requirements for inverter-based generators include, but are not limited to:

- Protection and Coordination;
- Power Quality;
- Voltage, Reactive Power and Power Factor Control; and
- Dynamic Response to System Events (e.g., voltage/frequency ride-through, primary frequency response).

(b) Power System Stabilizers.

If an Interconnection Study performed for an Interconnection Customer indicated the Generating Facility causes or contributes to a power oscillation problem, then Interconnection Customer will be required to provide a damping function in accordance with this Agreement (Article 5.4) and Transmission Provider's Power System Stabilizer Policy. The Interconnection Studies for 24C-IC-1224 did not identify the need for a damping function to be provided. Transmission Provider's Power System Stabilizer Policy may be found in the Generator Interconnection folder on Transmission Provider's OASIS website at: <https://www.oasis.oati.com/SOCO>.

(c) Radio Frequency Interference.

Interconnection Customer shall operate all of its equipment that is capable of generating radio frequency energy in compliance with, and in no event allowing

such equipment to cause harmful interference as prohibited by, applicable law, including, but not limited to, Federal Communications Commission rules and 47 C.F.R. §15.5 (General Condition of Operation). Transmission Provider and Interconnection Customer will reasonably cooperate to identify the source of any allegedly harmful interference; provided, however, Interconnection Customer shall be solely responsible for promptly eliminating any harmful interference that is caused by Interconnection Customer's equipment. Failure to comply with these requirements will result in immediate disconnection; reconnection cannot occur until Interconnection Customer proves, to Transmission Provider's reasonable satisfaction, that the interference caused by Interconnection Customer's equipment is corrected.

2. Metering and Data Acquisition Requirements:

Metering and data acquisition requirements will be in accordance with the provisions of Articles 7 and 8 of this Agreement, and the following requirements.

(a) Retail Station Service.

Interconnection Customer shall be responsible for contacting and coordinating with the appropriate electric service provider to arrange for retail station service. The Metering Equipment provided for in this Agreement does not include Interconnection Customer's retail station service metering equipment unless approved as such by Transmission Provider.

(b) Metering Equipment not located at the Point of Interconnection.

(i) If the Parties mutually determine that Metering Equipment should be installed at the Generating Facility rather than the Point of Interconnection, Interconnection Customer shall be responsible for the purchase, installation, operation, testing, and maintenance of any such Metering Equipment installed at the Generating Facility. Interconnection Customer shall be responsible for installation, calibration, and testing of Metering Equipment installed at the Generating Facility per the requirements of Articles 7.3 and 7.4 of this Agreement.

(ii) Interconnection Customer shall be responsible for the purchase, installation, operation, testing, and maintenance of any data acquisition equipment, telemetry equipment, or other equipment and software necessary at the Generating Facility for the telemetry of metered data from the Generating Facility to Transmission Provider.

(iii) Metering Equipment not installed at the Point of Interconnection shall be adjusted for losses as mutually agreed from the location of metering to the Point of Interconnection in accordance with Good Utility Practices. Any Party performing such a study to determine the loss adjustment shall provide a copy to the other Party.

(c) Meteorological Data.

Interconnection Customer shall provide Transmission Provider with site-specific meteorological data, in accordance with Article 8.4, including but not limited to one (1) minute and hourly time-averaged measurements from data samples at ten (10) seconds or greater frequency for the following parameters at the Generating Facility: total global horizontal irradiance, total global radiation within the plane of the array, air temperature, relative humidity, barometric pressure, back of module surface temperature and other pertinent meteorological conditions.

3. Generator Balancing Service Arrangements:

Interconnection Customer must demonstrate, to Transmission Provider's reasonable satisfaction, that it has satisfied the requirements of this Section 3 of Appendix C prior to initial synchronization of the Generating Facility.

Interconnection Customer is responsible for ensuring that its actual Generating Facility output matches any delivery schedules (e.g., associated with a confirmed NAESB e-Tag) from the Generating Facility to (1) another Balancing Authority Area or (2) a load within Transmission Provider's Balancing Authority Area, consistent with the scheduling requirements of Transmission Provider, including ramping into and out of such delivery schedules, as measured at the Point of Interconnection, consistent with the scheduling requirements of Transmission Provider's Tariff and any applicable FERC-approved market structure.

Interconnection Customer shall arrange for the supply of energy when there is a difference between the actual Generating Facility output and the delivery schedules (e.g., associated with a confirmed NAESB e-Tag) from the Generating Facility to (1) another Balancing Authority Area or (2) a load within Transmission Provider's Balancing Authority Area (the "Generator Balancing Service Arrangements").

Options Interconnection Customer may use to satisfy its obligation for making such Generator Balancing Service Arrangements include, but are not limited to:

- (a) obtaining such service from another entity that (i) has generating resources deliverable within the applicable Balancing Authority Area, (ii) agrees to assume responsibility for providing such Generator Balancing Service Arrangements to Interconnection Customer, and (iii) has appropriate coordination service arrangements or agreements with the applicable Balancing Authority Area that addresses Generator Balancing Service Arrangements for all generating resources for which the entity is responsible within the applicable Balancing Authority Area;
- (b) committing sufficient additional unscheduled generating resources to the control of and dispatch by the applicable Balancing Authority Area operator that are capable of supplying energy not supplied by Interconnection Customer's scheduled Generating Facility, and entering into an appropriate coordination services agreement with the applicable Balancing Authority Area that addresses

Generator Balancing Service Arrangements obligations for the Generating Facility;

- (c) entering into an arrangement with another Balancing Authority Area to dynamically schedule Interconnection Customer's Generating Facility out of the applicable Balancing Authority Area and into such other Balancing Authority Area;
- (d) entering into an agreement for Generator Imbalance Service under Schedule 10 of Transmission Provider's Tariff; or
- (e) in the event the load/generation balancing function of the applicable Balancing Authority Area is accomplished through the function of its market structures approved by FERC, by entering into an arrangement consistent with such FERC-approved market structure.

In the event Interconnection Customer fails to demonstrate to Transmission Provider that it has otherwise complied with this Section 3, to the extent generator balancing service is necessary, Interconnection Customer shall be deemed to have elected to enter into an agreement for Generator Imbalance Service under Schedule 10 of Transmission Provider's Tariff.

4. Monthly Administration Charge:

In accordance with the activities and costs as described below, Interconnection Customer shall pay Transmission Provider a Monthly Administration Charge of \$5,000 for costs and expenses incurred by Transmission Provider for ongoing coordination, communication, planning, and administration required for parallel operations.

Transmission Provider may revise the amount of the Monthly Administration Charge on an annual basis by making a filing in accordance with Article 14.

Beginning sixty (60) Calendar Days after execution of this Agreement and continuing until the actual initial synchronization, the Monthly Administration Charge covers the following activities:

- Activities related to verification and logging of generation operational data:
 - Setup of data telemetry to Southern Companies' Energy Logging Data System (ELDS), and
 - Setup of power quality meter data telemetry;
- Activities related to Operations Center Communication:
 - Setup of real-time communication between Generator Operators and Transmission Operators (particularly GenComm), and
 - Training of Generator Operators in use of GenComm;
- Activities related to Operational Planning:
 - Review of modifications to Facility design and equipment specifications,
 - Validation of final generator steady-state and dynamic models, and

- Incorporation of generator models to Southern Companies' transmission planning base cases;
- Energy Management System Support:
 - Addition of generator and real-time data telemetry to Southern Companies' EMS;
- Monthly billing and data transfer:
 - Invoicing, payments, and handling of security; and
- Management oversight and involvement for Generator Interconnection Agreement:
 - Drafting and review of Operating Protocols & Procedures document,
 - Verification of generator's ability to operate to meet transmission requirements (e.g., voltage schedule, power quality), and
 - Management of generator interconnection pre-sync and pre-COD process.

Following the actual Initial Synchronization Date, the Monthly Administration Charge covers the following activities:

- Coordination of Facility operations with Transmission Provider's Transmission System:
 - Coordination of day-ahead operating schedules with Transmission Operations,
 - Coordination of voltage schedules with Transmission Operations,
 - Coordination of planned outages,
 - Coordination of response to unplanned outages, curtailments, or System Emergencies,
 - Coordination of updates to Generating Facility modeling data,
 - Coordination of updates to Operating Protocols & Procedures, and
 - Review of EMS data or Power Quality (PQ) meter data as needed for event analysis; and
- Monthly billing and data transfers:
 - Invoicing, payments, and handling of security.

5. Annual Operation and Maintenance Expenses per the provisions of Article 10 of this Agreement:

The current process used by Transmission Provider for determination and collection of operation and maintenance expenses is set forth below. Transmission Provider may change its process in the future and such new process would become applicable upon agreement of the Parties or approval by FERC.

(a) Payment of Expense of Owning, Operating, and Maintaining the Interconnection Facilities.

(i) Transmission Provider shall ensure Interconnection Facilities are operated and maintained in accordance with Good Utility Practices and in a non-discriminatory manner.

(ii) The estimated annual operation and maintenance expenses for Transmission Provider's Interconnection Facilities shall be determined per the provisions of this Section 5 of Appendix C. Transmission Provider, in its reasonable discretion, shall develop an estimate of all operating and maintenance expenses to be paid by Interconnection Customer for Transmission Provider's Interconnection Facilities on an annual basis and provide such estimate to Interconnection Customer at least eight (8) weeks before January 1 of the effective year. Interconnection Customer shall pay one-twelfth (1/12) of the applicable annual estimated expenses each month in accordance with Article 12. In addition, Interconnection Customer shall pay its pro rata share of all costs reasonably incurred by Transmission Provider (excluding any such costs reimbursed to Transmission Provider through insurance proceeds) to repair and restore Transmission Provider's Interconnection Facilities caused by any Force Majeure event upon receipt of an invoice in accordance with Article 12.

(iii) Transmission Provider shall true-up the applicable estimate to Transmission Provider's actual expenses within a reasonable period of time after such actual expenses are known but not less often than annually. In the event that the actual expenses to be paid by Interconnection Customer under this Section 5 of Appendix C are more or less than Transmission Provider's initial estimate, the difference (either a credit or an additional charge) shall be reflected on a subsequent invoice.

(b) Cost Support for Operation & Maintenance Charges.¹

The inputs set forth in this Section 5 of Appendix C are used to calculate charges to reimburse Transmission Provider for owning, operating, and maintaining Interconnection Facilities. Transmission Provider will recover charges for operation and maintenance activities through invoices to Interconnection Customer that reflect costs incurred in the following eight categories:

1. Labor²
2. Materials³
3. Transportation⁴
4. Data Acquisition⁵

¹ For additional information, see *Southern Company Services, Inc.*, 112 FERC ¶ 61,145 (2005) and FERC Docket Nos. EL05-53 and ER05-129.

² Includes the following employee-related overhead costs: direct labor charges, payroll taxes, federal, state, and local taxes, pension and insurance, pay incentives and direct payroll benefits.

³ Includes storage and handling of materials.

⁴ Derived by applying a transportation usage rate. Monthly costs for vehicles owned by Transmission Provider cover fuel, maintenance, repairs and depreciation. If the vehicles are leased, the costs are the lease fees.

⁵ Equipment used to capture real-time operational data pertaining to Interconnection Facilities.

5. Supervision, Engineering⁶, and Support⁷
6. Control Center⁸
7. Property Insurance
8. Taxes⁹

The costs incurred by Transmission Provider in connection with owning, operating, and maintaining Interconnection Facilities are the kinds of costs that would be assignable to the following FERC Uniform System of Accounts:

I. Direct Operation and Maintenance Costs.

- 562 Station expenses (Major only).
- 563 Overhead line expenses (Major only).
- 566 Miscellaneous transmission expenses (Major only).
- 569 Maintenance of structures (Major only).
- 570 Maintenance of station equipment (Major only).
- 571 Maintenance of overhead lines (Major only).
- 926 Employee pensions and benefits.

II. Indirect Operation and Maintenance Costs.

- 556 System Control and load dispatching.
- 557 Other expenses.
- 560 Operation supervision and engineering.
- 561 Load dispatching (Major only).
- 568 Maintenance supervision and engineering (Major only).
- 920 Administrative and general salaries.
- 921 Office supplies and expenses.
- 923 Outside services employed.
- 926 Employee pensions and benefits.

III. Other Costs.

- 408.1 Taxes other than income taxes, utility operating income.
- 408.2 Taxes other than income taxes, other income and deductions.

⁶ Includes costs such as project management and supervision of activities, maintenance scheduling, voltage control, switching and line monitoring.

⁷ Costs associated with employee salaries and benefits, general office expenses and building maintenance and operations expenses.

⁸ Transmission System control center, energy management systems and electronic monitoring equipment (collectively, “Control Center”). This includes costs related to personnel (such as grid operators) who work in these areas. A portion of the total charges is allocated to the generator using a line-termination ratio.

⁹ Includes Ad Valorem taxes.

Exhibit 1 of Appendix C

Voltage Schedules at the Point of Interconnection

Commencing with the initial synchronization of the Generating Facility, Interconnection Customer shall maintain voltage schedules at the Point of Interconnection as communicated by Transmission Provider from time to time. Typical voltage schedules are demonstrated in this exhibit, and the initial voltage schedules for the Generating Facility will be provided by Transmission Provider prior to initial synchronization.

Schedule #1 - Southern Balancing Authority Area Maximum Load for the day greater than 37,000 MW

Operating Time	New 24C-IC-1224/1225 230 kV Interconnecting Substation
00:01 - 06:00	238 kV
06:01 - 09:00	239 kV
09:01 – 21:00	240 kV
21:01 – 24:00	239 kV

Schedule #2 - Southern Balancing Authority Area Maximum Load for the day between 30,000 and 37,000 MW

Operating Time	New 24C-IC-1224/1225 230 kV Interconnecting Substation
00:01 - 06:00	237 kV
06:01 - 12:00	238 kV
12:01 – 21:00	239 kV
21:01 – 24:00	238 kV

Schedule #3 - Southern Balancing Authority Area Maximum Load for the day between 25,000 and 30,000 MW

Operating Time	New 24C-IC-1224/1225 230 kV Interconnecting Substation
00:01 - 06:00	237 kV
06:01 - 18:00	238 kV
18:01 – 21:00	238 kV
21:01 – 24:00	237 kV

Schedule #4 - Southern Balancing Authority Area Maximum Load for the day below 25,000 MW

Operating Time	New 24C-IC-1224/1225 230 kV Interconnecting Substation
00:01 - 06:00	237 kV
06:01 - 18:00	237 kV
18:01 – 21:00	238 kV
21:01 – 24:00	237 kV

Exhibit 2 of Appendix C

Single-Line Diagram for Generating Facility and 24C-IC-1224/1225 230 kV Interconnecting Substation

- Existing Transmission Facilities
- 24C-IC-1224 Interconnecting Facilities & Interconnecting Upgrades
- 24C-IC-1225 Interconnecting Facilities & Interconnecting Upgrades




Exhibit 3 of Appendix C

Initial Synchronization Requirements

Interconnection Customer shall coordinate with Transmission Provider to complete all requirements necessary for the initial synchronization of the Generating Facility to the electric system. This Exhibit 3 of Appendix C includes a general list of initial synchronization requirements and modeling data to be provided prior to initial synchronization of the Generating Facility. A schedule of the requirements and milestones (e.g., updated Generating Facility modeling data) to be completed prior to initial synchronization of the Generating Facility will be provided to Interconnection Customer sixty (60) Calendar Days after execution of this Agreement. Transmission Provider's list of Generating Facility data required prior to initial synchronization may be found in the Generator Interconnection folder on Transmission Provider's OASIS website at: <https://www.oasis.oati.com/SOCO>.

In general, the initial synchronization requirements include:

- Generating Facility physical design submittal and compatibility review;
- Updated Generating Facility modeling data submittal milestones;
- Interconnection protection relaying coordination and testing;
- Point of Interconnection metering installed;
- Retail service metering installed;
- Data telemetry installed and verified;
- Transmission Provider's EMS (and other operational tools) updated;
- Voice communications and GenComm setup and tested;
- Operating Protocols and Procedures document complete and reviewed; and
- Affected System upgrades complete (if applicable).

Prior to initial synchronization, Transmission Provider will provide Interconnection Customer with Transmission Provider's "Operating Protocols and Procedures" document for interconnected generators. Interconnection Customer will comply with the operating and technical requirements of Transmission Provider's "Operating Protocols and Procedures" document for interconnected generators in order to ensure the safe and reliable operation of the electric system and compliance with any Applicable Reliability Standards.

After all initial synchronization requirements have been completed and at least ten (10) Calendar Days prior to the Initial Synchronization Date, Interconnection Customer shall provide notice to Transmission Provider regarding its readiness to synchronize the Generating Facility to the electric system. Promptly following such notice, Transmission Provider shall evaluate the synchronization of the Generating Facility to the electric system in order to ensure the safe and reliable operation of the electric system. Initial synchronization shall not occur without the prior written confirmation from Transmission Provider that the Generating Facility may be synchronized to the electric system.

Exhibit 4 of Appendix C

Commercial Operation Requirements

1. Pre-Commercial Operation Requirements:

Interconnection Customer shall coordinate with Transmission Provider to complete all requirements necessary for Commercial Operation of the Generating Facility. This Exhibit 4 of Appendix C includes a general list of pre-commercial requirements and modeling data to be provided prior to Commercial Operation of the Generating Facility. A schedule of the requirements and milestones (e.g., updated Generating Facility modeling data) to be completed prior to Commercial Operation of the Generating Facility will be provided to Interconnection Customer sixty (60) Calendar Days after execution of this Agreement. Transmission Provider's list of Generating Facility data required prior to Commercial Operation may be found in the Generator Interconnection folder on Transmission Provider's OASIS website at: <https://www.oasis.oati.com/SOCO>.

In general, requirements for Commercial Operation of the Generating Facility include:

- Submittal of final Generating Facility dynamic modeling data (including final control settings);
- Validation of modeling data by comparison to test results;
- Verification of plant's ability to meet operational requirements (e.g., voltage, power quality, reactive power) at full load;
- Additional Generating Facility data, including telemetry and historical data, verified (see Appendix C, Section 2(b)); and
- Final plant commissioning report.

2. Completion of Requirements and Performance Validation Process:

The period between the In-Service Date and Commercial Operation Date (e.g., Trial Operation) must allow sufficient time for: (i) Interconnection Customer to complete activities related to commissioning the Generating Facility (e.g., the Generating Facility is synchronized, tuning/programming has been completed, and normal, stable plant operations have been achieved), and (ii) Transmission Provider's pre-COD operational performance validation process ("Pre-COD Operational Validation"). Further, the Pre-COD Operational Validation must be completed prior to Transmission Provider declaring the Generating Facility ready for Commercial Operation. The Pre-COD Operational Validation is estimated to take a minimum of six (6) weeks to complete after all Interconnection Customer pre-commercial operation activities and unit testing have been completed. Interconnection Customer must ensure there is sufficient time prior to the expected Commercial Operation Date for the Pre-COD Operational Validation to be completed after all inverters are synchronized, tuning/programming has been completed, and normal, stable plant operations are achieved. Once all such requirements have been completed and Transmission Provider has completed its Pre-COD Operational Validation, Transmission Provider will give written confirmation to Interconnection Customer that the Generating Facility may commence Commercial Operation.

Interconnection Customer may not commence Commercial Operation prior to receipt of such written confirmation from Transmission Provider.

The Commercial Operation Date shall not be before the date that Transmission Provider completes its Pre-COD Operational Validation.

Tariff Record Data:

Record Content Description	Appendix D
Tariff Record Title	Security Arrangements Details
Record Version Number	0.0.0
Option Code	A
Record Narrative Name	
Tariff Record ID	3823
Tariff Record Collation Value	283132032
Tariff Record Parent Identifier	3819
Proposed Date	2025-06-06
Priority Order	1000000000
Record Change Type	NEW
Record Content Type	1
Associated Filing Identifier	

Appendix D to LGIA

Security Arrangements Details

Infrastructure security of Transmission System equipment and operations and control hardware and software is essential to ensure day-to-day Transmission System reliability and operational security. FERC will expect all Transmission Providers, market participants, and Interconnection Customers interconnected to the Transmission System to comply with the recommendations offered by the President's Critical Infrastructure Protection Board and, eventually, best practice recommendations from the electric reliability authority. All public utilities will be expected to meet basic standards for system infrastructure and operational security, including physical, operational, and cyber-security practices.

Tariff Record Data:

Record Content Description	Appendix E
Tariff Record Title	Commercial Operation Date
Record Version Number	0.0.0
Option Code	A
Record Narrative Name	
Tariff Record ID	3824
Tariff Record Collation Value	283132064
Tariff Record Parent Identifier	3819
Proposed Date	2025-06-06
Priority Order	1000000000
Record Change Type	NEW
Record Content Type	1
Associated Filing Identifier	

Appendix E to LGIA

Commercial Operation Date

This Appendix E is a part of this Agreement between Transmission Provider and Interconnection Customer.

[Date]

Southern Company Services, Inc.
Attn: General Manager, Transmission Policy and Services
600 North 18th Street / BIN 13N-8812
Birmingham, AL 35203
Email: tscspinter@southernco.com

Re: _____ Large Generating Facility

Dear General Manager, Transmission Policy and Services,

On [Date] [Interconnection Customer] has completed Trial Operation of [Facility Name] (YY-IC-XXXX). This letter confirms that [Interconnection Customer] commenced Commercial Operation of [Facility Name] Large Generating Facility, effective as of [Date plus one day OR actual effective date].

Thank you.

[Signature]

[Interconnection Customer Representative]

Tariff Record Data:

Record Content Description	Appendix F
Tariff Record Title	Addresses for Delivery of Notices and Billings
Record Version Number	0.0.0
Option Code	A
Record Narrative Name	
Tariff Record ID	3825
Tariff Record Collation Value	283132096
Tariff Record Parent Identifier	3819
Proposed Date	2025-06-06
Priority Order	1000000000
Record Change Type	NEW
Record Content Type	1
Associated Filing Identifier	

Appendix F to LGIA

Addresses for Delivery of Notices and Billings

Notices:

Transmission Provider:

Southern Company Services, Inc.
Attn: General Manager, Transmission Policy and Services
600 North 18th Street / BIN 13N-8812
Birmingham, AL 35203
Email: tscspinter@southernco.com

With a copy to:

Alabama Power Company
Attn: Power Delivery Senior Vice President
600 North 18th Street / BIN 18N-0001
Birmingham, AL 35203

Interconnection Customer:

SR Stockton I, LLC
Attn: Nicholas Keesler, Senior Interconnection Project Manager
c/o Silicon Ranch Corporation
222 2nd Ave. S., Suite 1900
Nashville, TN 37201
Phone: (615) 577-4786
Email: nicholas.keesler@siliconranch.com and notices@siliconranch.com

With a copy to:

SR Stockton I, LLC
Attn: Richard A. Johnson, General Counsel
c/o Silicon Ranch Corporation
222 2nd Ave S, Suite 1900
Nashville, TN 37201
Phone: (615) 577-4786
Email: richard.johnson@siliconranch.com

Billings and Payments:

Transmission Provider:

Southern Company Services, Inc.
Attn: Manager, Wholesale Contracts
3535 Colonnade Parkway / S-420 EC
Birmingham, AL 35243
Facsimile: (205) 992-7756

Interconnection Customer:

SR Stockton I, LLC
Attn: Accounts Payable
c/o Silicon Ranch Corporation
222 2nd Ave. S., Suite 1900
Nashville, TN 37201
Phone: (615) 577-4786
Email: payables@siliconranch.com and invoicecapture@siliconranch.com

Alternative Forms of Delivery of Notices (telephone, facsimile or email):

Transmission Provider:

[To be supplied.]

Interconnection Customer:

SR Stockton I, LLC
Attn: Accounts Payable
c/o Silicon Ranch Corporation
222 2nd Ave. S., Suite 1900
Nashville, TN 37201
Phone: (615) 577-4786
Email: payables@siliconranch.com and invoicecapture@siliconranch.com

Tariff Record Data:

Record Content Description	Appendix G
Tariff Record Title	Interconnection Requirements for Wind Generating Plant
Record Version Number	0.0.0
Option Code	A
Record Narrative Name	
Tariff Record ID	3826
Tariff Record Collation Value	283132128
Tariff Record Parent Identifier	3819
Proposed Date	2025-06-06
Priority Order	1000000000
Record Change Type	NEW
Record Content Type	1
Associated Filing Identifier	

Appendix G to LGIA

Interconnection Requirements for a Wind Generating Plant

Appendix G sets forth requirements and provisions specific to a wind generating plant or a Generating Facility that contains a wind generating plant. All other requirements of this LGIA continue to apply to wind generating plant interconnections.

A. Technical Standards Applicable to a Wind Generating Plant

i. Low Voltage Ride-Through (LVRT) Capability

A wind generating plant shall be able to remain online during voltage disturbances up to the time periods and associated voltage levels set forth in the standard below. The LVRT standard provides for a transition period standard and a post-transition period standard.

Transition Period LVRT Standard

The transition period standard applies to wind generating plants subject to FERC Order 661 that have either: (i) interconnection agreements signed and filed with the Commission, filed with the Commission in unexecuted form, or filed with the Commission as non-conforming agreements between January 1, 2006 and December 31, 2006, with a scheduled in-service date no later than December 31, 2007, or (ii) wind generating turbines subject to a wind turbine procurement contract executed prior to December 31, 2005, for delivery through 2007.

1. Wind generating plants are required to remain in-service during three-phase faults with normal clearing (which is a time period of approximately 4 – 9 cycles) and single line to ground faults with delayed clearing, and subsequent post-fault voltage recovery to prefault voltage unless clearing the fault effectively disconnects the generator from the system. The clearing time requirement for a three-phase fault will be specific to the wind generating plant substation location, as determined by and documented by transmission

provider. The maximum clearing time the wind generating plant shall be required to withstand for a three-phase fault shall be 9 cycles at a voltage as low as 0.15 p.u., as measured at the high side of the wind generating plant step-up transformer(i.e. the transformer that steps the voltage up to the transmission interconnection voltage or “GSU”), after which, if the fault remains following the location-specific normal clearing time for three-phase faults, the wind generating plant may disconnect from the transmission system.

2. This requirement does not apply to faults that would occur between the wind generator terminals and the high side of the GSU or to faults that would result in a voltage lower than 0.15 per unit on the high side of the GSU serving the facility.
3. Wind generating plants may be tripped after the fault period if this action is intended as part of a special protection system.
4. Wind generating plants may meet the LVRT requirements of this standard by the performance of the generators or by installing additional equipment (e.g., Static VAr Compensator, etc.) within the wind generating plant or by a combination of generator performance and additional equipment.
5. Existing individual generator units that are, or have been, interconnected to the network at the same location at the effective date of the Appendix G LVRT Standard are exempt from meeting the Appendix G LVRT Standard for the remaining life of the existing generation equipment. Existing individual generator units that are replaced are required to meet the Appendix G LVRT Standard.

Post-transition Period LVRT Standard

All wind generating plants subject to FERC Order No. 661 and not covered by the transition period described above must meet the following requirements:

1. Wind generating plants are required to remain in-service during three-phase faults with normal clearing (which is a time period of approximately 4 – 9 cycles) and single line to ground faults with delayed clearing, and subsequent post-fault voltage recovery to prefault voltage unless clearing the fault effectively disconnects the generator from the system. The clearing time requirement for a three-phase fault will be specific to the wind generating plant substation location, as determined by and documented by transmission provider. The maximum clearing time the wind generating plant shall be required to withstand for a three-phase fault shall be 9 cycles after which, if the fault remains following the location-specific normal clearing time for three-phase faults, the wind generating plant may disconnect from the transmission system. A wind generating plant shall remain interconnected during such a fault on the transmission system for a voltage level as low as zero volts, as measured at the high voltage side of the wind GSU.
2. This requirement does not apply to faults that would occur between the wind generator terminals and the high side of the GSU.
3. Wind generating plants may be tripped after the fault period if this action is intended as part of a special protection system.
4. Wind generating plants may meet the LVRT requirements of this standard by the performance of the generators or by installing additional equipment (e.g., Static VAR Compensator) within the wind generating plant or by a combination of generator performance and additional equipment.

Existing individual generator units that are, or have been, interconnected to the network at the same location at the effective date of the Appendix G LVRT Standard are exempt from meeting the Appendix G LVRT Standard for the remaining life of the existing generation equipment. Existing individual generator units that are replaced are required to meet the Appendix G LVRT Standard.

ii. Power Factor Design Criteria (Reactive Power)

The following reactive power requirements apply only to a newly interconnecting wind generating plant that has executed a Facilities Study Agreement as of the effective date of the Final Rule establishing the reactive power requirements for non-synchronous generators in Article 9.6.1 of this LGIA (Order No. 827). A wind generating plant to which this provision applies shall maintain a power factor within the range of 0.95 leading to 0.95 lagging, measured at the Point of Interconnection as defined in this LGIA, if Transmission Provider's Cluster Study shows that such a requirement is necessary to ensure safety or reliability. The power factor range standard can be met by using, for example, power electronics designed to supply this level of reactive capability (taking into account any limitations due to voltage level, real power output, etc.) or fixed and switched capacitors if agreed to by Transmission Provider, or a combination of the two. Interconnection Customer shall not disable power factor equipment while the wind plant is in operation. Wind plants shall also be able to provide sufficient dynamic voltage support in lieu of the power system stabilizer and automatic voltage regulation at the generator excitation system if the Cluster Study shows this to be required for system safety or reliability.

iii. Supervisory Control and Data Acquisition (SCADA) Capability

The wind plant shall provide SCADA capability to transmit data and receive instructions from Transmission Provider to protect system reliability. Transmission Provider and the wind

plant Interconnection Customer shall determine what SCADA information is essential for the proposed wind plant, taking into account the size of the plant and its characteristics, location, and importance in maintaining generation resource adequacy and transmission system reliability in its area.